1. Introduction to the Agreement

The communication protocol is MODBUS-RTU protocol. This product only supports function codes 0x03, 0x06, 0x10; the communication interface is TTL serial port;

two. Introduction to communication protocols

Information transmission is asynchronous, Modbus-RTU mode is in 11-bit bytes.

Word format (serial data) 10-bit binary	
Start bit 1	
8 data bits	
No parity bit	
Stop bit 1 bit	

Data frame structure:

The data frame	Address	Function	data area	CRC check
interval is more than 3.5 bytes	code 1 byte	code 1 byte	N bytes	2 bytes

Before sending data, the data bus is required to be stationary, that is, no data transmission time is greater than 3.5 (for example: the baud rate is 9600 5ms) Message sending must start with a pause interval of at least 3.5 bytes, and the entire message frame must be used as a continuous Continuous data transmission stream, if there is a pause time of more than 3.5 byte times before the frame is completed, the receiving device will refresh Incomplete message and assumes the next byte is the address field of a new message. Likewise, if a new message arrives less than It starts after the previous message within 3.5 characters, and the receiving device will consider it as a continuation of the previous message.

1.1 Address code:

The address code is the first byte (8 bits) of each communication information frame, ranging from 1 to 255. This byte indicates the location set by the user The slave at the address will receive the information sent by the master. Each slave must have a unique address code, and only if it matches the address Only the slave machine with the address code can respond to the feedback information. When the slave sends back information, the data sent back start with their respective address codes. host The address code sent by the machine indicates the slave address to be sent, and the address code returned by the slave machine indicates the slave address sent back. Mutually The corresponding address code indicates where the information comes from.

1.2 Function code:

The function code is the second byte transmitted in each communication information frame. The function codes that can be defined by the ModBus communication protocol are 1 to

127. Sent as a host request, the function code is used to tell the slave what action it should perform. In response to the slave, the slave returns

The function code is the same as the function code sent from the host, and indicates that the slave has responded to the host and has performed relevant operations.

This machine only supports 0x03, 0x06, and 0x10 function codes.

function code	Define	Operation (binary)
0x03	reading register data,	Read data from one or more registers
0x06	writing a single register,	Write a set of binary data to a single register
0x10	writing multiple registers	Write multiple sets of binary data to multiple registers

1.3 Data area

The data area includes what kind of information needs to be sent back or what action needs to be performed by the slave. This information can be data (such as: start

(off input/output, analog input/output, register, etc.), reference address, etc. For example, the host uses function code

03 tells the slave to return the value of the register (including the starting address of the register to be read and the length of the read register), then return

The data returned includes the data length and data content of the register.

0x03 Read function host format

Address	Function code regist	er starting address Number of reg	ister addresses n (1~32) 1 byte 2 byte	CRC check code
code 1 byte		2 bytes		2 bytes

0x03 Read function slave return format

Address code fun	ction code returns	the number of registers	Number of registers	CRC check code
		n*2	according to	
1 byte 1 byte		1 byte 2*n words		2 bytes
			Festival	

0x06 Write single register function host format

Address	Function code regist	er starting address 1 byte 2	Register data 2	CRC check code
code 1 byte	byte		bytes	2 bytes

0x06 Write single register function slave return format

Address code functi	on code register starting addre	ss 1 byte 1 byte 2 byte	Register data 2	CRC check code
			bytes	2 bytes

0x10 Write multiple register function host format

Address code	Function code regist	er start	Number of register addresses	Number of bytes written	Register data CRC ca	libration
address			n(1~32)	2*n		Code verification
1 byte	1 byte	2 bytes	2 bytes	1 byte 2*n byte 2 b	yte	

0x10 Write multiple registers slave host format

Address	Function code regis	ter starting address Number of regi	ster addresses n (1~32) 1 byte 1 byte	CRC check code
code 1 byte		2 bytes		2 bytes

Factory default baud rate 115200 device address 1

Introduction to protocol registers (the data in a single register address is double-byte data)

VAETvariage antic22VR.W00.000001SETConcertang23AR.W10.000011SETConcertang datayoat23AR.W20.00002IDUTControl and variage22NR40.00001POWEControl and variage22NR40.00001POWEControl and variage data yout22NR40.00001POWEControl and variage data yout20NKR50.00001ALLOWControl and variage data yout20NKR60.00001ALLOWControl and variage data yout20NKR80.00001MHCWControl and variage data yout20NKR80.00001VMHCWControl and variage data yout20NKR100.00001OUT, MState from and variage20NR110.00001OUT, SAnge data yout21FCR1120.00001OUT, Sstate from and variage20NR110.00001OUT, Sstate from and variage20NR110.00001OUT, Sstate from and variage20NR110.0001OUT, Sstate from and variage20NR11
ISETConstraint23AR/W100001VOUTDependences states22VR20.0002DUTDependences states23AR30.00031POMROrganization states22NR40.00034UNDependences states22NR40.00034UNDependences states20NKR60.00056AHLONDependences states20NKR60.00056AHLONDestates states20NKR90.00037WHIGNDestates states20NKR90.00036OUT_HBis mack offer20NKR100.00036OUT_KBis mack offer20MR110.00067OUT_SBis mack offer20MR110.00067OUT_SBis mack offer20MR110.00067CNLSBis mack offer20R130.0007CNLSBis mack offer20R140.00067CNLSBis mack offer20R140.00067CNLSBis mack offer20R140.00067CNLSBis mack offer20R140.00067CNLSBis mack offer2 <td< td=""></td<>
VOUTOut_Antials distribute222VR2000000000000000000000000000000000
IOUTCatal manuclasing alar23ARR3060033POVERCatal manuclasing alar22WR400001INNreport whys stratego yam22VR5000035Alt-COWCatal Control Netword20InKR00.60007MHICONCatal Control Netword20InKR00.60007WHICONUser Storage Wright Wright20Integ890.60007WHICONUser Storage Wright Wright20Integ890.60007UHINONUser Storage Wright Wright20Integ890.60007OUT_NManuscrister20Integ8100.60001OUT_SManuscrister20Integ8100.60001TLNGeords rinna20Integ110.60001TLNGeords rinna20Integ140.60001TLNGeords rinna20Integ140.60001CCCgata instant20Integ140.60001TLNGeords rinna20Integ140.60001TLNGeords rinna20Integ140.60001TLNGeords rinna20IntegR140.60001TLNGeords rinna20IntegR
PONER Contact poor shoary outa. 2 2 N R 4 00004 UN Fort steps engry sub. 2 2 V R 5 00005 AHLOW Contact that is a load and 2 0 MK R 6 000005 MH410H Mrth field court MM 2 0 MK R 6 000007 MH410H Mrth field court MM 2 0 MK R 8 0.0003 OUT_H Mre mode with 2 0 H R 10 0.0000A GUT_H Mre mode with 2 0 M R 11 0.0000A GUT_H Mre mode with 2 0 S R 12 0.0000C GUT_H Mre mode with 2 0 S R 12 0.0000C T_LN associate 2 0 S R 13 0.0000F DNC pestat wate 2 </td
UN Instruction strayman 2 2 V R 5 0.0008 AH-LOW Dapa AH Low strayman 2 0 Intk R 6 0.0008 AH-LAN Antigen test trade with 2 0 Intk R 7 0.00087 WH-LOW Law Schmaux WH-spin 2 0 WW and R 8 0.00087 WH-LOW Law Schmaux WH-spin 2 0 WW and R 9 0.0009 OUT_H Him -sharabat 2 0 M R 10 0.0000 OUT_S Another branch 2 0 S R 11 0.0000 CLT_S weign branch 2 0 S R 14 0.0000 T_N accord branch 2 0 S R 17 0.0000 T_CN edita track 2 0 S R 14 0.0001 DCK edita track <t< td=""></t<>
AHLOW OgeA ALLOW SERCUPA 2 0 MK R 6 0.00006 AHHLOH Alting 156 ready //m 2 0 MK R 7 0.0007 WH-COM Lee 16th date //m high 2 0 wayn R 6 0.00056 UM-HCH Make free-Iverand 2 0 wayn R 6 0.00057 UM-HCH Make free-Iverand 2 0 WH 8 10 0.00050 CUT_H Max-mean or also 2 0 M R 11 0.00050 OUT_S Macroand stream 2 0 S R 13 0.00000 T_N and main orpanian 2 1 F/C R 14 0.00051 LOCK protecta 12 0 R 14 0.00013 CVCC value lastin 2 0 R 17 0.0011 CVCC value lastin 2 0
Al+HGHM High Holt way (M)20HKR70.0007WH-LOWLow (Heth days (M) High20WayR80.0008WH-HGH16 det name alway and20WayR90.0009OUT_HHenhaus alway20HR100.0000AOUT_M-decents inernal20MR110.0000AOUT_M-decents inernal20MR110.0000AOUT_Simperator value20SR120.0000CT_INelectral inernal20SR140.0000ELOCKpatiedon20IRW160.0000FLOCKpatiedon20IRW160.0001CVCCvalue oroland20IRW160.0001CVCCvalue oroland20IRW180.0001CVCCvalue oroland20IRW190.0011ELEDtemperator space20IRW190.0011ELEPbasing and20IRW100.0011SLAFEADOmodel intras20IRW100.0011SLAFEADOmodel intras20IRW100.0011ELEPbasing and and control20IRW100.0016
WH4.0WLet (Et odp XWH kg)20xxyaR80.0008WH4H0H156 to (ma - tox set)20woyaR90.0009OUT_Hme - maxa on ma20HR100.0000AOUT_M-Secosia bainsal20MR110.0006CUT_N-Secosia bainsal20SR120.000CT_IN-secosia bainsal20SR120.000CT_EXwise kg (xk)21F/CR140.000EIOCKprotection20-RW160.000FCVCCvise kg (xk)20-RW160.000FCVCCwise kg (xk)20-RW160.000FCVCCvise g (xk)20-RW160.000FCVCvise g (xk
WH-HKBHIbot on time - nour time20wwyaR90.0009OUT_Hifter - niture or time20HR100.000AOUT_M-decords internal20MR110.000BOUT_Surgenoses value20MR110.000DT_INestand tangenose21F/CR130.000DT_EKvalue tangenose21F/CR140.000ELOCKpatterin20-R/W160.0001CVCCvalue tangenose20-R/W180.0001CVCCvalue sexth20-R/W180.0001CVCCvalue sexth20-R/W180.0001CVCCvalue sexth20-R/W180.0001CVCCvalue sexth20-R/W180.0001CVCCvalue sexth20-R/W190.00013CVCCvalue sexth20-R/W190.00013CVCCvalue sexth20-R/W190.00014CVCCvalue sexth20-R/W190.00015CVCCvalue sexth20-R/W190.00015SLEPtexibil20-R/W20.00016VERSI
OUT_Htes:mate at see20HR100.000AOUT_MSeourds transl20MR110.000BOUT_SWormaar wat20SR120.000CT_Nederal dropenace21F/CR140.000BLCKwite ky tox20F/CR140.000DLCKpretcén20F/CR140.000DLCKpretcén20F/CRW150.000DCVCviteg containt areau20RW160.0001CVCviteg containt areau20RW160.0001CVCviteg containt areau20RW170.0001CVCviteg containt areau20RW180.0012CVCviteg containt areau20RW190.0001CVCviteg containt areau20RW190.0001CVCviteg containt areau20RW190.0001SLEPbackaft20MRW190.0001SLEPbackaft20KRW20.0001SLEPbackaft20KRW20.0001SLEPbackaft20KRW20.0001SLEPbackaft20KRW20.0001<
OUT_M Seconds Nemal 2 0 M R 11 DADMA OUT_S terpersate value 2 0 S R 12 0000C T_IN abord terpersate value 2 1 F/C R 13 00000C T_EX state values 2 1 F/C R 144 0x0000 DOCK protection 2 0 - RW 155 0x0000 PROTECT state denote 2 0 - RW 18 0x0010 CVCG value sendut 2 0 - RW 18 0x0011 ONOFF intel sendut 2 0 - RW 190 0x0011 SLEEP social information pronte 2 0 M R 0x0016 VERSION zenotist means 2 0 - RW 0x0016 SLAPE ADD most termans
Distribution Instruction Instruction <thinstruction< th=""> <thinstruction< th=""></thinstruction<></thinstruction<>
Tab extent temperature 2 1 F/C R 13 0x0000 T_EX value key tok 2 1 F/C R 14 0x000E LOCK posteten 2 0 I F/C R 14 0x000E LOCK posteten 2 0 I R/W 15 0x000F PROTECT statis constant 2 0 I R 17 0x0011 ONOFF statis constant current 2 0 I R/W 18 0x0012 FC oikuk sotton 2 0 I R/W 18 0x0013 BLED issignet lane sotton 2 0 I R/W 19 0x0016 SLEF bicklost statis sotton 2 0 R/W I 0x0016 SLMEED bicititititititititititititititititititi
Land Value Mark 2 1 F/C R 14 Ox000E LOCK protection 22 0 - R/W 15 0x000F PROTECT state surfaurt 22 0 - R/W 16 0x000F CVCC value carcentari carent 2 0 - R/W 16 0x000F CVCC value carcentari carent 2 0 - R/W 18 0x0011 ONOFF state subth 2 0 - R/W 19 0x0013 BLED state subth 2 0 M R/W - 0x0014 SLEEP taxity 2 0 M R/W - 0x0015 MODEL bigitress kord 2 0 I/M R/W - 0x0017 SLEEP taxity 2 0 I/M R/W - 0x0017 SLAVE-ADD mote stare stadres 2
Lock protection 2 0 1 R/W 15 Ox0000 PROTECT status containt 2 0 1 R/W 16 0x0010 CVCC voltage containt current 2 0 1 R/W 16 0x0010 CVCC voltage containt current 2 0 1 R/W 18 0x0011 DNOFF status swton 2 0 1 R/W 18 0x0012 FC output output 2 0 1 R/W 19 0x0013 BLEDP batalogt 2 0 M R/W 20 0x0015 VERSION deventine poduct 2 0 M R/W 2 0x0017 SLAVE-ADD modent imment 2 0 I/W R/W 25 0x0019 T-NOFFSET number idevaldenes 2 0 I/W R/W 26 0x0011 DEVICE
PROTECT attiles content 2 0 1 R/W 16 0.x0010 CVCC valage content 2 0 1 R 17 0.x0011 DNOFF status content 2 0 1 R/W 184 0.x0011 DNOFF status content 2 0 1 R/W 184 0.x0013 FC oupit 2 0 1 R/W 194 0.x0013 BLED temperature synthal 2 0 1 R/W 194 0.x0014 SLEP backtght 2 0 1 R 0.x0016 VERSION screen time podat 2 0 1 R 0.x0017 SLAVEADD model timesate 2 0 1 R/W 2 0.x0017 SLAVEADD model timesate 2 0 1 R/W 2 0.x0017 SLAVEADD model timesate <
CVCC valage consider current 2 0 1 R 17 0x0011 ONOFF status souch 2 0 1 R/W 18 0x0012 FC ooput 2 0 1 R/W 19 0x0013 BLED imperature symbol 2 0 1 R/W 20 0x0014 SLEEP backsight 2 0 M R/W
DNOEFstatus switch201R180x0012PCoutput201R/W180x0013B-LEDtemperature symbol20NR/W190x0014SLEEPbackigh20MR/W200x0016MODELbigtimesis level20NR0x0015MODELbigtimesis level201R0x0016VERSIONscreen time product201R0x0017SLAVE-ADDmodel timware201R/W0x0017SLAVE-ADDindifferesis level201R/W0x0017SLAVE-ADDindifferesis level201R/W0x0017SLAVE-ADDindifferesis level201R/W0x0017SLAVE-ADDindifferesis level201R/W0x0018BALDRATE_Lversion201R/W260x0014SLAVE-ADDindifferesis level201R/W260x0014BALDRATE_Lversion201R/W260x0016BALDRATE_Lindifferesis level201R/W260x0016BALDRATE_Lindifferesis level201R/W300x0016BALDRATE_Lindifferesis
FC output 2 0 1 R/M 19 0.0013 BLED temperature symbol 2 0 1 R/W 20 0.0014 SLEEP backight 2 0 M R/W 20 0.00015 MODEL brightness level 2 0 M R/W 0.00015 VERSION screen time product 2 0 I R 0.00017 SLAVE-ADD model timester 2 0 I R 0.00017 SLAVE-ADD model timester 2 0 I R/W 0.00017 SLAVE-ADD model timester 2 0 I R/W 25 0.00018 BAUDRATE_L version 2 1 F/C R/W 26 0.00014 T-EX-OFFSET baud nete ternal 2 0 I R/W 28 0.00016 EXTROCH band te
BLED temperature symbol 2 0 1 1 1 1 0 000000 BLED temperature symbol 2 0 N R/W 20 0 <td< td=""></td<>
Interpretation operation Image: Construction Image: Construction<
MODELbrightness level201N.N.M.N. <t< td=""></t<>
INDECLDignities aventLIII
PLENCIANBartent me productPLONNCONOOONNOOO
Descriptionmodel immare100N/W1000BAUDRATE_Lversion20R/W250x0019T-IN-OFFSETnumber slave address21F/CR/W260x001AT-EX-OFFSETbaud rate internal21F/CR/W270x001BBUZZERtemperature20R/W280x001CEXTRACT-Mcorrection external20R/W290x001DDEVICEtemperature correction buzzer switch quick addrest or up devide statusCR/W300x001EMPPT-SWMPPT switch20R/W310x0021MPPT-Kmer querte correction tourser switch quick addrest or up devide statusR/W330x0021MPPT-SWMPT switch20R/W330x0021MPPT-Kmer querte querte correction buzzer switch quick addrest or up devide statusR/W330x0021MPPT-KMPT switch20R/W330x0021GW-SWconstant power switch20R/W350x0023GWconstant power switch20R/W350x0023GWconstant power switch20R/W350x0023GWconstant power switch20R/W350x0023GWconstant power s
BADDRATE_LVersion10R/WR/W2.50.00013T-IN-OFFSETnumber slave address21F/CR/W2.60.x001AT-EX-OFFSETbaud rate internal21F/CR/W2.70.x001BBUZZERtemperature20.'R/W2.80.x001CEXTRACT-Mcorrection external20.'R/W2.90.x001DDEVICEtemperature correction buzzer switch quick adjustment Oxiput data group devide status.'R/W3.00.x001EMPPT-SWMPPT switch20.'R/W3.10.x001FMPPT-KMPPT switch20.'R/W3.10.x0021BatFultul power cutoff current20.'R/W3.30.x0021CW-SWconstant power switch20.'R/W3.30.x0021CWconstant power switch20.'R/W3.30.x0021Current20.'R/W3.30.x0021CWconstant power switch20.'R/W3.40.x0022CWconstant power switch20.'R/W3.50.x0023CWconstant power switch20.'R/W3.50.x0023CWconstant power switch20.'R/W3.50.x0023CWconstant power switch111
Invertised tumber stave address111
PERCONCETbadd rate internal21P/CR/W210.0011BUZZERtemperature20R/W280.0010EXTRACT-Mcorrection external20R/W290.00010DEVICEtemperature correction buzzer switch quick adjustment Oxeput data group devide statusR/W300.0001EMPPT-SWMPPT switch20R/W310.0001EMPPT-KMPPT maximum power point coefficient20R/W320.00020BatFulfull power cut-oft current20R/W330.00021CW-SWconstant power value20R/W350.00023CWconstant power value1Internal
DD2LEIXtemperaturePOR/W20CX001CEXTRACT-Mcorrection external20NR/W290x001DDEVICEtemperature correction buzzer switch quick at struent odput data struent oup devide statusR/W300x001EMPPT-SWMPPT switch20NR/W310x001FMPPT-tKMPPT maximum power point coefficient20R/W320x0020BatFulfull power cut-off current20R/W330x0021CWconstant power switch20NR/W340x0022CWconstant power value20R/W350x0023Incl
EXTRACTIVITCorrection external20R/W230.00011DEVICEtemperature correction buzzer switch quick adjustment Osquet data group devige status'R/W300x001EMPPT-SWMPPT switch20'R/W310x001FMPPT-KMPPT maximum power point coefficient20'R/W320x0020BatFulfull power cut-off current20'R/W330x0021CW-SWconstant power switch20'R/W340x0022CWconstant power value20'R/W350x0023Import currentImport valueImport currentImport c
DE VICEtemperature correction buzzer switch quick adjustment Odeput data group devide statusCR/W3000001EMPPT-SWMPPT switch20·R/W310x001FMPPT-KMPPT maximum power point coefficient20·R/W320x0020BatFulfull power cut-off current20·R/W330x0021CW-SWconstant power switch20·R/W340x0022CWconstant power value20·R/W350x0023Import cut-off current20·R/W350x0023CWconstant power value20·R/W350x0023Import cut-off current1Import cut-off currentImport cut-off currentImport cut-off currentImport cut-off currentCWconstant power value20·R/W350x0023Import cut-off currentImport cut-off currentImport cut-off currentImport cut-off currentImport cut-off currentCWconstant power value20·R/W350x0023Import cut-off currentImport cut-off currentImport cut-off currentImport cut-off currentImport cut-off cut-off currentCWconstant power valueImport cut-off
MPPT-KMPPT maximum power point coefficient20IR/W310.00011BatFulfull power cut-off current20IR/W320.00021CW-SWconstant power switch20IR/W330.00021CWconstant power value20IR/W340.00022CWconstant power value20IR/W350.00023CWconstant power value20IR/W350.00023CUconstant power valueIIIIIIICUconstant power valueIIIIIIIICUconstant power valueIIIIIIIIICUconstant power valueIII
INFERMPPT maximum power point coefficient20R/W3200020BatFulfull power cut-off current20'R/W330x0021CW-SWconstant power switch20'R/W340x0022CWconstant power value20'R/W350x0023CWconstant power value1IIIIIICWconstant power value20'R/W350x0023CWconstant power valueIII
Bair of full power cut-off current20R/W3300021CW-SWconstant power switch20R/W340x0022CWconstant power value20R/W350x0023CWconstant power value20R/W350x0023CWconstant power valueCCCCCCWconstant power valueCCCCCCCWconstant power valueCCCCCCCWconstant power valueCCCCCCCWconstant power valueCCCCCCCWconstant power valueCCC<
CW-SWconstant power switch20R/W34000022CWconstant power value20rR/W350x0023CCC<
Covconstant power value20R/W5500025Image: Constant power valueImage:
MUSICIN HOST LYPE 2 0 0 R/W 48 0x0030 WIFLCONFIG Immunor surgery 2 0 0 DAM 40 0x0030
WiFI network distribution function Z U U K/W 49 UXU031 WiFI network distribution function Z U U K/W 49 UXU031
Ine first two bytes of the IP address 2 0 0 R/W 51 0x0033 IP\/d.l The first two bytes of the IP address 2 0 0 R/W 51 0x0033
I ne last two bytes of the IP address 2 0 0 K/W 52 0X0034
Votage setting 2 2 V R/W 80 0x0050
Current setting Z S A R/W 81 0x0051 SLIVE 2 2 3 A R/W 81 0x0051
Low voltage protection 2 2 2 V R/W 82 0x0052
value Overvoltage 2 2 V R/W 83 0x0053
protection value 2 3 A R/W 84 0x0054
Overcurrent protection Z 1 W R/W 85 0x0055
S-OHP_H value Overpower protection value 2 0 H R/W 86 0x0056
S-OHP_Hvalue Overpower protection value20HR/W860x0056S-OHP_MMaximum output duration - hours20MR/W870x0057S-OHP_MDDDDDDDD
S-OHP_Hvalue Overpower protection value20HR/W860x0056S-OHP_MMaximum output duration - hours20MR/W870x0057S-OAH_LMaximum output duration - minutes20htKR/W880x0058
S-OHP_Hvalue Overpower protection value20HR/W860x0056S-OHP_MMaximum output duration - hours20MR/W870x0057S-OAH_LMaximum output duration - minutes20htKR/W880x0058S-OAH_HMaximum output AH Low 16-bit20htKR/W890x0059
S-OHP_Hvalue Overpower protection value20HR/W860x0056S-OHP_MMaximum output duration - hours20MR/W870x0057S-OAH_LMaximum output duration - minutes20htKR/W880x0058S-OAH_HMaximum output AH Low 16-bit20htKR/W890x0059S-OWH_Lmaximum output AH High 16-bit2010mwHR/W900x005A
S-OHP_Hvalue Overpower protection value20HR/W860x0056S-OHP_MMaximum output duration - hours20MR/W870x0057S-OAH_LMaximum output duration - minutes20htKR/W880x0058S-OAH_HMaximum output AH Low 16-bit20htKR/W890x0059S-OWH_Lmaximum output AH High 16-bit2010mwHR/W900x005AS-OWH_Hmaximum output WH Low 16-bit2010mwHR/W910x005B
S-OHP_Hvalue Overpower protection value20HR/W860x0056S-OHP_MMaximum output duration - hours20MR/W870x0057S-OAH_LMaximum output duration - minutes20htKR/W880x0058S-OAH_HMaximum output duration - minutes20htKR/W890x0059S-OAH_HMaximum output AH Low 16-bit2010mwHR/W890x0059S-OWH_Lmaximum output AH High 16-bit2010mwHR/W900x005AS-OWH_Hmaximum output WH Low 16-bit2010mwHR/W910x005BS-OTPmaximum output WH20F/CR/W920x005C

Note 1: (0019H) Baud rate register meaning 0:9600 1:14400 2:19200 3:38400 4:56000 5:576000 6:115200 (7:2400 8:4800 supported by some devices)

Note 2: This product is designed with a total of 10 groups of storage data groups M0-M9, each group has a serial number of 20-2D, a total of 14 data, among which the M0 data group is the data group called by default when the product is powered on, and the M1 and M2 data groups are The product panel can quickly call up the data group. M3-M9 are ordinary storage arrays. The calculation method of the starting address of the data group is: 0050H + data group number * 0010H. For example, the starting address of the M3 data group is: 0050H+3*0010H=0080H.

Note 3: The read and write values of the key lock function are 0 and 1, 0 means non-locked, and 1 means locked.

Note 4: Protection status register:

0:Normal operation,1:OVP,2:OCP,3:OPP,4:LVP,5:OAH,6:OHP,7:OTP,8:OEP,9:OWH,10:ICP 11:ETP

0: Alarm code	1: OVP over voltage protecti	on 2: OCP over current protection	3: OPP over power protection
4: LVP input undervoltage protection	5: OAH maximum output capacity	6: OHP maximum output	7: OTP over temperature protection
protect	quantity	batwan	
8: OEP no output protection 9:	OWH maximum energy output	10: ICP maximum input power	11: ETP external temperature protection
	out	stream protection	protect

Note 5: The reading values of constant voltage and constant current state are 0 and 1, 0 is CV state, and 1 is CC state.

Note 6: The read and write values of the switch output function are 0 and 1, 0 is the closed state, and 1 is the open state.

Note 7: The reading and writing range of the backlight brightness level is 0-5, with level 0 being the darkest and level 5 being the brightest.

Note 8: The written value of the quick recall data group function is 0-9, and the corresponding data group data will be automatically recalled after writing.

Note 9: Description of WiFi related registers

name	Detailed	Register address
MASTER	description of host type (0x3B3A: WIFI, others to be determined)	0030H
WIFI-CONFIG WIFI pairing status (0: invalid 1: Touch pairing 2: AP pairing)		0031H
WIFI-STATUS WIFI status (: Invalid network 1: Connected to router 2: Successfully connected to server 3: Touch configuration	0032H
2	Pair 4:AP pairing)	
IPV4-H	The first two bytes of the IP address are 0xC0A8	0033H
IPV4-L	The last two bytes of the IP address are 0x0108	0034H

IPV4-H: 0xC0A8 IPV4-L: 0x0108

IPv4 = 192.168.1.8

1.4 Error check code (CRC check):

The host or slave can use the check code to determine whether the received information is correct. Due to electronic noise or some other interference, Errors sometimes occur during the transmission of information. The error check code (CRC) can check whether the host or slave is transmitting communication data. Whether the information in the sending process is wrong, wrong data can be discarded (whether sending or receiving), which increases the system system safety and efficiency. The CRC (redundant cyclic code) of the MODBUS communication protocol contains 2 bytes, which is a 16-bit binary number. The CRC code is calculated by the sending device (host) and placed at the end of the sent information frame. The device (slave) that receives the information then restarts Newly calculate the CRC of the received information, and compare whether the calculated CRC matches the received one. If the two do not match, then Indicates an error. The CRC check code is sent with the low bit first and the high bit last.

Calculation method of CRC code:

(1) Preset a 16-bit register to hexadecimal FFFF (that is, all 1); call this register a CRC register;

(2) Combine the first 8-bit binary data (the first byte of the communication information frame) with the lower 8 bits of the 16-bit CRC register

Bit-wise exclusive OR and put the result in the CRC register;

(3) Shift the contents of the CRC register one bit to the right (toward the lower bit), fill the highest bit with 0, and check the shifted-out bit after the right shift;

(4) If the shifted bit is 0: Repeat step 3 (shift one bit to the right again); if the shifted bit is 1: CRC register and multi-item

Formula A001 (1010 0000 0000 0001) performs XOR;

(5) Repeat steps 3 and 4 until the right shift is performed 8 times, so that the entire 8-bit data is processed;

(6) Repeat steps 2 to 5 to process the next byte of the communication information frame;

(7) After calculating all bytes of the communication information frame according to the above steps, the high and low values of the 16-bit CRC register obtained

Bytes are exchanged;

(8) The final content of the CRC register is the CRC code.

3. Communication examples

Example 1: The host reads the output voltage and output current display values.

The message format sent by the host:

The master	Number of bytes	Sent information	Remark
sends the slave	1	01	Sent to slave with address 01
address	1	03	Read register
function code register	2	0002H	Register starting address
starting address register address number	2	0002H	2 bytes in total
CRC code	2	65CBH	The CRC code is calculated by the host

For example, if the current display value is 05.00V, 1.500A, the message format returned by the slave is:

Slave response byte number	Slave address	Returned information	Remark
function code	1	01	from slave 01
read byte	1	03	Read register
number address	1	04	1 byte in total
is 0002H Register content address is	2	01F4H	Output voltage display value
0003H Register content CRC code	2	05DCH	Output current display value
	2	B8F4H	The CRC code is calculated from the slave machine

Example 2: The host needs to set the voltage to 24.00V

The message format sent by the host:

The master	Number of bytes	Sent information	Remark
sends the slave	1	01H	from slave 01
address	1	06H	Write to a single register
function code	2	0000H	Register address
register address 0000H. The content of the	2	0960H	Set output voltage value
register is the CRC code.	2	8FB2H	The CRC code is calculated by the host

The message format returned by the slave after receiving the response.

The slave	Number of bytes	Returned information	Remark
responds to the	1	01H	Sent to slave with address 01
slave	1	06H	Write to a single register
address function	2	0000H	Register starting address
code register. The address is 0000H. The contents of	the register are 2	0960H	Set output voltage value
CRC code	2	8FB2H	The CRC code is calculated from the slave machine

Example 3: The host needs to set the voltage to 24.00V and the current to 15.00A.

The message format sent by the host:

The master sends	Number of bytes	Sent information	Remark
the slave address,	1	01H	from slave 01
the function	1	10H	write register
code register, the starting	2	0000H	Register starting address
address, the number of register	2	0002H	2 bytes in total
addresses, the number	1	04H	1 byte in total
of bytes written, the address is 0000H, the content of	2	0960H	Set output voltage value
the register, the address is 0001H, the content of the	2	05DCH	Set output current value
register, the CRC code	2	F2E4H	The CRC code is calculated by the host

The message format returned by the slave after receiving the response:

			45
Slave response	Number of bytes	Returned information	Remarks:
slave address	1	01H	Send to the slave write register with
function	1	10H	address 01. The
code register starting	2	0000H	starting address of the
address register address number	2	0002H	register is a total of
CRC code	2	41C8H	2 bytes and the CRC code is calculated by the slave.