



• Start

USE	TYPE	STAGE	STOCK No.	COL.	C or L pF	IMP. Ohm	Qo	QL	Conn.
455 KHz IFT	10 E	1st	YMC-14600 A	Y	180+10	50K:500	110+20%	35+20%	1
		2nd	YMC-14601 A	W	"	30K:500	" -10%	" -10%	1
		3rd	YMC-14602 A	BK	"	15K: 5K	"	"	1
	7 E	1st	LMC-4100 A	Y	150+ 5	50K:500	105+20%	35+20%	1
		2nd	LMC-4101 A	W	"	30K:500	" -10%	" -10%	1
		3rd	LMC-4102 A	BK	"	15K: 5K	"	"	1
	10 E	1st	YOC-15000 A	Y	180+10	15K:150	60+20%	35+20%	1
		2nd	YOC-15001 A	W	"	35K:150	" -10%	" -10%	1
		3rd	YMC-15002 A	BK	"	37K:12K	110+20%	"	1
	7 E	1st	LPC-4200 A	Y	150+ 5	15K:150	60+20%	35+20%	1
		2nd	LPC-4201 A	W	"	35K:150	" -10%	" -10%	1
		3rd	LMC-4202 A	BK	"	37K:12K	105+20%	40+20%	1
455 KHz discr.	10 E	disc.P " S	WYHN-9202 PCR WYHN-9203 SDG	P BL	200(E)+10 1000(E)+10		140+20% 110±20%		5A 5B
10.7 MHz IFT	10 K	1st	KAN-2207 BM	V	50(E)+ 5	20K:300	100+20%	27+20%	2
		2nd3rd	KAC-6400 A	O	47+ 5	13K:350	90±20%	"	1
		disc.P	KAC-6401 PPF	P	27+ 5	12K: 3K	100+20%	25+20%	3A
		disc.S	KAC-6666 SZ	BL	68+ 0	12K	90±20%	35±20%	3B
	7 E	1st	85 AN-1715 BM	V	50(E)+ 5	20K:300	115+20%	30+20%	2
		2nd3rd	85 AC-3000 A	O	47+ 5	13K:350	105+20%	"	1
		disc.P	85 AC-3001 PPF	P	33+ 5	12K: 3K	100+20%	"	3A
		disc.S	85 FC-3002 SZ	BL	68+ 0	12K	105±20%	38±20%	3B
	10 K	1st2nd 3rd	KAC-6184 A	BK	82+ 5		65+20%		1
		disc.P	KAC-6185 PPF	P	33+ 5		68+20%		3A
		disc.S	KAC-6186 SZ	BL	56+ 0		78±20%		3B
	7 E	1st2nd 3rd	85 PC-2874 A	BK	82+ 5		60+20%		1
disc.P		85 PC-3100 PPF	P	27+ 5		"		3A	
disc.S		85 FC-1517 SZ	BL	56+ 0		105±20%		3B	
OSC.	10 E		YXR-18194 N	R	360 μH		>50		6
	7 E		LBR-5423 N	R	360 μH		>50		6
STEREO MPX COILS	10PA	SCA Trp	CAN-1896 HM	BK	22,0 mH		83+20%		7
		38 KHz doubl.	CAN-1979 A	W	11,75mH		47+20%		6
		19 KHz Amp.	CAN-1898 HM	O	7,00mH		42+20%		7
		19 KHz Osc/Amp	CAN-1980 BX	Y	7,00mH		42+20%		8

Y=yellow, W=white, BK=black, V=violet, O=orange, P=pink, BL=blue, R=red, E=External

Standard coils

