

SMD EIA-96 1%

Code	Value	Code	Value	Code	Value	Code	Value
1	100	25	178	49	316	73	562
2	102	26	182	50	324	74	576
3	105	27	187	51	332	75	590
4	107	28	191	52	340	76	604
5	110	29	196	53	348	77	619
6	113	30	200	54	357	78	634
7	115	31	205	55	365	79	649
8	118	32	210	56	374	80	665
9	121	33	215	57	383	81	681
10	124	34	221	58	392	82	698
11	127	35	226	59	402	83	715
12	130	36	232	60	412	84	732
13	133	37	237	61	422	85	750
14	137	38	243	62	432	86	768
15	140	39	249	63	442	87	787
16	143	40	255	64	453	88	806
17	147	41	261	65	464	89	825
18	150	42	267	66	475	90	845
19	154	43	274	67	487	91	866
20	158	44	280	68	499	92	887
21	162	45	287	69	511	93	909
22	165	46	294	70	523	94	931
23	169	47	301	71	536	95	953
24	174	48	309	72	549	96	976

Code	Multiplier
Z	1
Y or R	0.01
X or S	0.1
A	1
B or H	10
C	100
D	1000
E	10000
F	100000

Code examples:
01Y = $100 \times 0.01 = 1\Omega$
68X = $499 \times 0.1 = 49.9\Omega$
76X = $604 \times 0.1 = 60.4\Omega$
01A = $100 \times 1 = 100\Omega$
29B = $196 \times 10 = 1.96k\Omega$
01C = $100 \times 100 = 10k\Omega$