






BASED NEON GLOW LAMPS

Signalite Type		ASA#	Breakdon Voltage (max.) A.C.	Breakdon Voltage (max.) D.C.	Series Resistance (Ohms)	Rated Life Hours (Avg.)	Circuit Volts	Watts (Nom.)	Base	Bulb	Notes	Max. Overall Length Inches (mm)
NE2D		C7A	65	90	100,000	25,000	105-125	1/15	S.C. Midget Flange	T2	(1) (3) (5) (6)	15/16" (23.8)
NE2J		C9A	95	135	30,000	25,000	105-125	1/4	S.C. Midget Flange	T2	(1) (2) (3) (5)	15/16" (23.8)
NE3		8AA	65	90	200,000	15,000	105-125	1/25	Telephone Slide	T2 Round	(1) (3) (5) (7)	1-11/16" (42.7)
NE4		8AB	65	90	100,000	15,000	105-125	1/15	Telephone Slide	T2	(1) (3) (5) (7)	1-3/4" (44.5)
NE5		8AC	65	120	200,000	3,000	105-125	—	Telephone Slide	T2	(2) (3)	1-11/16" (42.7)
NE7		B4A	55	75	30,000	7,500	105-125	—	Wire Terminal	T4-1/2	(1) (3) (5) (8)	1-1/4" (31.75)
NE16		7AA	55	75	—	1,000	105-125	—	DC Bayonet	T4-1/2	(2) (3)	1-1/2" (38.1)
NE17		B5A	55	75	30,000	7,500	105-125	1/4	DC Bayonet	T4-1/2	(1) (3) (5)	1-1/2" (38.1)
NE21		B6A	55	75	30,000	7,500	105-125	1/4	SC Bayonet	T4-1/2	(1) (3) (5)	1-1/2" (38.1)
NE30		J6A	60	85	4,800	10,000	105-125	1	Medium Screw	S11	(3) (4)	2-3/16" (55.6)
NE32		L6A	60	85	4,800	10,000	105-125	1	DC Bayonet	G10	(1) (3) (5)	2-1/8" (54.0)
NE34		R2A	65	90	3,500	10,000	105-125	2	Medium Screw	S14	(3) (4)	3-1/2" (88.9)
NE40		R6A	65	90	2,200	10,000	105-125	3.5	Medium Screw	S14	(3) (4)	3-1/2" (88.9)
NE42		R9A	65	90	2,200	10,000	105-125	3.5	DC Bayonnet	S14	(3) (4)	3-5/16" (100.0)
NE45		B7A	65	90	30,000	7,500	105-125	1/4	Candle Screw	T4-1/2	(3) (4)	1-17/32" (38.9)
NE47		B8A	65	90	30,000	7,500	105-125	1/4	SC Bayonet	T4-1/2	(1) (3) (5)	1-1/2" (38.1)
NE48		B9A	65	90	30,000	7,500	105-125	1/4	DC Bayonet	T4-1/2	(1) (2) (3) (5)	1-1/2" (38.1)
NE51		B1A	65	90	200,000	15,000	105-125	1/25	Miniature Bayonet	T3-1/4	(1) (3) (5)	1-3/16" (30.2)
NE51H		B2A	95	135	47,000	25,000	105-125	1/7	Miniature Bayonet	T3-1/4	(2) (3) (5)	1-3/16" (30.2)
NE54		F2A	65	90	30,000	7,500	105-125	1/4	Wire Terminal	T4-1/2	(1) (3) (5)	1-1/4" (31.75)
NE56		4A	60	85	30,000	10,000	210-250	1	Medium Screw	S11	(3) (4)	2-3/16" (55.6)
NE57		F3A	55	75	30,000	7,500	105-125	1/4	Candle Screw	T4-1/2	(3) (4)	1-17/32" (38.9)
NE58		F4A	55	75	100,000	7,500	210-250	1/2	Candle Screw	T4-1/2	(3) (4)	1-17/32" (38.9)
NE79		R1A	65	90	7,500	10,000	105-125	1	DC Bayonet	S7	(3) (4)	2" (50.8)
NE84		K1A	95	135	30,000	25,000	105-125	1/4	Miniature Telephone Slide	T2	(1) (2) (3) (5)	1-1/32" (26.2)

Notes:

1. May be used on circuits of higher voltage provided proper external resistor is used.
2. High brightness lamps with a small amount of radio active additive to reduce dark effect.
3. D.C. life approximately 60% of A.C. values.
4. Resistor included in base.
5. External resistor, not included.
6. Meets Mil. Spec. MS25252.
7. Lamp must fall free through a .310" dia. cylinder ½" long.
8. For D.C. operation, center electrode is negative.