

Ansteuerung zum Programmieren:

ISP:

JTAGE ICE MK II (10 Pin)	ISP (6 Pin)	AT-Mega2560	Arduino Mega
Pin1 (TCK)	Pin 3 SCK	PB1 SCK	-Bild-
Pin2 (GND)	Pin 6 GND	Diverse GND	-Bild-
Pin3 (TDO)	Pin 1 MISO	PB3 MISO	-Bild-
Pin4 (VTref)	Pin 2 Vcc	Diverse Vcc	-Bild-
Pin6 (nSRST)	Pin 5 RESET	30 Reset	-Bild-
Pin9 (TDI)	Pin 6 MOSI	PB2 MOSI	-Bild-

ISP Stecker	Arduino Mega 2560 ISP
<p>ISP6PIN</p>	

Pin	JTAGE ICE MK II	AT-Mega2560	Arduino Mega
1	TCK	PF4 TCK	A4
2	GND	GND	GND
3	TDO	PF6 TDO	A6
4	VTref	Diverse ... Vcc	5V
5	TMS	PF5 TMS	A5
6	nSRST	30 RESET	RESET
7	-		---
8	nTRST	---	---
9	TDI	PF7 TDI	A7
10	GND	Diverse... GND	GND

Jtag Stecker ICE MK II	