

EX		K		ADDR										K	EX	Bereich	Bausteine	Funktion	Ort	
A15	A14	A13	A12	A11	A10	A9	A8	A7	A6	A5	A4	A3	A2	A1	A0					
0	0	0	0	0	0	x	x	x	x	x	x	x	x	x	0	0	0x0000 - 0x03FF	IC4/5 2114	RAM	Basisplatine
						0	0	x	x	x	x	x	x	x	x		0x0000 - 0x00FF	Zeropage		
						0	1	x	x	x	x	x	x	x	x		0x0100 - 0x01FF	Stack		
						1	0	x	x	x	x	x	x	x	x		0x0200 - 0x02FF	RAM P.2		
						1	1	x	x	x	x	x	x	x	x		0x0300 - 0x03FF	RAM P.3		
0	0	0	0	1	0	x	x	x	x	x	x	x	x	x	1	0	0x0400 - 0x07FF	IC2/3 2114	RAM	Interfaceplatine
						x	x	x	x	x	x	x	x	x	x	2	0	0x0800 - 0x0BFF	EPROM TM	Interfaceplatine
						0	1	x	x	x	x	x	x	x	x	3	0	0x0C00 - 0x0FFF		
						0	0	x	x	x	x	x	x	x	x	4	0	0x1000 - 0x13FF	IC5 2716	EPROM PM
0	0	1	0	1	0	x	x	x	x	x	x	x	x	x	5	0	0x1400 - 0x17FF	IC3 6522	VIA	Interfaceplatine
						x	x	x	x	x	x	x	x	x	x	0	0	0x1800 - 0x19FF	ORB	
						x	x	x	x	x	0	0	0	0	x			0x1800	ORA	
						x	x	x	x	x	0	0	0	1	x			0x1801	DDRB	
						x	x	x	x	x	0	0	1	0	x			0x1802	DDRA	
						x	x	x	x	x	0	0	1	1	x			0x1803	T1L-L/T1C-L	
						x	x	x	x	x	0	1	0	0	x			0x1804	T1C-H	
						x	x	x	x	x	0	1	0	1	x			0x1805	T1L-L	
						x	x	x	x	x	0	1	1	0	x			0x1806	T1L-H	
						x	x	x	x	x	0	1	1	1	x			0x1807	T2L-L/T2C-L	
						x	x	x	x	x	1	0	0	0	x			0x1808	T2C-H	
						x	x	x	x	x	1	0	0	1	x			0x1809	SR	
						x	x	x	x	x	1	0	1	0	x			0x180A	ACR	
						x	x	x	x	x	1	0	1	1	x			0x180B	PCR	
						x	x	x	x	x	1	1	0	0	x			0x180C	IFR	
						x	x	x	x	x	1	1	1	0	x			0x180D	IER	
						x	x	x	x	x	1	1	1	1	x			0x180E	ORA	
						0	1	0	1	0	1	0	1	1	0	0	0x1A00 - 0x1BFF	IC3 6532	RIOT	Basisplatine
																	0x1A00 - 0x1A7F	RAM		
																	0x1A80	PAD		
																	0x1A81	PADD		
																	0x1A82	PBD		
																	0x1A83	PBDD		
																	0x1AD4	IRQ DIS		
																	0x1AD5	READ FLAG		
																	0x1ADC	IRQ ENA		
																	0x1AE4	PA7IRQ DIS NEG EDET		
																	0x1AE5	PA7IRQ DIS POS EDET		
																	0x1AE6	PA7IRQ ENA NEG EDET		
																	0x1AE7	PA7IRQ ENA POS EDET		
																	0x1AF4	CLK1T IRQDIS		
																	0x1AF5	CLK8T IRQDIS		
																	0x1AF6	CLK64T IRQDIS		
																	0x1AF7	CLK1KT IRQDIS		
																	0x1AFC	CLK1T IRQENA		
																	0x1AFD	CLK8T IRQENA		
																	0x1AFE	CLK64T IRQENA		
																	0x1AFF	CLK1KT IRQENA		
0	0	1	1	1	1	x	x	x	x	x	x	x	x	x	7	0	0x1C00 - 0x1FFF	IC2 2708	EPRON - Monitor	Basisplatine
						1	1	1	1	1	1	0	1	0	x	0xFFFFA	NMIL	0x2F		
						1	1	1	1	1	1	1	0	1	x	0xFFFFB	NMIH	0x1F		
						1	1	1	1	1	1	1	1	0	x	0xFFFFC	RESL	0x1D		
						1	1	1	1	1	1	1	1	0	x	0xFFFFD	RESH	0x1C		
						1	1	1	1	1	1	1	1	1	x	0xFFFFE	IRQL	0x32		
						1	1	1	1	1	1	1	1	1	1	0xFFFFF	IRQH	0x1F		