

2N109	GE-P	35V	0.15A	0.165W	
2N1304	GE-N	25V	0.3A	0.15W	10MHz
2N1305	GE-P	30V	0.3A	0.15W	5MHz
2N1307	GE-P	30V	0.3A	0.15W	B>60
2N1613	SI-N	75V	1A	0.8W	60MHz
2N1711	SI-N	75V	1A	0.8W	70MHz
2N1893	SI-N	120V	0.5A	0.8W	
2N2102	SI-N	120V	1A	1W	<120MHz
2N2148	GE-P	60V	5A	12.5W	
2N2165	SI-P	30V	50mA	0.15W	18MHz
2N2166	SI-P	15V	50mA	0.15W	10MHz
2N2219A	SI-N	40V	0.8A	0.8W	250MHz
2N2222A	SI-N	40V	0.8A	0.5W	300MHz
2N2223	2xSI-N	100V	0.5A	0.6W	>50
2N2223A	2xSI-N	100V	0.5A	0.6W	>50
2N2243A	SI-N	120V	1A	0.8W	50MHz
2N2369A	SI-N	40V	0.2A	.36W	12/18ns
2N2857	SI-N	30V	40mA	0.2W	>1GHz
2N2894	SI-P	12V	0.2A	1.2W	60/90ns
2N2905A	SI-P	60V	0.6A	0.6W	45/100
2N2906A	SI-P	60V	0.6A	0.4W	45/100
2N2907A	SI-P	60V	0.6A	0.4W	45/100
2N2917	SI-N	45V	0.03A		>60Mz
2N2926	SI-N	25V	0.1A	0.2W	300MHz
2N2955	GE-P	40V	0.1A	0.15W	200MHz
2N3019	SI-N	140V	1A	0.8W	100MHz
2N3053	SI-N	60V	0.7A	5W	100MHz
2N3054	SI-N	90V	4A	25W	3MHz
2N3055	SI-N	100V	15A	115W	800kHz
2N3055	SI-N	100V	15A	115W	800kHz
2N3055H	SI-N	100V	15A	115W	800kHz
2N3251	SI-P	50V	0.2A	0.36W	
2N3375	SI-N	40V	0.5A	11.6W	500MHz
2N3439	SI-N	450V	1A	10W	15MHz
2N3440	SI-N	300V	1A	10W	15MHz
2N3441	SI-N	160V	3A	25W	POWER
2N3442	SI-N	160V	10A	117W	0.8MHz
2N3495	SI-P	120V	0.1A	0.6W	>150MHz
2N3502	SI-P	45V	0.6A	0.7W	200MHz
2N3553	SI-N	65V	0.35A	7W	500MHz
2N3571	SI-N	30V	0.05A	0.2W	1.4GHz
2N3583	SI-N	250/175V	2A	35W	>10MHz
2N3632	SI-N	40V	0.25A	23W	400MHz
2N3646	SI-N	40V	0.2A	0.2W	
2N3700	SI-N	140V	1A	0.5W	200MHz
2N3707	SI-N	30V	0.03A	0.36W	100MHz
2N3708	SI-N	30V	0.03A	0.36W	80MHz
2N3716	SI-N	100V	10A	150W	4MHz
2N3725	SI-N	80V	0.5A	1W	35/60ns
2N3740	SI-P	60V	4A	25W	>4MHz
2N3741	SI-N	80V	4A	25W	>4MHz
2N3742	SI-N	300V	0.05A	1W	>30MHz
2N3767	SI-N	100V	4A	20W	>10MHz
2N3771	SI-N	50V	30A	150W	POWER
2N3772	SI-N	100V	20A	150W	POWER
2N3773	SI-N	160V	16A	150W	POWER
2N3792	SI-P	80V	10A	150W	4MHz
2N3819	N-FET	25V	20mA	0.36W	
2N3820	P-FET	20V	15mA	0.36W	
2N3821	N-FET	50V	2.5mA	0.3W	
2N3824	N-FET	50V	10mA	0.3W	<250E
2N3866	SI-N	55V	0.4A	1W	175MHz
2N3904	SI-N	60V	0.2A	.35W	300MHz
2N3906	SI-P	40V	0.2A	.35W	250MHz
2N3909	P-FET	20V	10MA	0.3W	
2N3958	N-FET	50V	5mA	0.25W	
2N3963	SI-P	80V	0.2A	0.36W	>40MHz
2N3972	N-FET	40V	50mA	1.8W	
2N4001	SI-N	100V	1A	15W	40MHz
2N4033	SI-P	80V	1A	0.8W	150MHz
2N4036	SI-P	90V	1A	1W	60MHz
2N409	GE-P	13V	15mA	80mW	6.8MHz

2N4126	SI-P	25V	200mA		HF
2N4220	N-FET	30V	0.2A		
2N4236	SI-P	80V	3A	1W	>3MHz
2N427	GE-P	30V	0.4A	0.15W	B>40
2N428	GE-P	30V	0.4A	0.15W	B>60
2N4286	SI-N	30V	0.05A	0.25W	
2N4287	SI-N	45V	0.1A	0.25W	40MHz
2N4291	SI-P	40V	0.2A	0.25W	150MH
2N4302	N-FET	30V	0.5mA	0.3W	
2N4347	SI-N	140V	5A	100W	0.8MHz
2N4348	SI-N	140V	10A	120W	>0.2MHz
2N4351	N-FET	30V	30mA	0.3W	140KHz
2N4391	N-FET	40V	50mA	30E	Up<10V
2N4392	N-FET	40V	25mA	60E	Up<5V
2N4393	N-FET	40V	5mA	100E	Up<3V
2N4401	SI-N	60V	0.6A		200MHz
2N4403	SI-P	40V	0.6A		200MHz
2N4416	N-FET	30V	15mA	VHF/UHF	
2N4420	SI-N	40V	0.2A	0.36W	
2N4427	SI-N	40V	0.4A	1W	175MHz
2N4906	SI-P	80V	5A	87.5W	>4MHz
2N4920	SI-P	80V	1A	30W	
2N4923	SI-N	80V	1A	30W	
2N5038	SI-N	150V	20A	140W	0.5us
2N5090	SI-N	55V	0.4A	4W	5mA
2N5109	SI-N	40V	0.5A	2.5W	1.5GHz
2N5116	P-FET	30V	5mA	150E	Up<4V
2N5154	SI-N	100V	2A	10W	
2N5179	SI-N	20V	50mA	0.2W	>1GHz
2N5192	SI-N	80V	4A	40W	2MHz
2N5240	SI-N	375V	5A	100W	>2MHz
2N5298	SI-N	80V	4A	36W	>0.8MHz
2N5308	N-DARL	40V	0.3A	0.4W	B>7K
2N5320	SI-N	100V	2A	10W	AFSWITCH
2N5322	SI-P	100V	2A	10W	AFSWITCH
2N5401	SI-P	160V	0.6A	0.31W	
2N5416	SI-P	350V	1A	10W	15MHz
2N5433	N-FET	25V	0.4A	0.3W	7E
2N5457	N-FET	25V	1mA	Up<6V	
2N5458	N-FET	25V	2.9mA	UNI	
2N5460	P-FET	40V	5mA	Up<6V	GEN.P
2N5461	P-FET	40V	9mA	0.31W	
2N5462	P-FET	40V	16mA	Up<9V	GEN.
2N5484	N-FET	25V	5mA	0.31W	
2N5485	P-FET	25V	4mA	Up<4V	
2N5551	SI-N	180V	0.6A	0.31W	VID.
2N5589	SI-N	36V	0.6A	3W	175MHz
2N5639	N-FET	30V	10mA	310mW	
2N5672	SI-N	150V	30A	140W	0.5us
2N5680	SI-P	120V	1A	1W	
2N5682	SI-N	120V	1A	1W	>30MHz
2N5684	SI-P	80V	50A	200W	
2N5686	SI-N	80V	50A	300W	>2MHz
2N5770	SI-N	30V	0.05A	0.7W	>900MHz
2N5771	SI-P	15V	50mA	625mW	>850MHz
2N5876	SI-P	80V	10A	150W	>4MHz
2N5878	SI-N	80V	10A	150W	>4MHz
2N5879	SI-N	60V	10A	150W	>4MHz
2N5884	SI-P	80V	25A	200W	AFPOWSW
2N5886	SI-N	80V	25A	200W	>4MHz
2N6031	SI-P	140V	16A	200W	1MHz
2N6050	P-DARL+D	60V	12A	100W	
2N6059	SI-N	100V	12A	150W	
2N6083	SI-N	36V	5A	PQ=30W	175MHz
2N6098	SI-N	70V	10A	75W	AFPOWSWITCH
2N6099	SI-N	70V	10A	75W	AFPOWSWITCH
2N6109	SI-P	60V	7A	40W	10MHz
2N6124	SI-P	45V	4A	40W	
2N6211	SI-P	275V	2A	20W	20MHz
2N6213	SI-P	400V	2A	35W	>20MHz
2N6248	SI-P	110V	15A	125W	>6MHz
2N6284	N-DARL	100V	20A	160W	B>75

2N6287	P-DARL	100V	20A	160W	
2N6292	SI-N	80V	7A	40W	
2N6356	N-DARL	50V	20A	150W	B>150
2N6422	SI-P	500V	2A	35W	>10MHz
2N6427	N-DARL	40V	0.5A	0.625W	
2N6476	SI-P	130V	4A	16W	5MHz
2N6488	SI-N	90V	15A	75W	
2N6491	SI-P	90V	15A	30W	
2N6517	SI-N	350V	0.5A	0.625W	>40
2N6520	SI-P	350V	0.5A	0.625W	>40
2N6547	SI-N	850/400V	15A	175W	
2N6556	SI-P	100V	1A	10W	>75MHz
2N6609	SI-P	160V	16A	150W	2MHz
2N6660	N-FET	60V	2A	6.25W	3E
2N6661	N-FET	90V	2A	6.2W	4E
2N6675	SI-N	400V	15A		
2N6678	SI-N	400V	15A		
2N6716	SI-N	60V	2A	2W	50MHz
2N6718	SI-N	100V	2A	2W	50MHz
2N6725	N-DARL	60V	2A	1W	B>15K
2N6728	SI-P	60V	2A	2W	>50MHz
2N697	SI-N	60V	1A	0.6W	<50MHz
2N7002	N-FET	60V	0.115A	0.2W	7,00E+05
2N914	SI-N	40V	0.5A	SW	<40/40NS
2N918	SI-N	30V	50mA	0.2W	600MHz
2SA1006B	SI-P	250V	1.5A	25W	80MHz
2SA1009	SI-P	350V	2A	15W	
2SA1011	SI-P	160V	1.5A	25W	120MHz
2SA1013	SI-P	160V	1A	0.9W	50MHz
2SA1015	SI-P	50V	0.15A	0.4W	80MHz
2SA1016	SI-P	100V	0.05A	0.4W	110MHz
2SA1017	SI-P	120V	50mA	0.5W	110MHz
2SA1018	SI-P	250V	70mA	0.75W	>50MHz
2SA1020	SI-P	50V	2A	0.9W	100MHz
2SA1027	SI-P	50V	0.2A	0.25W	100MHz
2SA1029	SI-P	30V	0.1A	0.2W	280MHz
2SA1034	SI-P	35V	50mA	0.2W	200MHz
2SA1037	SI-P	50V	0.4A	FR	140MHz
2SA1048	SI-P	50V	0.15A	0.2W	80MHz
2SA1049	SI-P	120V	0.1A	0.2W	100MHz
2SA1061	SI-P	100V	6A	70W	15MHz
2SA1062	SI-N	120V	7A	80W	15MHz
2SA1065	SI-P	150V	10A	120W	50MHz
2SA1084	SI-P	90V	0.1A	0.4W	90MHz
2SA1103	SI-P	100V	7A	70W	20MHz
2SA1106	SI-P	140V	10A	100W	20MHz
2SA1110	SI-P	120V	0.5A	5W	250MHz
2SA1111	SI-P	150V	1A	20W	200MHz
2SA1112	SI-P	180V	1A	20W	200MHz
2SA1115	SI-P	50V	0.2A	UNI	200MHz
2SA1120	SI-P	35V	5A		170MHz
2SA1123	SI-P	150V	50mA	0.75W	200MHz
2SA1124	SI-P	150V	50mA	1W	200MHz
2SA1127	SI-P	60V	0.1A	0.4W	200MHz
2SA1141	SI-P	115V	10A	100W	90MHz
2SA1142	SI-P	180V	0.1A	8W	180MHz
2SA1145	SI-P	150V	50mA	0.8W	200MHz
2SA1150	SI-P	35V	0.8A	0.3W	120MHz
2SA1156	SI-P	400V	0.5A	10W	POWER
2SA1160	SI-P	20V	2A	0.9W	150MHz
2SA1163	SI-P	120V	0.1A		100MHz
2SA1170	SI-P	200V	17A	200W	20MHz
2SA1185	SI-P	50V	7A	60W	100MHz
2SA1186	SI-P	150V	10A	100W	
2SA1200	SI-P	150V	50mA	0.5W	120MHz
2SA1201	SI-P	120V	0.8A	0.5W	120MHz
2SA1206	SI-P	15V	0.05A	0.6W	
2SA1207	SI-P	180V	70mA	0.6W	150MHz
2SA1208	SI-P	180V	0.07A	0.9W	
2SA1209	SI-P	180V	0.14A	10W	
2SA1210	SI-P	200V	0.14A	10W	
2SA1213	SI-P	50V	2A	0.5W	120MHz

2SA1215	SI-P	160V	15A	150W	50MHz
2SA1216	SI-P	180V	17A	200W	40MHz
2SA1220A	SI-P	120V	1.2A	20W	160MHz
2SA1221	SI-P	160V	0.5A	1W	45MHz
2SA1225	SI-P	160V	1.5A	15W	100MHz
2SA1227A	SI-P	140V	12A	120W	60MHz
2SA1232	SI-P	130V	10A	100W	60MHz
2SA1241	SI-P	50V	2A	10W	100MHz
2SA1242	SI-P	35V	5A	1W	170MHz
2SA1244	SI-P	60V	5A	20W	60MHz
2SA1249	SI-P	180V	1.5A	10W	120MHz
2SA1261	SI-P	100V	10A	60W	POWER
2SA1262	SI-P	60V	4A	30W	15MHz
2SA1264N	SI-P	120V	8A	80W	30MHz
2SA1265N	SI-P	140V	10A	100W	30MHz
2SA1266	SI-P	50V	0.15A	0.4W	POWER
2SA1268	SI-N	120V	0.1A	0.3W	100MHz
2SA1270	SI-P	35V	0.5A	0.5W	200MHz
2SA1271	SI-P	30V	0.8A	0.6W	120MHz
2SA1275	SI-P	160V	1A	0.9W	20MHz
2SA1282	SI-P	20V	2A	0.9W	80MHz
2SA1283	SI-P	60V	1A	0.9W	85MHz
2SA1286	SI-P	30V	1.5A	0.9W	90MHz
2SA1287	SI-P	50V	1A	0.9W	90MHz
2SA1292	SI-P	80V	15A	70W	100MHz
2SA1293	SI-P	100V	5A	30W	0.2us
2SA1294	SI-P	230V	15A	130W	
2SA1295	SI-P	230V	17A	200W	35MHz
2SA1296	SI-P	20V	2A	0.75W	120MHz
2SA1298	SI-P	30V	0.8A	0.2W	120MHz
2SA1300	SI-P	10V	2A	0.75W	140MHz
2SA1302	SI-P	200V	15A	150W	25MHz
2SA1303	SI-P	150V	14A	125W	50MHz
2SA1306	SI-P	160V	1.5A	20W	
2SA1306A	SI-P	180V	1.5A	20W	100MHz
2SA1307	SI-P	60V	5A	20W	0.1us
2SA1309	SI-P	30V	0.1A	0.3W	80MHz
2SA1310	SI-P	60V	0.1A	0.3W	200MHz
2SA1315	SI-P	80V	2A	0.9W	0.2us
2SA1316	SI-P	80V	0.1A	0.4W	50MHz
2SA1317	SI-P	60V	0.2A	0.3W	200MHz
2SA1318	SI-P	60V	0.2A	0.5W	200MHz
2SA1319	SI-P	180V	0.7A	0.7W	120MHz
2SA1321	SI-P	250V	50mA	0.9W	100MHz
2SA1328	SI-P	60V	12A	40W	0.3us
2SA1329	SI-P	80V	12A	40W	0.3us
2SA1345	SI-N	50V	0.1A	0.3W	250MHz
2SA1346	SI-P	50V	0.1A		200MHz
2SA1348	SI-P	50V	0.1A		200MHz
2SA1349	P-ARRAY	80V	0.1A	0.4W	170
2SA1352	SI-P	200V	0.1A	5W	70MHz
2SA1357	SI-P	35V	5A	10W	170MHz
2SA1358	SI-P	120V	1A	10W	120MHz
2SA1359	SI-P	40V	3A	10W	100MHz
2SA1360	SI-P	150V	50mA	5W	200MHz
2SA1361	SI-P	250V	50mA		80MHz
2SA1370	SI-P	200V	0.1A	1W	150MHz
2SA1371E	SI-P	300V	0.1A	1W	150MHz
2SA1376	SI-P	200V	0.1A	0.75W	120MHz
2SA1380	SI-P	200V	0.1A	1.2W	
2SA1381	SI-P	300V	0.1A		150MHz
2SA1382	SI-P	120V	2A	0.9W	0.2us
2SA1383	SI-P	180V	0.1A	10W	180MHz
2SA1386	SI-P	160V	15A	130W	40MHz
2SA1387	SI-P	60V	5A	25W	80MHz
2SA1392	SI-P	60V	0.2A	0.4W	200MHz
2SA1396	SI-P	100V	10A	30W	
2SA1399	SI-P	55V	0.4A	0.9W	150MHz
2SA1400	SI-P	400V	0.5A	10W	
2SA1403	SI-P	80V	0.5A	10W	800MHz
2SA1405	SI-P	120V	0.3A	8W	500MHz
2SA1406	SI-P	200V	0.1A	7W	400MHz

2SA1407	SI-P	150V	0.1A	7W	400MHz
2SA1413	SI-P	600V	1A	10W	26MHz
2SA1428	SI-P	50V	2A	1W	100MHz
2SA1431	SI-P	35V	5A	1W	170MHz
2SA1441	SI-P	100V	5A	25W	<300ns
2SA1443	SI-P	100V	10A	30W	
2SA1450	SI-P	100V	0.5A	0.6W	120MHz
2SA1451	SI-P	60V	12A	30W	70MHz
2SA1460	SI-P	60V	1A	1W	<40NS
2SA1470	SI-P	80V	7A	25W	100MHz
2SA1475	SI-P	120V	0.4A	15W	500MHz
2SA1476	SI-P	200V	0.2A	15W	400MHz
2SA1477	SI-P	180V	0.14A	10W	150MHz
2SA1488	SI-P	60V	4A	25W	15MHz
2SA1489	SI-P	80V	6A	60W	20MHz
2SA1490	SI-P	120V	8A	80W	20MHz
2SA1491	SI-P	140V	10A	100W	20MHz
2SA1494	SI-P	200V	17A	200W	20MHz
2SA1507	SI-P	180V	1.5A	10W	120MHz
2SA1515	SI-P	40V	1A	0.3W	150MHz
2SA1516	SI-P	180V	12A	130W	25MHz
2SA1519	SI-P	50V	0.5A	0.3W	200MHz
2SA1535A	SI-P	180V	1A	40W	200MHz
2SA1538	SI-P	120V	0.2A	8W	400MHz
2SA1539	SI-P	120V	0.3A	8W	400MHz
2SA1540	SI-P	200V	0.1A	7W	300MHz
2SA1541	SI-P	200V	0.2A	7W	300MHz
2SA1553	SI-P	230V	15A	150W	25MHz
2SA1566	SI-N	120V	0.1A	0.15W	130MHz
2SA1567	SI-P	50V	12A	35W	40MHz
2SA1568	SI-P	60V	12A	40W	
2SA1577	SI-P	32V	0.5A	0.2W	200MHz
2SA1593	SI-P	120V	2A	15W	120MHz
2SA1601	SI-P	60V	15A	45W	
2SA1606	SI-P	180V	1.5A	15W	100MHz
2SA1615	SI-P	30V	10A	15W	180MHz
2SA1624	SI-P	300V	0.1A	0.5W	70MHz
2SA1625	SI-P	400V	0.5A	0.75W	
2SA1626	SI-P	400V	2A	1W	0.5/2.7us
2SA1633	SI-P	150V	10A	100W	20MHz
2SA1643	SI-P	50V	7A	25W	75MHz
2SA1667	SI-P	150V	2A	25W	20MHz
2SA1668	SI-P	200V	2A	25W	20MHz
2SA1670	SI-P	80V	6A	60W	20MHz
2SA1671	SI-P	120/120V	8A	75W	20MHz
2SA1672	SI-P	140V	10A	80W	20MHz
2SA1673	SI-P	180V	15A	85W	20MHz
2SA1680	SI-P	60V	2A	0.9W	100/400ns
2SA1684	SI-P	120V	1.5A	20W	150MHz
2SA1694	SI-P	120/120V	8A	80W	20MHz
2SA1695	SI-P	140V	10A	80W	20MHz
2SA1703	SI-P	30V	1.5A	1W	180MHz
2SA1706	SI-P	60V	2A	1W	
2SA1708	SI-P	120V	1A	1W	120MHz
2SA1726	SI-P	80V	6A	50W	20MHz
2SA1776	SI-P	400V	1A	1W	
2SA1803	SI-P	80V	6A	55W	30MHz
2SA1837	SI-P	230V	1A	20W	70MHz
2SA1930	SI-P	180V	2A	20W	200MHz
2SA1962	SI-P	230V	15A	130W	25MHz
2SA329	GE-P	15V	10mA	0.05W	
2SA467	SI-P	40V	0,4A	0,3W	
2SA473	SI-P	30V	3A	10W	100MHz
2SA483	SI-P	150V	1A	20W	9MHz
2SA493	SI-P	50V	0.05A	0.2W	80MHz
2SA495	SI-P	35V	0.1A	0.2W	200MHz
2SA562	SI-P	30V	0.5A	0.5W	200MHz
2SA566	SI-P	100V	0.7A	10W	100MHz
2SA608	SI-N	40V	0.1A	0.1W	180MHz
2SA614	SI-P	80V	1A	15W	30MHz
2SA620	SI-P	30V	0.05A	0.2W	120MHz
2SA626	SI-P	80V	5A	60W	15MHz

2SA628	SI-P	30V	0.1A		100MHz
2SA639	SI-P	180V	50mA	0.25W	
2SA642	SI-P	30V	0.2A	0.25W	200MHz
2SA643	SI-P	40V	0.5A	0.5W	180MHz
2SA653	SI-P	150V	1A	15W	5MHz
2SA684	SI-P	60V	1A	1W	200MHz
2SA699	SI-P	40V	2A	10W	150MHz
2SA708A	SI-P	100V	0.7A	0.8W	50MHz
2SA720	SI-P	60V	0.5A	0.6W	200MHz
2SA725	SI-P	35V	0.1A	0.15W	100MHz
2SA733	SI-P	60V	0.15A	0.25W	50MHz
2SA738	SI-P	25V	1.5A	8W	160MHz
2SA747	SI-P	120V	10A	100W	15MHz
2SA756	SI-P	100V	6A	50W	20MHz
2SA762	SI-P	110V	2A	23W	80MHz
2SA765	SI-P	80V	6A	40W	10MHz
2SA768	SI-P	60V	4A	30W	10MHz
2SA769	SI-P	80V	4A	30W	10MHz
2SA770	SI-P	60V	6A	40W	10MHz
2SA771	SI-P	80V	6A	40W	2MHz
2SA777	SI-P	80V	0.5A	0.75W	120MHz
2SA778A	SI-P	180V	0.05A	0.2W	60MHz
2SA781	SI-P	20V	0.2A	0.2W	<80/16
2SA794	SI-P	100V	0.5A	5W	120MHz
2SA794A	SI-P	120V	0.5A	5W	120MHz
2SA812	SI-P	50V	0.1A	0.15W	
2SA814	SI-P	120V	1A	15W	30MHz
2SA816	SI-P	80V	0.75A	1.5W	100MHz
2SA817	SI-P	80V	0.3A	0.6W	100MHz
2SA817A	SI-P	80V	0.4A	0.8W	100MHz
2SA836	SI-P	55V	0.1A	0.2W	100MHz
2SA838	SI-P	30V	30mA	0.25W	300MHz
2SA839	SI-P	150V	1.5A	25W	6MHz
2SA841	SI-P	60V	0.05A	0.2W	140MHz
2SA858	SI-P	150V	50mA	0.5W	100MHz
2SA872	SI-P	90V	0.05A	0.2W	120MHz
2SA872A	SI-P	120V	50mA	0.3W	120MHz
2SA884	SI-P	65V	0.2A	0.27W	140MHz
2SA885	SI-P	45V	1A	5W	200MHz
2SA886	SI-P	50V	1.5A	1.2W	
2SA893	SI-P	90V	50mA	0.3W	
2SA900	SI-P	18V	1A	1.2W	
2SA914	SI-P	150V	0.05A		200MHz
2SA915	SI-P	120V	0.05A	0.8W	80MHz
2SA916	SI-P	160V	0.05A	1W	80MHz
2SA921	SI-P	120V	20mA	0.25W	200MHz
2SA933	SI-P	50V	0.1A	0.3W	
2SA934	SI-P	40V	0.7A	0.75W	
2SA935	SI-P	80V	0.7A	0.75W	150MHz
2SA937	SI-P	50V	0.1A	0.3W	140MHz
2SA940	SI-P	150V	1.5A	25W	4MHz
2SA941	SI-P	120V	0.05A	0.3W	150MHz
2SA949	SI-P	150V	50mA	0.8W	120MHz
2SA965	SI-P	120V	0.8A	0.9W	120MHz
2SA966	SI-P	30V	1.5A	0.9W	120MHz
2SA968	SI-P	160V	1.5A	25W	100MHz
2SA970	SI-P	120V	0.1A		100MHz
2SA982	SI-P	140V	8A	80W	20MHz
2SA984	SI-P	60V	0.5A	0.5W	120MHz
2SA985	SI-P	120V	1.5A	25W	180MHz
2SA988	SI-P	120V	0.05A	0.5W	
2SA991	SI-P	60V	0.1A	0.5W	90MHz
2SA992	SI-P	100V	0.05A	0.2W	
2SA995	SI-P	100V	0.05A	0.4W	100MHz
2SB1009	SI-P	40V	2A	10W	100MHz
2SB1010	SI-P	40V	2A	0.75W	100MHz
2SB1012K	P-DARL	120V	1.5A	8W	
2SB1013	SI-P	20V	2A	0.7W	
2SB1015	SI-P	60V	3A	25W	0.4us
2SB1016	SI-P	100V	5A	30W	5MHz
2SB1017	SI-P	80V	4A	25W	9MHz
2SB1018	SI-P	100V	7A	30W	0.4us

2SB1020	P-DARL+D	100V	7A	30W	0.8us
2SB1023	P-DARL+D	60V	3A	20W	B=5K
2SB1035	SI-P	30V	1A	0.9W	100MHz
2SB1039	SI-P	100V	4A	40W	20MHz
2SB1050	SI-P	30V	5A	1W	120MHz
2SB1055	SI-P	120V	6A	70W	20MHz
2SB1065	SI-P	60V	3A	10W	
2SB1066	SI-P	50V	3A	1W	70MHz
2SB1068	SI-P	20V	2A	0.75W	180MHz
2SB1071	SI-P	40V	4A	25W	150MHz
2SB1077	P-DARL	60V	4A	40W	B>1K
2SB1086	SI-P	160V	1.5A	20W	50MHz
2SB1098	P-DARL+D	100V	5A	20W	B=80
2SB1099	P-DARL+D	100V	8A	25W	B=6K
2SB1100	P-DARL+D	100V	10A	30W	B=6
2SB1109	SI-P	160V	0.1A	1.25W	
2SB1109S	SI-P	160V	0.1A	1.25W	
2SB1117	SI-P	30V	3A	1W	280MHz
2SB1120	SI-P	20V	2.5A	0.5W	250MHz
2SB1121T	SI-P	30V	2A		150MHz
2SB1123	SI-P	60V	2A	0.5W	150MHz
2SB1132	SI-P	40V	1A	0.5W	150MHz
2SB1133	SI-P	60V	3A	25W	40MHz
2SB1134	SI-P	60V	5A	25W	30W
2SB1135	SI-P	60V	7A	30W	10MHz
2SB1136	SI-P	60V	12A	30W	10MHz
2SB1140	SI-P	25V	5A	10W	320MHz
2SB1141	SI-P	20V	1.2A	10W	150MHz
2SB1143	SI-P	60V	4A	10W	140MHz
2SB1146	P-DARL	120V	6A	25W	
2SB1149	P-DARL	100V	3A	15W	B=10K
2SB1151	SI-P	60V	5A	20W	
2SB1154	SI-P	130V	10A	70W	30MHz
2SB1156	SI-P	130V	20A	100W	
2SB1162	SI-P	160V	12A	120W	
2SB1163	SI-P	170V	15A	150W	
2SB1166	SI-P	60V	8A	20W	130MHz
2SB1168	SI-P	120V	4A	20W	130MHz
2SB1182	SI-P	40V	2A	10W	100MHz
2SB1184	SI-P	60V	3A	15W	70MHz
2SB1185	SI-P	50V	3A	25W	70MHz
2SB1186	SI-P	120V	1.5A	20W	50MHz
2SB1187	SI-P	80V	3A	35W	
2SB1188	SI-P	40V	2A		100MHz
2SB1202	SI-P	60V	3A	15W	150MHz
2SB1203	SI-P	60V	5A	20W	130MHz
2SB1204	SI-P	60V	8A	20W	130MHz
2SB1205	SI-P	25V	5A	10W	320MHz
2SB1212	SI-P	160V	1.5A	0.9W	50MHz
2SB1223	P-DARL+D	70V	4A	20W	20MHz
2SB1236	SI-P	120V	1.5A	1W	50MHz
2SB1237	SI-P	40V	1A	1W	150MHz
2SB1238	SI-P	80V	0.7A	1W	100MHz
2SB1240	SI-P	40V	2A	1W	100MHz
2SB1243	SI-P	60V	3A	1W	
2SB1254	P-DARL	160V	7A	70W	
2SB1255	P-DARL	160V	8A	100W	B>5K
2SB1258	P-DARL+D	100V	6A	30W	B>1K
2SB1274	SI-P	60V	3A	30W	100MHz
2SB1282	P-DARL+D	100V	4A	25W	50MHz
2SB1292	SI-P	80V	5A	30W	
2SB1302	SI-P	25V	5A		320MHz
2SB1318	P-DARL+D	100V	3A	1W	B>200
2SB1326	SI-P	30V	5A	0.3W	120MHz
2SB1329	SI-P	40V	1A	1.2W	150MHz
2SB1330	SI-P	32V	0.7A	1.2W	100MHz
2SB1331	SI-P	32V	2A	1.2W	100MHz
2SB1353E	SI-P	120V	1.5A	1.8W	50MHz
2SB1361	SI-P	150V	9A	100W	15MHz
2SB1370	SI-P	60V	3A	30W	15MHz
2SB1373	SI-P	160V	12A	2.5W	15MHz
2SB1375	SI-P	60V	3A	25W	9MHz

2SB1382	P-DARL+D	120V	16A	75W	B>2
2SB1393	SI-P	30V	3A	2W	30MHz
2SB1420	SI-P	120V	16A	80W	50MHz
2SB1425	SI-P	20V	2A	1W	90MHz
2SB1429	SI-P	180V	15A	150W	10MHz
2SB1434	SI-P	50V	2A	1W	110MHz
2SB1468	SI-P	60/30V	12A	25W	
2SB1470	P-DARL	160V	8A	150W	B>5K
2SB1490	P-DARL	160V	7A	90W	B>5K
2SB1493	P-DARL	160/140V	7A	70W	20
2SB1503	P-DARL	160V	8A	120W	B>5K
2SB1556	P-DARL	140V	8A	120W	B>5K
2SB1557	P-DARL	140V	7A	100W	B>5K
2SB1559	P-DARL	160V	8A	80W	B>5K
2SB1560	P-DARL	160V	10A	100W	50MHz
2SB1565	SI-P	80V	3A	25W	15MHz
2SB1587	P-DARL+D	160V	8A	70W	B>5K
2SB1624	P-DARL	110V	6A	60W	B>5K
2SB206	GE-P	80V	30A	80W	
2SB324	GE-P	32V	1A	0.25W	
2SB337	GE-P	50V	7A	30W	LF-POWER
2SB407	GE-P	30V	7A	30W	
2SB481	GE-P	32V	1A	6W	15KHz
2SB492	GE-P	25V	2A	6W	
2SB511E	SI-P	35V	1.5A	10W	8MHz
2SB524	SI-P	60V	1.5A	10W	70MHz
2SB527	SI-P	110V	0.8A	10W	70MHz
2SB531	SI-P	90V	6A	50W	8MHz
2SB536	SI-P	130V	1.5A	20W	40MHz
2SB537	SI-P	130V	1.5A	20W	60MHz
2SB541	SI-P	110V	8A	80W	9MHz
2SB544	SI-P	25V	1A	0.9W	180MHz
2SB546A	SI-P	200V	2A	25W	5MHz
2SB549	SI-P	120V	0.8A	10W	80MHz
2SB557	SI-P	120V	8A	80W	
2SB560	SI-P	100V	0.7A	0.9W	100MHz
2SB561	SI-P	25V	0.7A	0.5W	
2SB564	SI-P	30V	1A	0.8W	
2SB598	SI-P	25V	1A	0.5W	180MHz
2SB600	SI-P	200V	15A	200W	4MHz
2SB601	P-DARL	100V	5A	30W	
2SB605	SI-P	60V	0.7A	0.8W	120MHz
2SB621	SI-N	25V	1.5A	0.6W	200MHz
2SB621A	SI-N	50V	1A	0.75W	200MHz
2SB631	SI-P	100V	1A	8W	
2SB632	SI-P	25V	2A	10W	100MHz
2SB633	SI-P	100V	6A	40W	15MHz
2SB637	SI-P	50V	0.1A	0.3W	200MHz
2SB641	SI-P	30V	0.1A		120MHz
2SB647	SI-P	120V	1A	0.9W	140MHz
2SB649A	SI-P	160V	1.5A	1W	140MHz
2SB656	SI-P	160V	12A	125W	20MHz
2SB673	P-DARL+D	100V	7A	40W	0.8us
2SB676	P-DARL	100V	4A	30W	0.15us
2SB681	SI-N	150V	12A	100W	13MHz
2SB688	SI-P	120V	8A	80W	10MHz
2SB700	SI-P	160V	12A	100W	
2SB703	SI-P	100V	4A	40W	18MHz
2SB705	SI-P	140V	10A	120W	17MHz
2SB707	SI-P	80V	7A	40W	POWER
2SB709	SI-P	45V	0.1A	0.2W	80MHz
2SB716	SI-P	120V	0.05A	0.75W	
2SB720	SI-P	200V	2A	25W	100MHz
2SB727	P-DARL+D	120V	6A	50W	B>1K
2SB731	SI-P	60V	1A	10W	75MHz
2SB733	SI-P	20V	2A	1W	>50MHz
2SB734	SI-P	60V	1A	1W	80MHz
2SB739	SI-P	20/16V	2A	0.9W	80MHz
2SB740	SI-P	70V	1A	0.9W	
2SB744	SI-P	70V	3A	10W	45MHz
2SB750	P-DARL+D	60V	2A	35W	B>100
2SB753	SI-P	100V	7A	40W	0.4us

2SB764	SI-P	60V	1A	0.9A	150MHz
2SB765	P-DARL+D	120V	3A	30W	B>1K
2SB766	SI-P	30V	1A		200MHz
2SB772	SI-P	40V	3A	10W	80MHz
2SB774	SI-P	30V	0.1A	0.4W	150MHz
2SB775	SI-P	100V	6A	60W	13MHz
2SB776	SI-P	120V	7A	70W	15MHz
2SB788	SI-P	120V	0.02A	0.4W	150MHz
2SB791	P-DARL+D	120V	8A	40W	B>10
2SB794	P-DARL+D	60V	1.5A	10W	B=7
2SB795	P-DARL+D	80V	1.5A	10W	B<3
2SB808	SI-P	20V	0.7A	0.25W	250MHz
2SB810	SI-P	30V	0.7A	0.35W	160MHz
2SB815	SI-P	20V	0.7A	0.25W	250MHz
2SB816	SI-P	150V	8A	80W	15MHz
2SB817	SI-P	160V	12A	100W	
2SB817F	SI-P	160V	12A	90W	15MHz
2SB819	SI-P	50V	1.5A	1W	150MHz
2SB822	SI-P	40V	2A	0.75W	100MHz
2SB824	SI-P	60V	5A	30W	30MHz
2SB825	SI-P	60V	7A	40W	10MHz
2SB826	SI-P	60V	12A	40W	10MHz
2SB827	SI-P	60V	7A	80W	10MHz
2SB828	SI-P	60V	12A	80W	10MHz
2SB829	SI-P	60V	15A	90W	20MHz
2SB857	SI-P	50V	4A	40W	NF/S-L
2SB861	SI-P	200V	2A	30W	
2SB863	SI-P	140V	10A	100W	15MHz
2SB865	P-DARL	80V	1.5A	0.9W	
2SB873	SI-P	30V	5A	1W	120MHz
2SB882	P-DARL+D	70V	10A	40W	B>5K
2SB883	P-DARL+D	70V	15A	70W	B=5K
2SB884	P-DARL	110V	3A	30W	B=4K
2SB885	P-DARL+D	110V	3A	35W	B=4K
2SB891	SI-P	40V	2A	5W	100MHz
2SB892	SI-P	60V	2A	1W	
2SB895A	P-DARL	60V	1A		B=8000
2SB897	P-DARL+D	100V	10A	80W	B>1
2SB908	P-DARL+D	80V	4A	15W	0.15us
2SB909	SI-P	40V	1A	1W	150MHz
2SB922	SI-P	120V	12A	80W	20MHz
2SB926	SI-P	30V	2A	0.75W	
2SB938A	P-DARL+D	60V	4A	40W	B>1K
2SB940	SI-P	200V	2A	35W	30MHz
2SB941	SI-P	60V	3A	35W	POWER
2SB945	SI-P	130V	5A	40W	30MHz
2SB946	SI-P	130V	7A	40W	30MHz
2SB950A	P-DARL+D	80V	4A	40W	B>1K
2SB953A	SI-P	50V	7A	30W	150MHz
2SB955	P-DARL+D	120V	10A	50W	B=4
2SB975	P-DARL+D	100V	8A	40W	B>6K
2SB976	SI-P	27V	5A	0.75W	120MHz
2SB985	SI-P	60V	3A	1W	150MHz
2SB986	SI-P	60V	4A	10W	150MHz
2SB988	SI-P	60V	3A	30W	<400/2200
2SC1000	SI-N	55V	0.1A	0.2W	80MHz
2SC1008	SI-N	80V	0.7A	0.8W	75MHz
2SC1012A	SI-N	250V	60mA	0.75W	>80MHz
2SC1014	SI-N	50V	1.5A	7W	
2SC1017	SI-N	75V	1A	60mW	120MHz
2SC1030	SI-N	150V	6A	50W	
2SC1046	SI-N	1000V	3A	25W	
2SC1047	SI-N	30V	20mA	0.4W	650MHz
2SC1050	SI-N	300V	1A	40W	
2SC1051	SI-N	150V	7A	60W	8MHz
2SC1061	SI-N	50V	3A	25W	8MHz=H106
2SC1070	SI-N	30V	20mA		900MHz
2SC1080	SI-N	110V	12A	100W	4MHz
2SC109	SI-N	50V	0.6A	0.6W	
2SC1096	SI-N	40V	3A	10W	60MHz
2SC1106	SI-N	350V	2A	80W	
2SC1114	SI-N	300V	4A	100W	10MHz

2SC1115	SI-N	140V	10A	100W	10MHz
2SC1116	SI-N	180V	10A	100W	10MHz
2SC1161	SI-P	160V	12A	120W	
2SC1162	SI-N	35V	1.5A	10W	
2SC1172	SI-N	1500V	5A	50W	
2SC1195	SI-N	200V	2.5A	100W	
2SC1213C	SI-N	50V	0.5A	0.4W	UNI
2SC1214	SI-N	50V	0.5A	0.6W	50MHz
2SC1215	SI-N	30V	50mA	0.4W	1.2GHZ
2SC1216	SI-N	40V	0.2A	0.3W	<20/40
2SC1226	SI-N	40/50V	2A	10W	150MHz
2SC1238	SI-N	35V	0.15A	5W	1.7GHz
2SC1247A	SI-N	50V	0.5A	0.4W	60MHz
2SC1308	SI-N	1500V	7A	50W	
2SC1312	SI-N	35V	0.1A	0.15W	100MHz
2SC1318	SI-N	60V	0.5A	0.6W	200MHz
2SC1343	SI-N	150V	10A	100W	14MHz
2SC1345	SI-N	55V	0.1A	0.1W	230MHz
2SC1359	SI-N	30V	30mA	0.4W	250MHz
2SC1360	SI-N	50V	0.05A	1W	>300MHz
2SC1362	SI-N	50V	0.2A	0.25W	140MHz
2SC1368	SI-N	25V	1.5A	8W	180MHz
2SC1382	SI-N	80V	0.75A	5W	100MHz
2SC1384	SI-N	60V	1A	1W	200MHz
2SC1393	SI-N	30V	20mA	250mW	700MHz
2SC1398	SI-N	70V	2A	15W	
2SC1413A	SI-N	1200V	5A	50W	
2SC1419	SI-N	50V	2A	20W	5MHz
2SC1426	SI-N	35V	0.2A		2.7GHz
2SC1431	SI-N	110V	2A	23W	80MHz
2SC1432	N-DARL	30V	0.3A	0.3W	B=40
2SC1439	SI-N	150V	50mA	0.5W	130MHz
2SC1445	SI-N	100V	6A	40W	10MHz
2SC1446	SI-N	300V	0.1A	10W	55MHz
2SC1447	SI-N	300V	0.15A	20W	80MHz
2SC1448	SI-N	150V	1.5A	25W	3MHz
2SC1449	SI-N	40V	2A	5W	60MHz
2SC1450	SI-N	150V	0.4A	20W	
2SC1454	SI-N	300V	4A	50W	10MHz
2SC1474-4	SI-N	20V	2A	0.75W	80MHz
2SC1501	SI-N	300V	0.1A	10W	55MHz
2SC1505	SI-N	300V	0.2A	15W	
2SC1507	SI-N	300V	0.2A	15W	80MHz
2SC1509	SI-N	80V	0.5A	1W	120MHz
2SC1515	SI-N	200V	0.05A	0.2W	110MHz
2SC1520	SI-N	300V	0.2A	12.5W	
2SC1545	N-DARL	40V	0.3A	0.3W	B=1K
2SC1567	SI-N	100V	0.5A	5W	120MHz
2SC1570	SI-N	55V	0.1A	0.2W	100MHz
2SC1571	SI-N	40V	0.1A	0.2W	100MHz
2SC1573	SI-N	200V	0.1A	1W	80MHz
2SC1577	SI-N	500V	8A	80W	7MHz
2SC1583	SI-N	50V	0.1A	0.4W	100MHz
2SC1619	SI-N	100V	6A	50W	10MHz
2SC1623	SI-N	60V	0.1A	0.2W	250MHz
2SC1624	SI-N	120V	1A	15W	30MHz
2SC1627	SI-N	80V	0.4A	0.8W	100MHz
2SC1674	SI-N	30V	.02A	600MC	RF/IF
2SC1675	SI-N	50V	.03A	0.25W	
2SC1678	SI-N	65V	3A	3W	
2SC1685	SI-N	60V	0.1A	150MC	UNI
2SC1688	SI-N	50V	30mA	0.4W	550MHz
2SC1708A	SI-N	120V	50mA	0.2W	150MHz
2SC1729	SI-N	35V	3.5A	16W	500MHz
2SC1730	SI-N	30V	0.05A	UHF	1.1GHz
2SC1740	SI-N	40V	100mA	0.3W	
2SC1741	SI-N	40V	0.5A	0.3W	250MHz
2SC1756	SI-N	300V	0.2A		>50MHz
2SC1760	SI-N	100V	1A	7.9W	80MHz
2SC1775A	SI-N	120V	0.05A	0.2W	UNI
2SC1781	SI-N	50V	0.5A	0.35W	
2SC1815	SI-N	50V	0.15A	0.4W	80MHz

2SC1815BL	SI-N	60V	0.15A	0.4W	B>350
2SC1815GR	SI-N	60V	0.15A	0.4W	B>200
2SC1815Y	SI-N	60V	0.15A	0.4W	B>120
2SC1827	SI-N	100V	4A	30W	10MHz
2SC1832	N-DARL	500V	15A	150W	B>10
2SC1841	SI-N	120V	0.05A	0.5W	
2SC1844	SI-N	60V	0.1A	0.5W	100MHz
2SC1845	SI-N	120V	0.05A	0.5W	
2SC1846	SI-N	120V	0.05A	0.5W	
2SC1847	SI-N	50V	1.5A	1.2W	
2SC1855	SI-N	20V	20mA	0.25W	550MHz
2SC1871	SI-N	450V	15A	150W	<1/3us
2SC1879	N-DARL+D	120V	2A	0.8W	B>1
2SC1890	SI-N	90V	0.05A	0.3W	200MHz
2SC1895	SI-N	1500V	6A	50W	2MHz
2SC1906	SI-N	19V	0.05A	0.3W	
2SC1907	SI-N	30V	0.05A		1100MHz
2SC1913	SI-N	150V	1A	15W	120MHz
2SC1914	SI-N	90V	50mA	0.2W	150MHz
2SC1921	SI-N	250V	0.05A	0.6W	
2SC1922	SI-N	1500V	2.5A	50W	
2SC1923	SI-N	30V	20mA	10mW	550MHz
2SC1929	SI-N	300V	0.4A	25W	80MHz
2SC1941	SI-N	160V	50mA	0.8W	
2SC1944	SI-N	80V	6A	PQ=16W	
2SC1945	SI-N	80V	6A	20W	
2SC1946A	SI-N	35V	7A	50W	
2SC1947	SI-N	35V	1A	4W	175MHz
2SC1953	SI-N	150V	0.05A	1.2W	70MHz
2SC1957	SI-N	40V	1A	1.8W	27MHz
2SC1959	SI-N	30V	0.5A	0.5W	200MHz
2SC1967	SI-N	35V	2A	8W	470MHz
2SC1968	SI-N	35V	5A	3W	470MHz
2SC1969	SI-N	60V	6A	20W	
2SC1970	SI-N	40V	0.6A	5W	
2SC1971	SI-N	35V	2A	12.5W	
2SC1972	SI-N	35V	3.5A	25W	
2SC1975	SI-N	120V	2A	3.8W	50MHz
2SC1980	SI-N	120V	20mA	0.25W	200MHz
2SC1984	SI-N	100V	3A	30W	B=700
2SC1985	SI-N	80V	6A	40W	10MHz
2SC2023	SI-N	300V	2A	40W	10MHz
2SC2026	SI-N	30V	0.05A	0.25W	
2SC2027	SI-N	1500/800V	5A	50W	
2SC2036	SI-N	80V	1A	PQ=1..4W	
2SC2053	SI-N	40V	0.3A	0.6W	500MHz
2SC2055	SI-N	18V	0,3A	0,5W	
2SC2058	SI-N	40V	0.05A	0.25W	
2SC2060	SI-N	40V	0.7A	0.75W	150MHz
2SC2061	SI-N	80V	1A	0.75W	120MHz
2SC2068	SI-N	300V	0.05A		95MHz
2SC2073	SI-N	150V	1.5A	25W	4MHz
2SC2078	SI-N	80V	3A	10W	150MHz
2SC2086	SI-N	75V	1A	0.45W	27MHz
2SC2092	SI-N	75V	3A	5W	27MHz
2SC2094	SI-N	40V	3.5A	PQ>15W	175MHz
2SC2097	SI-N	50V	15A	PQ=85W	
2SC2120	SI-N	30V	0.8A	0.6W	120MHz
2SC2122	SI-N	800V	10A	50W	
2SC2166	SI-N	75V	4A	12.5W	RFPOWER
2SC2168	SI-N	200V	2A	30W	10MHz
2SC2200	SI-N	500V	7A	40W	1US
2SC2209	SI-N	50V	1.5A	10W	150MHz
2SC2216	SI-N	45V	50mA	0.3W	300MHz
2SC2228	SI-N	160V	0.05A	0.75W	>50
2SC2229	SI-N	200V	50mA	0.8W	120MHz
2SC2230	SI-N	200V	0.1A	0.8W	50MHz
2SC2233	SI-N	200V	4A	40W	8MHz
2SC2235	SI-N	120V	0.8A	0.9W	120MHz
2SC2236	SI-N	30V	1.5A	0.9W	120MHz
2SC2237	SI-N	35V	2A	PQ>7.5W	175MHz
2SC2238	SI-N	160V	1.5A	25W	100MHz

2SC2240	SI-N	120V	50mA	.3W	100MHz
2SC2261	SI-N	180V	8A	80W	15MHz
2SC2267	SI-N	400/360V	0.1A	0.4W	
2SC2270	SI-N	50V	5A	10W	100MHz
2SC2271	SI-N	300V	0.1A	0.9W	50MHz
2SC2275	SI-N	120V	1.5A	25W	200MHz
2SC2283	SI-N	38V	0.75A	2.8W	500MHz
2SC2287	SI-N	38V	1.5A	7.1W	175MHz
2SC2295	SI-N	30V	0.03A	0.2W	250MHz
2SC2307	SI-N	500V	12A	100W	18MHz
2SC2308	SI-N	55V	0.1A	0.2W	230MHz
2SC2310	SI-N	55V	0.1A	0.2W	230MHz
2SC2312	SI-N	60V	6A	18.5W	27MHz
2SC2314	SI-N	45V	1A	5W	
2SC2320	SI-N	50V	0,2A	0,3W	
2SC2329	SI-N	38V	0.75A	2W	175MHz
2SC2331	SI-N	150V	2A	15W	POWER
2SC2333	SI-N	500/400V	2A	40W	
2SC2334	SI-N	150V	7A	40W	POWER
2SC2335	SI-N	500V	7A	40W	POWER
2SC2336B	SI-N	250V	1.5A	25W	95MHz
2SC2344	SI-N	180V	1.5A	25W	120MHz
2SC2347	SI-N	15V	50mA	250mW	650MHz
2SC2362	SI-N	120V	50mA	0.4W	130MHz
2SC2363	SI-N	120V	50mA	0.5W	130MHz
2SC2365	SI-N	600V	6A	50W	POWER
2SC2369	SI-N	25V	70mA	0.25W	4.5GHz
2SC2383	SI-N	160V	1A	0.9W	100MHz
2SC2389	SI-N	120V	50mA	0.3W	140MHz
2SC2407	SI-N	35V	0.15A	0.16W	500MHz
2SC2412	SI-N	50V	0.1A		180MHz
2SC2433	SI-N	120V	30A	150W	80MHz
2SC2440	SI-N	450V	5A	40W	
2SC2458	SI-N	50V	0.15A	0.2W	80MHz
2SC2466	SI-N	30V	0.05A		2.2GHz
2SC2482	SI-N	300V	0.1A	0.9W	50MHz
2SC2485	SI-N	100V	6A	70W	15MHz
2SC2486	SI-N	120V	7A	80W	15MHz
2SC2491	SI-N	100V	6A	40W	15MHz
2SC2497	SI-N	70V	1.5A	5W	150MHz
2SC2498	SI-N	30V	0.05A	0.3W	3.5GHz
2SC2508	SI-N	40V	6A	50W	175MHz
2SC2510	SI-N	55V	20A	250W	28MHz
2SC2512	SI-N	30V	50mA	TUNE	900MHz
2SC2516	SI-N	150V	5A	30W	<0.5/2us
2SC2517	SI-N	150V	5A	30W	<0.5/2us
2SC2538	SI-N	40V	0.4A	0.7W	
2SC2539	SI-N	35V	4A	17W	175MHz
2SC2542	SI-N	450V	5A	40W	
2SC2547	SI-N	120V	0.1A	0.4W	
2SC2551	SI-N	300V	0.1A	0.4W	80MHz
2SC2552	SI-N	500V	2A	20W	
2SC2553	SI-N	500V	5A	40W	1us
2SC2562	SI-N	60V	5A	25W	0.1us
2SC2563	SI-N	120V	8A	80W	90MHz
2SC2570A	SI-N	25V	70mA	0.6W	
2SC2579	SI-N	160V	8A	80W	20MHz
2SC2581	SI-N	200V	10A	100W	
2SC2590	SI-N	120V	0.5A	5W	250MHz
2SC2592	SI-N	180V	1A	20W	250MHz
2SC2603	SI-N	50V	0.2A	0.3W	
2SC2610	SI-N	300V	0.1A	0.8W	80MHz
2SC2611	SI-N	300V	0.1A	0.8W	80MHz
2SC2621E	SI-N	300V	0.2A	10W	>50MHz
2SC2625	SI-N	450V	10A	80W	
2SC2630	SI-N	35V	14A	100W	
2SC2631	SI-N	150V	50mA	0,75W	160MHz
2SC2632	SI-N	150V	50mA	1W	160MHz
2SC2634	SI-N	60V	0.1A	0.4W	200MHz
2SC2653	SI-N	350V	0.2A	15W	>50MHz
2SC2654	SI-N	40V	7A	40W	
2SC2655	SI-N	50V	2A	0.9W	0.1us

2SC2656	SI-N	450V	7A	80W	<1.5/4.5
2SC2660	SI-N	200V	2A	30W	30MHz
2SC2668	SI-N	30V	20mA	0.1W	550MHz
2SC2671	SI-N	15V	80mA	0.6W	5.5GHz
2SC2682	SI-N	180V	0.1A	8W	180MHz
2SC2690	SI-N	120V	1.2A	20W	160MHz
2SC2694	SI-N	35V	20A	140W	
2SC2705	SI-N	150V	50mA	0.8W	200MHz
2SC2706	SI-N	140V	10A	100W	90MHz
2SC2712	SI-N	50V	0.15A	0.15W	80MHz
2SC2714	SI-N	30V	20mA	0.1W	550MHz
2SC2717	SI-N	30V	50mA	0.3W	300MHz
2SC2724	SI-N	30V	30mA		200MHz
2SC2749	SI-N	500V	10A	100W	50MHz
2SC2750	SI-N	150V	15A	100W	POWER
2SC2751	SI-N	500V	15A	120W	50MHz
2SC2752	SI-N	500V	0.5A	10W	<1/3.5
2SC2753	SI-N	17V	0.07A	0.3W	5GHz
2SC2759	SI-N	30V	50mA	0.2W	2.3GHz
2SC2786	SI-N	20V	20mA		600MHz
2SC2787	SI-N	50V	30mA	0.3W	250MHz
2SC2791	SI-N	900V	5A	100W	
2SC2792	SI-N	850V	2A	80W	
2SC2793	SI-N	900V	5A	100W	
2SC2802	SI-N	300V	0.2A	10W	80MHz
2SC2808	SI-N	100V	50mA	0.5W	140MHz
2SC2810	SI-N	500V	7A	50W	18MHz
2SC2812	SI-N	55V	0.15A	0.2W	100MHz
2SC2814	SI-N	30V	0.03A	F	320MHz
2SC2825	SI-N	80V	6A	70W	B>500
2SC2837	SI-N	150V	10A	100W	70MHz
2SC2839	SI-N	20V	30mA	0.15W	320MHz
2SC2851	SI-N	36V	0.3A	1W	1.5GHz
2SC2873	SI-N	50V	2A	0.5W	120MHz
2SC2878	SI-N	20V	0.3A	0.4W	30MHz
2SC2879	SI-N	45V	25A	PEP=100W	28MHz
2SC2882	SI-N	90V	0.4A	0.5W	100MHz
2SC288A	SI-N	35V	20mA	0.15W	
2SC2898	SI-N	500V	8A	50W	
2SC2901	SI-N	40V	0.2A	0.6W	<12/18
2SC2908	SI-N	200V	5A	50W	50MHz
2SC2910	SI-N	160V	70mA	0.9W	150MHz
2SC2911	SI-N	180V	140mA	10W	150MHz
2SC2912	SI-N	200V	140mA	10W	150MHz
2SC2922	SI-N	180V	17A	200W	50MHz
2SC2923	SI-N	300V	0.1A		140MHz
2SC2928	SI-N	1500V	5A	50W	
2SC2939	SI-N	500V	10A	100W	2.5us
2SC2958	SI-N	160V	0.5A	1W	
2SC2979	SI-N	800V	3A	40W	
2SC2987	SI-N	140V	12A	120W	60MHz
2SC2988	SI-N	36V	0.5A		175MHz
2SC2999	SI-N	20V	30mA		750MHz
2SC3001	SI-N	20V	3A	PQ=7W	175MHz
2SC3019	SI-N	35V	0.4A	0.6W	520MHz
2SC3020	SI-N	35V	1A	10W	
2SC3022	SI-N	35V	7A	50W	
2SC3026	SI-N	1700V	5A	50W	POWER
2SC3030	N-DARL	900V	7A	80W	
2SC3039	SI-N	500V	7A	52W	
2SC3042	SI-N	500/400V	12A	100W	
2SC3052F	SI-N	50V	0.2A	0.15W	200MHz
2SC3063	SI-N	300V	0.1A	1.2W	140MHz
2SC3067	2xSI-N	130V	50mA	0.5W	160
2SC3068	SI-N	30V	0.3A	Ueb=15V	B>8
2SC3071	SI-N	120V	0.2A	Ueb=15V	B>
2SC3073	SI-N	30V	3A	15W	100MHz
2SC3074	SI-N	60V	5A	20W	120MHz
2SC3075	SI-N	500V	0.8A	10W	1/1.5us
2SC3089	SI-N	800V	7A	80W	
2SC3101	SI-N	250V	30A	200W	25MHz
2SC3102	SI-N	35V	18A	170W	520MHz

2SC3112	SI-N	50V	0.15A	0.4W	100MHz
2SC3116	SI-N	180V	0.7A	10W	120MHz
2SC3117	SI-N	180V	1.5A	10W	120MHz
2SC3133	SI-N	60V	6A	1.5W	27MHz
2SC3148	SI-N	900V	3A	40W	1us
2SC3150	SI-N	900V	3A	50W	15MHz
2SC3153	SI-N	900V	6A	100W	
2SC3157	SI-N	150V	10A	60W	
2SC3158	SI-N	500V	7A	60W	
2SC3164	SI-N	500V	10A	100W	
2SC3169	SI-N	500V	2A	25W	>8MHz
2SC3175	SI-N	400V	7A	50W	40MHz
2SC3178	SI-N	1200V	2A	60W	
2SC3179	SI-N	60V	4A	30W	15MHz
2SC3180N	SI-N	80V	6A	60W	30MHz
2SC3181N	SI-N	120V	8A	80W	30MHz
2SC3182N	SI-N	140V	10A	100W	30MHz
2SC3195	SI-N	30V	20mA	0.1W	550MHz
2SC3199	SI-N	60V	0.15A	0.2W	130MHz
2SC3200	SI-N	120V	0.1A	0.3W	100MHz
2SC3202	SI-N	35V	0.5A	0.5W	300MHz
2SC3203	SI-N	35V	0.8A	0.6W	120MHz
2SC3205	SI-N	30V	2A	1W	120MHz
2SC3206	SI-N	150V	0.5A	0.8W	120MHz
2SC3210	SI-N	500V	10A	100W	1us
2SC3211	SI-N	800V	5A	70W	>3MHz
2SC3212	SI-N	800V	7A	3W	3.5MHz
2SC3225	SI-N	40V	2A	0.9W	1us
2SC3231	SI-N	200V	4A	40W	8MHz
2SC3240	SI-N	50V	25A	110W	30MHz
2SC3242	SI-N	20V	2A	0.9W	80MHz
2SC3244E	SI-N	100V	0.5A	0.9W	130MHz
2SC3245A	SI-N	150V	0.1A	0.9W	200MHz
2SC3246	SI-N	30V	1.5A	0.9W	130MHz
2SC3247	SI-N	50V	1A	.9W	130MHz B>
2SC3257	SI-N	250V	10A	40W	1/3.5us
2SC3258	SI-N	100V	5A	30W	120MHz
2SC3260	N-DARL	800V	3A	50W	B>10
2SC3262	N-DARL	800V	10A	100W	
2SC3263	SI-N	230V	15A	130W	
2SC3264	SI-N	230V	17A	200W	60MHz
2SC3271	SI-N	300V	1A	5W	80MHz
2SC3277	SI-N	500V	10A	90W	20MHz
2SC3279	SI-N	10V	2A	0.75W	150MHz
2SC3280	SI-N	160V	12A	120W	30MHz
2SC3281	SI-N	200V	15A	150W	30MHz
2SC3284	SI-N	150V	14A	125W	60MHz
2SC3293	N-DARL+D	50V	1.2A	20W	180
2SC3297	SI-N	30V	3A	15W	100MHz
2SC3299	SI-N	60V	5A	20W	0.1us
2SC3300	SI-N	100V	15A	100W	
2SC3303	SI-N	100V	5A	20W	0.2us
2SC3306	SI-N	500V	10A	100W	1us
2SC3307	SI-N	900V	10A	150W	1us
2SC3309	SI-N	500V	2A	20W	1us
2SC3310	SI-N	500V	5A	30W	1us
2SC3311	SI-N	60V	0.1A	0.3W	150MHz
2SC3320	SI-N	500V	15A	80W	
2SC3326	SI-N	20V	0.3A	0.15W	30MHz
2SC3327	SI-N	50V	0.3A	0.2W	30MHz
2SC3328	SI-N	80V	2A	0.9W	100MHz
2SC3330	SI-N	60V	0.2A	0.3W	200MHz
2SC3331	SI-N	60V	0.2A	0.5W	200MHz
2SC3332	SI-N	180V	0.7A	0.7W	120MHz
2SC3334	SI-N	250V	50mA	0.9W	100MHz
2SC3345	SI-N	60V	12A	40W	90MHz
2SC3346	SI-N	80V	12A	40W	0.2us
2SC3355	SI-N	20V	0.1A	0.6W	6.5GHz
2SC3356	SI-N	20V	0.1A	0.2W	7GHz
2SC3377	SI-N	40V	1A	0.6W	150MHz
2SC3378	SI-N	120V	0.1A	0.2W	100MHz
2SC3379	SI-N	20V	1.5A	PQ=3W	

2SC3381	2xSI-N	80V	0.1A	0.4W	170MHz
2SC3383	SI-N	60V	0.2A	0.5W	250MHz
2SC3397	SI-N	50V	0.1A	46K/	250MHz
2SC3399	SI-N	50V	0.1A		250MHz
2SC3400	SI-N	50V	0.1A	22K/	250MHz
2SC3401	SI-N	50V	.1A		46K/23KOHM
2SC3402	SI-N	50V	0.1A	10K/	250MHz
2SC3405	SI-N	900V	0.8A	20W	1us
2SC3409	SI-N	900V	2A	80W	.8uS
2SC3416	SI-N	200V	0.1A	5W	70MHz
2SC3419	SI-N	40V	0.8A	5W	100MHz
2SC3420	SI-N	50V	5A	10W	100MHz
2SC3421O	SI-N	120V	1A	1.5W	BJT O-G
2SC3421Y	SI-N	120V	1A	10W	120MHz
2SC3422Y	SI-N	40V	3A	10W	100MHz
2SC3423	SI-N	150V	50mA	5W	200MHz
2SC3425	SI-N	500V	0.8A	10W	
2SC3446	SI-N	800V	7A	40W	18MHz
2SC3447	SI-N	800V	5A	50W	18MHz
2SC3456	SI-N	1100/800V	1.5A	40W	
2SC3457	SI-N	1100V	3A	50W	
2SC3460	SI-N	1100V	6A	100W	
2SC3461	SI-N	1100/800V	8A	120W	
2SC3466	SI-N	1200/650V	8A	120W	
2SC3467	SI-N	200V	0.1A	1W	150MHz
2SC3468	SI-N	300V	0.1A	1W	150MHz
2SC3486	SI-N	1500V	6A	120W	
2SC3502	SI-N	200V	0.1A	1.2W	
2SC3503	SI-N	300V	0.1A	7W	150MHz
2SC3504	SI-N	70V	0.05A	0.9W	500MHz
2SC3505	SI-N	900V	6A	80W	
2SC3507	SI-N	1000/800V	5A	80W	
2SC3509	N-DARL+D	900V	10A	100W	0.
2SC3514	SI-N	180V	0.1A	10W	200MHz
2SC3518	SI-N	60V	5A	10W	
2SC3520	SI-N	500V	18A	130W	18MHz
2SC3526	SI-N	110V	0.15A 7A	30W	1us
2SC3528	SI-N	500V	20A	125W	
2SC3549	SI-N	900V	3A	40W	
2SC3552	SI-N	1100V	12A	150W	15MHz
2SC3568	SI-N	150V	10A	30W	
2SC3571	SI-N	500V	7A	30W	
2SC3577	SI-N	850V	5A	80W	6MHz
2SC3581	SI-N	55V	0.4A	0.9W	150MHz
2SC3591	SI-N	400V	7A	50W	
2SC3595	SI-N	30V	0.5A	5W	2GHz
2SC3596	SI-N	80V	0.3A	8W	700MHz
2SC3597	SI-N	80V	0.5A	10W	800MHz
2SC3599	SI-N	120V	0.3A	8W	500MHz
2SC3600	SI-N	200V	0.1A	7W	400MHz
2SC3601	SI-N	200V	0.15A	7W	400MHz
2SC3608	SI-N	20V	0.08A		6.5GHz
2SC3611	SI-N	50V	0.15A	4W	300MHz
2SC3616	SI-N	25V	0.7A		250MHz
2SC3621	SI-N	150V	1.5A	10W	100MHz
2SC3623	SI-N	60V	0.15A	0.25W	B=1K
2SC3632	SI-N	600V	1A	10W	30MHz
2SC3636	SI-N	900/500V	7A	80W	
2SC3642	SI-N	1200V	6A	100W	200ns
2SC3655	SI-N	50V	0.1A	0.4W	46/23K
2SC3656	SI-N	50V	0.1A	0.4W	10K/10
2SC3659	SI-N+D	1700/800V	5A	50W	
2SC3668	SI-N	50V	2A	1W	100MHz
2SC3669	SI-N	80V	2A	1W	0.2us
2SC3675	SI-N	1500/900V	0.1A	10W	
2SC3678	SI-N	900V	3A	80W	
2SC3679	SI-N	900/800V	5A	100W	
2SC3680	SI-N	900/800V	7A	120W	6MHz
2SC3684	SI-N+D	1500V	10A	150W	
2SC3688	SI-N	1500V	10A	150W	0.2us
2SC3692	SI-N	100V	7A	30W	<300/180
2SC373	SI-N	35V	0.1A	0.2W	B>200

2SC3746	SI-N	80V	5A	20W	100MHz
2SC3748	SI-N	80V	10A	30W	100/600ns
2SC3752	SI-N	1100/800V	3A	30W	
2SC3781	SI-N	120V	0.4A	15W	500MHz
2SC3782	SI-N	200V	0.2A	15W	400MHz
2SC3783	SI-N	800V	5A	100W	
2SC3787	SI-N	180V	0.14A	10W	150MHz
2SC3788	SI-N	200V	0.1A	5W	150MHz
2SC3789	SI-N	300V	0.1A	7W	70MHz
2SC3790	SI-N	300V	0.1A	7W	150MHz
2SC3792	SI-N	50V	0.5A	0.5W	250MHz
2SC3795A	SI-N	900V	5A	40W	
2SC3807	SI-N	30V	2A	15W	260MHz
2SC3808	N-DARL	80V	2A	B>80	170MHz
2SC380TM	SI-N	30V	50mA	0.3W	100MHz
2SC3811	SI-N	40V	0.1A	0.4W	450MHz
2SC3831	SI-N	500V	10A	100W	
2SC3833	SI-N	500/400V	12A	100W	
2SC3842	SI-N	600V	10A	70W	32MHz
2SC3844	SI-N	600V	15A	75W	30MHz
2SC3851	SI-N	80V	4A	25W	15MHz
2SC3852	SI-N	80V	3A	25W	15MHz
2SC3855	SI-N	200V	10A	100W	20MHz
2SC3857	SI-N	200V	15A	150W	20MHz
2SC3858	SI-N	200V	17A	200W	20MHz
2SC3866	SI-N	900V	3A	40W	
2SC3868	SI-N	500V	1.5A	25W	0.7us
2SC3883	SI-N+D	1500V	6A	50W	
2SC3884A	SI-N	1500V	6A	50W	
2SC3886A	SI-N	1500V	8A	50W	0.1us
2SC388A	SI-N	25V	50mA	0.3W	300MHz
2SC3890	SI-N	500V	7A	30W	500NS
2SC3892A	SI-N+D	1500V	7A	50W	0.4us
2SC3893A	SI-N+D	1500V	8A	50W	
2SC3895	SI-N	1500/800V	8A	70W	
2SC3896	SI-N	1500V	8A	70W	
2SC3897	SI-N	1500V	10A	70W	
2SC3902	SI-N	180V	1.5A	10W	120MHz
2SC3907	SI-N	180V	12A	130W	30MHz
2SC3927	SI-N	900V	10A	120W	
2SC394	SI-N	25V	0.1A	200MC	RF
2SC3940	SI-N	30V	1A	1W	200MHz
2SC3943	SI-N	110V	0.15A	2W	300MHz
2SC3944	SI-N	150V	1A	40W	300MHz
2SC3948	SI-N	850V	10A	75W	20MHz
2SC3950	SI-N	30V	0.5A	5W	
2SC3952	SI-N	80V	0.5A	10W	700MHz
2SC3953	SI-N	120V	0.2A	8W	400MHz
2SC3954	SI-N	120V	0.3A	8W	400MHz
2SC3955	SI-N	200V	0.1A	7W	300MHz
2SC3956	SI-N	200V	0.2A	7W	70MHz
2SC3964	SI-N	40V	2A	1.5W	1us
2SC3972	SI-N	800/500V	5A	40W	
2SC3973A	SI-N	900V	7A	45W	
2SC3979A	SI-N	800V	3A	2W	10MHz
2SC3987	N-DARL+D	50V	3A	15W	
2SC3996	SI-N	1500/800V	15A	180W	
2SC3998	SI-N	1500V	25A	250W	POWER
2SC3999	SI-N	300V	0.1A	0.75W	300MHz
2SC4004	SI-N	900/800V	1A	30W	<1/4
2SC4020	SI-N	900V	3A	50W	1us
2SC4024	SI-N	100V	10A	35W	B>300
2SC4029	SI-N	230V	15A	150W	30MHz
2SC4043	SI-N	20V	50mA	0.15W	3.2GHz
2SC4046	SI-N	120V	0.2A	8W	350MHz
2SC4052	SI-N	600V	3A	40W	20MHz
2SC4056	SI-N	600V	8A	45W	
2SC4059	SI-N	600/450V	15A	130W	
2SC4064	SI-N	50V	12A	35W	40MHz
2SC4107	SI-N	500/400V	10A	60W	
2SC4119	N-DARL+D	1500V	15A	250W	B
2SC4123	SI-N+D	1500V	7A	60W	

2SC4125	SI-N+D	1500/800V	10A	70W	
2SC4131	SI-N	100V	15A	60W	18MHz
2SC4135	SI-N	120V	2A	15W	200MHz
2SC4137	SI-N	25V	0.1A		300MHz
2SC4138	SI-N	500V	10A	80W	<1/3.5us
2SC4153	SI-N	200V	7A	30W	0.5us
2SC4157	SI-N	600V	10A	100W	
2SC4159	SI-N	180V	1.5A	15W	100MHz
2SC4161	SI-N	500V	7A	30W	
2SC4169	N-DARL+D	50V	1.2A	1W	B=4K
2SC4199	SI-N	1400V	10A	100W	
2SC4200	SI-N	20V	0.6A	5W	2.5GHz
2SC4204	SI-N	30V	0.7A	0.6W	
2SC4231	SI-N	1200/800V	2A	30W	
2SC4235	SI-N	1200/800V	3A	80W	
2SC4236	SI-N	1200/800V	6A	100W	
2SC4237	SI-N	1200/800V	10A	150W	
2SC4242	SI-N	450/400V	7A	40W	
2SC4256	SI-N	1500V	10A	175W	6MHz
2SC4278	SI-N	150V	10A	100W	30MHz
2SC4288A	SI-N	1600/600V	12A	200W	
2SC4289A	SI-N	1500V	16A	200W	
2SC4290A	SI-N	1500V	20A	200W	
2SC4297	SI-N	500V	12A	75W	10MHz
2SC4298	SI-N	500V	15A	80W	10MHz
2SC4300	SI-N	900V	5A	75W	1/6us
2SC4304	SI-N	800V	3A	35W	
2SC4308	SI-N	30V	0.3A	0.6W	2.5GHz
2SC4313	SI-N	900V	10A	100W	0.5us
2SC4381	SI-N	150V	2A	25W	15MHz
2SC4382	SI-N	200V	2A	25W	15MHz
2SC4386	SI-N	160/120V	8A	75W	20MHz
2SC4387	SI-N	200V	10A	80W	20MHz
2SC4388	SI-N	200V	15A	85W	20MHz
2SC4408	SI-N	80V	2A	0.9W	100/600ns
2SC4429	SI-N	1100/800V	8A	60W	
2SC4430	SI-N	1100V	12A	65W	15MHz
2SC4431	SI-N	120V	1.5A	20W	150MHz
2SC4439	SI-N	180V	0.3A	8W	400MHz
2SC4467	SI-N	160/120V	8A	80W	20MHz
2SC4468	SI-N	200V	10A	80W	20MHz
2SC4484	SI-N	30V	2.5A	1W	250MHz
2SC4488	SI-N	120V	1A	1W	120MHz
2SC4511	SI-N	120V	6A	30W	20MHz
2SC4512	SI-N	120V	6A	50W	20MHz
2SC4517	SI-N	900V	3A	30W	6MHz
2SC4517A	SI-N	1000V	3A	30W	0.5us
2SC4531	SI-N+D	1500V	10A	50W	
2SC4532	SI-N	1700V	10A	200W	2uS
2SC4538	SI-N	900V	5A	80W	
2SC454	SI-N	30V	0.1A		230MHz
2SC4542	SI-N	1500V	10A	50W	
2SC4547	N-DARL+D	85V	3A	30W	B>2K
2SC4557	SI-N	900V	10A	80W	<1/5.5us
2SC4560	SI-N	1500V	10A	80W	
2SC458	SI-N	30V	0.1A	230MC	UNI
2SC4582	SI-N	600V	100A	65W	20MHz
2SC460	SI-N	30V	0.1A	0.2W	230MHz
2SC461	SI-N	30V	0.1A	0.2W	230MHz
2SC4744	SI-N	1500V	6A		POWER
2SC4745	SI-N	1500V	6A		
2SC4747	SI-N	1500V	10A	50W	0.3us
2SC4758	SI-N	1500V	8A	50W	HI-RES
2SC4769	SI-N+D	1500V	7A	60W	
2SC4770	SI-N	1500/800V	7A	60W	
2SC4793	SI-N	230V	1A	2W	100MHz
2SC4804	SI-N	900V	3A	30W	0.3us
2SC4820	SI-N	450V	6A	30W	12MHz
2SC4826	SI-N	200V	3A	1.3W	300MHz
2SC4834	SI-N	500V	8A	45W	<0.3/1.4
2SC4883A	SI-N	180V	2A	20W	120MHz
2SC4891	SI-N	1500V	15A	75W	

2SC4908	SI-N	900V	3A	35W	1us
2SC4924	SI-N	800V	10A	70W	
2SC4977	SI-N	450V	7A	40W	
2SC5002	SI-N	1500V	7A	80W	
2SC5003	SI-N+D	1500V	7A	80W	
2SC5027	SI-N	1100V	3A	50W	0.3us
2SC5030	SI-N	50V	5A	1.3W	150MHz
2SC5045	SI-N	1600V	15A	75W	
2SC5047	SI-N	1600V	25A	250W	
2SC5048	SI-N	1500V	12A	50W	0.3us
2SC5070	SI-N	30V	2A	1.5W	B>800
2SC5086	SI-N	20V	80mA		7GHZ
2SC509	SI-N	35V	0.5A	0.6W	60MHz
2SC5144	SI-N	1700V	20A	200W	
2SC5148	SI-N	1500V	8A	50W	0.2us
2SC5149	SI-N+D	1500V	8A	50W	0.2us
2SC5150	SI-N	1700V	10A	50W	03us
2SC5171	SI-N	180V	2A	20W	200MHz
2SC5198	SI-N	140V	10A	100W	30MHz
2SC5207	SI-N	1500V	10A	50W	0.4us
2SC5242	SI-N	230V	15A	130W	30MHz
2SC5244A	SI-N	1600V	30A	200W	
2SC5296	SI-N+D	1500V	8A	60W	
2SC5297	SI-N	1500V	8A	60W	
2SC5299	SI-N	1500V	10A	70W	0.2US
2SC535	SI-N	20V	20mA	0.1W	0.700M
2SC536	SI-N	40V	0.1A	180MC	UNI
2SC620	SI-N	50V	0.2A	0.25W	UNI
2SC643	SI-N	1100V	2.5A	50W	
2SC644	SI-N	30V	50mA	0.25W	
2SC645	SI-N	30V	30mA	0.14W	200MHz
2SC710	SI-N	30V	0.03A		200MHz
2SC711	SI-N	30V	0.05A		150MHz
2SC712	SI-N	30V	0.5A		150MHz
2SC717	SI-N	30V	50mA	0.2W	600MHz
2SC730	SI-N	40V	0.4A	PQ=1.5W	
2SC732	SI-N	50V	0.15A	0.4W	150MHz
2SC735	SI-N	35V	0.4A	0.3W	UNI
2SC752	SI-N	15V	100mA	0.1W	
2SC756	SI-N	40V	4A	10W	65MHz
2SC784	SI-N	40V	0.02A	500MC	RF
2SC815	SI-N	60V	0.2A	0.25W	200MHz
2SC828	SI-N	30V	0.05A	0.25W	UNI
2SC829	SI-N	30V	30mA	0.4W	230MHz
2SC839	SI-N	50V	0.03A		250MHz
2SC867	SI-N	400V	1A	23W	8MHz
2SC869	SI-N	160V	30mA	0.2W	150MHz
2SC898A	SI-N	150V	7A	80W	15MHz
2SC900	SI-N	30V	0.03A		100MHz
2SC930	SI-N	15V	0.03A	300MC	RF
2SC936	SI-N	1000V	1A	22W	POWER
2SC941	SI-N	35V	20mA	0.2W	120MHz
2SC943	SI-N	60V	0.2A	0.3W	220MHz
2SC945	SI-N	50V	0.1A	250MC	UNI
2SC982	N-DARL	40V	0.3A	0.4W	
2SD1010	SI-N	50V	50mA	0.3W	200MHz
2SD1012	SI-N	20V	0.7A	0.25W	250MHz
2SD1018	SI-N	250V	4A	80W	B>250
2SD1027	N-DARL+D	20V	15A	100W	B>1
2SD1033	SI-N	200V	2A	20W	10MHz
2SD1036	SI-N	150/120V	15A	150W	
2SD1047	SI-N	160V	12A	100W	15MHz
2SD1048	SI-N	20V	0.7A	0.25W	250MHz
2SD1049	SI-N	120V	25A	100W	
2SD1051	SI-N	50V	1.5A	1W	150MHz
2SD1055	SI-N	40V	2A	0.75W	100MHz
2SD1062	SI-N	60V	12A	40W	10MHz
2SD1064	SI-N	60V	12A	80W	
2SD1065	SI-N	60V	15A	90W	
2SD1073	N-DARL	300V	4A	40W	B>1K
2SD1088	N-DARL	300V	6A	30W	B>2000
2SD1113K	N-DARL+D	300V	6A	40W	

2SD1128	N-DARL	150V	5A	30W	
2SD1135	SI-N	80V	4A	40W	
2SD1138	SI-N	200V	2A	30W	
2SD1140	N-DARL	30V	1.5A	0.9W	
2SD1145	SI-N	60V	5A	0.9W	120MHz
2SD1148	SI-N	140V	10A	100W	20MHz
2SD1153	SI-N	80V	1.5A	0.9W	
2SD1163A	SI-N	300V	7A	40W	
2SD1164	SI-N	150V	1.5A	10W	DAR+DI
2SD1173	SI-N+D	1500V	5A	70W	
2SD1187	SI-N	100V	10A	80W	10MHz
2SD1189	SI-N	40V	2A	5W	100MHz
2SD1192	N-DARL+D	70V	10A	40W	B=5K
2SD1196	N-DARL+D	110V	8A	40W	B=40
2SD1198	N-DARL	30V	1A	1W	150MHz
2SD1207	SI-N	60V	2A	1W	
2SD1210	N-DARL+D	150V	10A	80W	B=5
2SD1213	SI-N	60V	20A	50W	
2SD1225	SI-N	40V	1A	1W	150MHz
2SD1238	SI-N	120V	12A	80W	20MHz
2SD1244	SI-N+D	2500/900V	1A	50W	
2SD1246	SI-N	30V	2A	0.75W	
2SD1247	SI-N	30V	2.5A	1W	
2SD1254	SI-N	130V	3A	30W	
2SD1255	SI-N	130V	4A	35W	30MHz
2SD1263A	SI-N	400V	0.75A	35W	30MHz
2SD1264	SI-N	200V	2A	30W	POWER
2SD1265	SI-N	60V	4A	30W	25kHz
2SD1266	SI-N	60V	3A	35W	POWER
2SD1267	SI-N	60V	4A	40W	20MHz
2SD1270	SI-N	130V	5A	2W	30MHz
2SD1271	SI-N	130V	7A	40W	30MHz
2SD1272	SI-N	200V	1A	40W	25MHz
2SD1273	SI-N	80V	3A	40W	50MHz
2SD1274	SI-N	150V	5A	40W	40MHz
2SD1276	N-DARL	60V	4A	40W	
2SD1286	N-DARL+D	60V	1A	8W	B=1K-3
2SD1288	SI-N	120V	7A	70W	
2SD1289	SI-N	120V	8A	80W	
2SD1292	SI-N	120V	1A	0.9W	100MHz
2SD1293	SI-N	120V	1A	1W	100MHz
2SD1297	N-DARL+D	150V	25A	100W	
2SD1302	SI-N	25V	0.5A	0.6W	200MHz
2SD1306	SI-N	30V	0.7A	150mW	250MHz
2SD1308	N-DARL+D	150V	8A	40W	
2SD1313	SI-N	800V	25A	200W	6MHz
2SD1314	N-DARL+D	600V	15A	150W	
2SD1330	SI-N	25V	0.5A	0.6W	200MHz
2SD1347	SI-N	60V	3A	1W	150MHz
2SD1348	SI-N	60V	4A	10W	150MHz
2SD1350A	SI-N	600V	0.5A	1W	55MHz
2SD1376K	N-DARL+D	120V	1.5A	40W	
2SD1378	SI-N	80V	0.7A	10W	120MHz
2SD1379	N-DARL	40V	2A	10W	150MHz
2SD1380	SI-N	40V	2A	10W	100MHz
2SD1382	SI-N	120V	1A	10W	100MHz
2SD1384	SI-N	40V	2A	0.75W	100MHz
2SD1391	SI-N	1500V	5A	80W	
2SD1392	N-DARL+D	60V	5A	30W	B=800
2SD1397	SI-N+D	1500V	3.5A	50W	
2SD1398	SI-N+D	1500V	5A	50W	
2SD1399	SI-N+D	1500V	6A	80W	
2SD1403	SI-N	1500V	6A	120W	
2SD1404	SI-N+D	300V	7A	25W	1us
2SD1405	SI-N	50V	3A	25W	2us
2SD1406	SI-N	60V	3A	25W	0.8us
2SD1407	SI-N	100V	5A	30W	12MHz
2SD1408	SI-N	80V	4A	30W	8MHz
2SD1409	N-DARL+D	600V	6A	25W	1us
2SD1411	SI-N	100V	7A	30W	10MHz
2SD1413	N-DARL+D	60V	3A	20W	.01US
2SD1415	N-DARL+D	100V	7A	30W	0.8us

2SD1426	SI-N+D	1500V	3.5A		
2SD1427	SI-N+D	1500V	5A	80W	
2SD1428	SI-N+D	1500V	6A	80W	
2SD1432	SI-N	1500V	6A	80W	
2SD1439	SI-N+D	1500V	3A	50W	
2SD1441	SI-N+D	1500V	4A	80W	
2SD1446	N-DARL+D	500V	6A	40W	B>50
2SD1453	SI-N	1500V	3A	50W	
2SD1457	N-DARL+D	140V	6A	60W	
2SD1458	SI-N	20V	0.7A	1W	
2SD1468	SI-N	30V	1A	0.3..0.4W	150
2SD1491	N-DARL+D	70V	2A	10W	B>2K
2SD1496	SI-N	1500V	5A	50W	
2SD1497-02	SI-N	1500V	6A	50W	
2SD1504	SI-N	30V	0.5A	0.3W	300MHz
2SD1506	SI-N	60V	3A	10W	90MHz
2SD1508	N-DARL	30V	1.5A	10W	B>400
2SD1509	N-DARL+D	80V	2A	10W	0.4uS
2SD1511	N-DARL	100V	1A	1W	150MHz
2SD1521	N-DARL+D	50V	1.5A	2W	B>2K
2SD1525	N-DARL+D	100V	30A	150W	
2SD1526	SI-N	130V	1A	1W	200MHz
2SD1541	SI-N	1500V	3A	50W	
2SD155	SI-N	80V	3A	25W	
2SD1554	SI-N+D	1500V	3.5A	40W	1us
2SD1555	SI-N+D	1500V	5A	40W	1us
2SD1556	SI-N+D	1500V	6A	50W	1us
2SD1563A	SI-N	160V	1.5A	10W	80MHz
2SD1565	N-DARL+D	100V	5A	30W	
2SD1576	SI-N	1500V	2.5A	48W	
2SD1577	SI-N	1500V	5A	80W	
2SD1579	N-DARL+D	150V	1.5A	1W	
2SD1589	N-DARL+D	100V	5A	20W	
2SD1590	N-DARL+D	150V	8A	25W	
2SD1595	N-DARL+D	60V	5A	20W	B=6K
2SD1609	SI-N	160V	0.1A		NF/S-L
2SD1610	SI-N	200V	0.1A	1.3W	140MHz
2SD1624	SI-N	60V	3A	.5W	150MHz
2SD1632	N-DARL+D	1500V	4A	80W	
2SD1647	N-DARL+D	50V	2A	25W	
2SD1649	SI-N+D	1500/800V	2.5A	50W	
2SD1650	SI-N+D	1500/800V	3.5A	50W	
2SD1651	SI-N+D	1500/800V	5A	60W	
2SD1652	SI-N+D	1500V	6A	60W	3MHz
2SD1656	SI-N	1500V	6A	50W	3MHz
2SD1663	SI-N	1500V	5A	80W	0.5us
2SD1664	SI-N	40V	1A	0.5W	150MHz
2SD1666	SI-N	60V	3A	20W	
2SD1667	SI-N	60V	5A	25W	30MHz
2SD1668R	SI-N	60V	7A	30W	
2SD1669	SI-N	60V	12A	30W	
2SD1677	SI-N	1500V	5A	100W	0.5us
2SD1680	SI-N	330/200V	7A	70W	
2SD1681	SI-N	20V	1.2A	10W	150MHz
2SD1683	SI-N	60V	4A	10W	150MHz
2SD1684	SI-N	120V	1.2A	10W	150MHz
2SD1706	SI-N	130/80V	15A	80W	20MHz
2SD1707	SI-N	130/80V	20A	100W	
2SD1710	SI-N	1500/800V	5A	100W	
2SD1725	SI-N	120V	4A	20W	180MHz
2SD1729	SI-N+D	1500/700V	3.5A	60W	
2SD1730	SI-N+D	1500/700V	5A	100W	
2SD1739	SI-N	1500/700V	6A	100W	
2SD1740	N-DARL	150V	5A	25W	B=5000
2SD1758	SI-N	40V	2A	10W	100MHz
2SD1760	SI-N	60V	3A	15W	90MHz
2SD1761	SI-N	80V	3A	35W	
2SD1762	SI-N	60V	3A	25W	70MHz
2SD1763A	SI-N	120V	1.5A	20W	80MHz
2SD1764	N-DARL+D	60V	2A	20W	B>100
2SD1765	N-DARL+D	100V	2A	20W	B>1K
2SD1769	N-DARL+D	120V	6A	50W	

2SD1776	SI-N	80V	2A	25W	40MHz
2SD1783	N-DARL+D	60V	5A	30W	B=2K
2SD1785	N-DARL+D	120V	6A	30W	100MHz
2SD1790	N-DARL+D	200V	4A	25W	B=1K
2SD1791	N-DARL	100V	7A	30W	50MHz
2SD1796	N-DARL+D	60V	4A	25W	
2SD1802	SI-N	60V	3A	15W	150MHz
2SD1806	SI-N+D	40V	2A	15W	150MHz
2SD1809	N-DARL	60V	1A	0.9W	B>2K
2SD1812	SI-N	160V	1.5A	0.9W	
2SD1815	SI-N	120V	3A	20W	180MHz
2SD1817	SI-D	80V	3A	15W	B>2K
2SD1825	N-DARL+D	70V	4A	20W	
2SD1827	N-DARL+D	70V	10A	30W	20MHz
2SD1830	N-DARL+D	110V	8A	30W	B=4K
2SD1835	SI-N	60V	2A	60/580	150MHz
2SD1843	N-DARL+D	60V	1A	1W	B>2000
2SD1847	SI-N+D	1500/700V	5A	100W	
2SD1849	SI-N+D	1500/700V	7A	120W	
2SD1853	N-DARL+D	80V	1.5A	0.7W	B>
2SD1856	N-DARL+D	60V	5A	25W	
2SD1857	SI-N	120V	1.5A	1W	80MHz
2SD1858	SI-N	40V	1A	1W	150MHz
2SD1859	SI-N	80V	0.7A	1W	120MHz
2SD1862	SI-N	40V	2A	1W	100MHz
2SD1863	SI-N	120V	1A	1W	100MHz
2SD1864	SI-N	60V	3A	1W	90MHz
2SD1877	SI-N+D	1500/800V	4A	50W	
2SD1878	SI-N+D	1500V	5A	60W	0.3us
2SD1880	SI-N+D	1500V	8A	70W	
2SD1881	SI-N+D	1500V	10A	70W	
2SD1887	SI-N	1500/800V	10A	70W	
2SD1894	SI-N	160V	7A	70W	20MHz
2SD1895	N-DARL	160V	8A	100W	20MHz
2SD1913	SI-N	60V	3A	20W	100MHz
2SD1929	N-DARL+D	60V	2A	1.2W	
2SD1930	N-DARL	100V	2A	1.2W	B=500
2SD1933	N-DARL+D	80V	4A	30W	
2SD1944	SI-N	80V	3A	30W	50MHz
2SD1958	SI-N	200V	4.5A	30W	10MHz
2SD1959	SI-N	1400V	10A	50W	
2SD1978	N-DARL+D	120V	1.5A	0.9W	
2SD198	SI-N	300V	1A	25W	45MHz
2SD1991	SI-N	60V	0.1A	0.4W	150MHz
2SD1992	SI-N	30V	0.5A	0.6W	200MHz
2SD1994	SI-N	60V	1A	1W	200MHz
2SD1996	SI-N	25V	0.5A	0.6W	200MHz
2SD200	SI-N	1500V	2.5A	10W	
2SD2006	SI-N	80V	0.7A	1.2W	120MHz
2SD2007	SI-N	40V	2A	1.2W	100MHz
2SD2010	N-DARL	60V	2A	1.2W	B>1000
2SD2012	SI-N	60V	3A	25W	3MHz
2SD2018	N-DARL+D	60V	1A	5W	B>6K5
2SD2052	SI-N	150V	9A	100W	20MHz
2SD2061	SI-N	80V	3A	30W	8MHz
2SD2066	SI-N	160V	12A	120W	
2SD2088	N-DARL+D	60V	2A	0.9W	B>2K
2SD2125	SI-N+D	1500V	5A	50W	0.2us
2SD213	SI-N	110V	10A	100W	
2SD2136	SI-N	60V	3A	1.5W	30MHz
2SD2137A	SI-N	80V	3A	15W	30MHz
2SD2141	N-DARL+D	380V	6A	35W	B>15
2SD2144	SI-N	25V	0.5A		B>560
2SD2151	SI-N	130/80V	10A	30W	20MHz
2SD2159	SI-N	30V	2A	1W	110MHz
2SD2250	N-DARL	160V	7A	90W	B>5K
2SD2253	SI-N+D	1700V	6A	50W	
2SD2255	N-DARL	160V	7A	70W	20MHz
2SD2276	N-DARL	160V	8A	120W	B>5K
2SD2331	N-DARL+D	1500V	3A		
2SD234	SI-N	60V	3A	25W	AF-POWER
2SD2340	SI-N	130V	6A	50W	

2SD2375	SI-N	80V	3A	25W	B>500
2SD2386	N-DARL	140V	7A	70W	B>5K
2SD2389	N-DARL	160V	10A	100W	B>5K
2SD2390	N-DARL	160V	10A	100W	55MHz
2SD2394	SI-N	60V	3A	30W	
2SD2395	SI-N	50V	3A	25W	
2SD2399	N-DARL+D	80V	4A	30W	B=1K-
2SD2438	N-DARL+D	160V	8A	70W	B>5K
2SD2493	N-DARL	110V	6A	60W	60MHz
2SD2498	SI-N	1500V	6A	50W	
2SD2499	SI-N+D	1500V	6A	50W	
2SD287	SI-N	200V	10A	100W	8MHz
2SD313	SI-N	60V	3A	30W	8MHz
2SD325	SI-N	35V	1.5A	10W	8MHz
2SD350	SI-N	1500V	5A	22W	
2SD350A	SI-N	1500V	5A	22W	
2SD359	SI-N	40V	2A	10W	LOWFREQPO
2SD361	SI-N	60V	1.5A	10W	70MHz
2SD381	SI-N	130V	1.5A	20W	60MHz
2SD382	SI-N	130V	1.5A	20W	60MHz
2SD386	SI-N	200V	3A	25W	8MHz
2SD400	SI-N	25V	1A	0.9W	
2SD401	SI-N	200V	2A	20W	10MHz
2SD414	SI-N	120/80V	0.8A	10W	
2SD415	SI-N	120/100V	0.8A	10W	
2SD424	SI-N	160V	15A	150W	POWER
2SD438	SI-N	100V	0.7A	0.9W	100MHz
2SD467	SI-N	25V	0.7A	0.5W	280MHz
2SD468	SI-N	25V	1A	0.9W	280MHz
2SD471	SI-N	30V	1A	0.8W	UNI (EBC
2SD476	SI-N	70V	4A	40W	7MHz
2SD478	SI-N	200V	2A	30W	
2SD545	SI-N	25V	1.5A	0.5W	
2SD549	N-DARL	30V	1.5A	15W	B>4K
2SD552	SI-N	220V	15A	150W	4MHz
2SD553	SI-N	70V	7A	40W	10MHz
2SD555	SI-N	400V	15A	200W	7MHz
2SD556	SI-N	120V	15A	120W	8MHz
2SD560	N-DARL	100V	5A	30W	
2SD571	SI-N	60V	700mA	1W	110MHz
2SD592	SI-N	30V	1A	0.75W	200MHz
2SD596	SI-N	30V	0.7A		170MHz
2SD600K	SI-N	120V	1A	8W	
2SD602A	SI-N	60V	0.5A	0.2W	200MHz
2SD612	SI-N	25V	2A	10W	100MHz
2SD613	SI-N	100V	6A	40W	15MHz
2SD617	N-DARL	120V	8A	100W	
2SD637	SI-N	60V	0.1A	0.4W	150MHz
2SD661	SI-N	35V	0.1A	0.4W	200MHz
2SD662	SI-N	250V	0.1A	0.6W	50MHz
2SD666	SI-N	120V	0.05A		140MHz
2SD667	SI-N	120V	1A		140MHz
2SD669A	SI-N	160V	1.5A	1W	140MHz
2SD676	SI-N	160V	12A	125W	8MHz
2SD712	SI-N	100V	4A	30W	8MHz
2SD717	SI-N	70V	10A	80W	0.3us
2SD718	SI-N	120V	8A	80W	12MHz
2SD725	SI-N	1500V	6A	50W	POWER
2SD726	SI-N	100V	4A	40W	10MHz
2SD731	SI-N	170V	7A	80W	7MHz
2SD732	SI-N	150V	8A	80W	15MHz
2SD734	SI-N	25V	0.7A	0.6W	250MHz
2SD762	SI-N	60V	3A	25W	25kHz
2SD763	SI-N	120V	1A	0.9W	
2SD768	N-DARL+D	120V	6A	40W	B>1K
2SD773	SI-N	20V	2A	1W	110MHz
2SD774	SI-N	100V	1A	1W	95MHz
2SD781	SI-N	150V	2A	1W	0.6us
2SD786	SI-N	40V	0.3A	0.25W	
2SD787	SI-N	20V	2A	0.9W	80MHz
2SD788	SI-N	20/20V	2A	0.9W	100MHz
2SD789	SI-N	100/50V	1A	0.9W	80MHz

2SD794	SI-N	70V	3A	10W	60MHz
2SD795	SI-N	40V	3A	20W	95MHz
2SD798	N-DARL	600V	6A	30W	B>1K5
2SD799	N-DARL+D	400V	6A	30W	
2SD800	SI-N	750V	4A	30W	8MHz
2SD809	SI-N	100V	1A	10W	85MHz
2SD819	SI-N	1500V	3.5A	50W	
2SD820	SI-N	1500V	5A	50W	
2SD822	SI-N	1500/600V	7A	50W	
2SD826	SI-N	60V	5A	10W	120MHz
2SD829	N-DARL+D	150V	15A	100W	B=
2SD837	N-DARL	60V	4A	40W	
2SD844	SI-N	50V	7A	60W	15MHz
2SD850	SI-N	1500V	3A	25W	
2SD856	SI-N	60V	3A	35W	POWER
2SD863	SI-N	50V	1A	0.9W	
2SD864K	N-DARL+D	120V	3A	30W	
2SD867	SI-N	130V	10A	100W	3MHz
2SD871	SI-N+D	1500V	5A	50W	
2SD879	SI-N	30V	3A	0.75W	200MHz
2SD880	SI-N	60V	3A	30W	0.8us
2SD882	SI-N	30V	3A	10W	
2SD889	SI-N+D	1500V	4A	50W	
2SD892A	N-DARL	60V	0.5A	0.4W	B>2K
2SD894	N-DARL	30V	1.5A	10W	120MHz
2SD895	SI-N	100V	6A	60W	10MHz
2SD917	SI-N	330V	7A	70W	POWER
2SD92	SI-N	100V	3A	20W	
2SD921	N-DARL	200V	5A	80W	B>700
2SD946	N-DARL	30V	1A		
2SD947	N-DARL	40V	2A	5W	150MHz
2SD951	SI-N	1500V	3A	65W	
2SD958	SI-N	120V	0.02A	0.4W	200MHz
2SD965	SI-N	40V	5A	0.75W	150MHz
2SD966	SI-N	40V	5A	1W	150MHz
2SD968A	SI-N	120V	0.5A	1W	120MHz
2SD970	N-DARL+D	120V	8A	40W	B>1K
2SD972	N-DARL	50V	4A	30W	B=3K
2SD982	N-DARL	200V	5A	40W	B=3000
2SD986	N-DARL	150/80V	1.5A	10W	
2SD998	N-DARL	100V	1.5A	10W	B=7K
2SJ103	P-FET	50V	2.6mA	Up<2V	
2SJ109	P-FET	DUAL	30V		Id>2.6mA
2SJ113	P-FET	100V	10A	100W	OE35
2SJ117	P-FET	400V	2A	40W	35ns
2SJ162	P-FET	160V	7A	100W	1E
2SJ174	P-FET	60V	20A	75W	235ns
2SJ175	P-FET	60V	10A	25W	OE25
2SJ177	P-FET	60V	20A	75W	<0E085
2SJ182	P-FET	60V	3A	20W	OE28
2SJ200	P-FET	180V	10A	120W	
2SJ201	P-FET	200V	12A	150W	
2SJ306	P-FET	250V	3A	25W	<2E 3
2SJ307	P-FET	250V	6A	2W	<1E
2SJ353	P-FET	60V	1.5A	1W	<E37
2SJ449	P-FET	250V	6A	35W	<E8
2SJ72	P-FET	25V	30MA	0.6W	Up<2V
2SJ74	P-FET	25V	1mA	Up<2V	
2SJ77	P-FET	160V	0.5A	30W	
2SJ79	P-FET	200V	0.5A	30W	
2SK1010	N-FET	500V	6A	80W	<1E5
2SK1036	N-FET	250V	1A	2W	80ns
2SK1057	N-FET	140V	7A	100W	
2SK1058	N-FET	160V	7A	100W	1E
2SK107	N-FET	9V	20MA	250MW	
2SK108	N-FET	50V	20mA	0.3W	70E
2SK1081	N-FET	800V	7A	125W	380ns
2SK1082	N-FET	900V	6A	125W	2.8E
2SK1101	N-FET	450V	10A	50W	E65 1
2SK1102	N-FET	500V	10A	50W	240ns
2SK1113	N-FET	120V	3A	20W	
2SK1117	N-FET	600V	6A	100W	1.25R

2SK1118	N-FET	600V	6A	45W	1.25R
2SK1119	N-FET	100V	4A	100W	
2SK1120	N-FET	1000V	8A	150W	1,00E+08
2SK117	N-FET	50V	5mA		
2SK1170	N-FET	500V	20A	120W	<E27
2SK118	N-FET	50V	0.3mA	0.1W	
2SK1181	N-FET	500V	13A	85W	0.4E
2SK1190	N-FET	60V	22A	35W	0,00E+00
2SK1191	N-FET	60V	30A	40W	0.03E
2SK1198	N-FET	700V	2A	35W	3.2E
2SK1213	N-FET	600V	6A	125W	40/85ns
2SK1217	N-FET	900V	8A	100W	
2SK1221	N-FET	250V	10A	80W	0,00E+00
2SK125	N-FET	25V	0.1A	0.3W	
2SK1257	N-FET	60V	40A	45W	0.05E
2SK1271	N-FET	1400V	5A	240W	<4E
2SK1275	N-FET	900V	2A	30W	7E
2SK1296	N-FET	60V	30A	0.024E	
2SK1299	N-FET	100V	3A	20W	0,00E+00
2SK1317	N-FET	1500V	2.5A	100W	12E
2SK1338	N-FET	900V	2A	50W	7E
2SK1341	N-FET	900V	6A	100W	3E
2SK1342	N-FET	900V	8A	100W	1,00E+06
2SK1345	N-FET	60V	20A	40W	<E055
2SK1350	N-FET	200V	15A	45W	0,00E+00
2SK1351	N-FET	500V	5A	40W	<1E5
2SK1356	N-FET	900V	3A	40W	
2SK1357	N-FET	900V	5A	125W	
2SK1358	N-FET	900V	9A	150W	1.4E
2SK1363	N-FET	900V	8A	90W	1.4E
2SK1377	N-FET	500V	5.5A	40W	
2SK1378	N-FET	400V	10A	125W	0.55E
2SK1379	N-FET	60V	50A	150W	<E017
2SK1388	N-FET	30V	35A	60W	<E022
2SK1400	N-FET	300V	7A	50W	
2SK1404	N-FET	600V	5A	35W	1,00E+05
2SK1419	N-FET	60V	15A	25W	<E08
2SK1420	N-FET	60V	25A	30W	0.045E
2SK1444	N-FET	450V	3A	25W	2.6E
2SK1447	N-FET	450V	9A	40W	<E6
2SK1460	N-FET	900V	3.5A	40W	2,00E+08
2SK1461	N-FET	900V	5A	120W	
2SK1462	N-FET	900V	8A	150W	
2SK1502	N-FET	900V	7A	120W	2E
2SK1507	N-FET	600V	9A	50W	240ns
2SK152	N-FET	15V	9.5mA	Up<2V	
2SK1529	N-FET	180V	10A	120W	
2SK1530	N-FET	200V	12A	150W	
2SK1531	N-FET	500V	15A	150W	E45
2SK1537	N-FET	900V	5A	100W	290ns
2SK1544	N-FET	500V	25A	200W	0.2E
2SK161	N-FET	18V	0.01A	0.2W	
2SK1612	N-FET	900V	3A	50W	40/140ns
2SK163	N-FET	50V	0.03A	0.4W	
2SK1637	N-FET	600V	4A	35W	<2E4
2SK1643	N-FET	900V	5A	125W	2.8E
2SK1653	N-FET	60V	45A	45W	<E02
2SK168	N-FET	30V	20mA	0.2W	FM-V/
2SK170	N-FET	40V	20mA	0.4W	
2SK1723	N-FET	600V	12A	150W	<E65
2SK1833	N-FET	500V	2.5A	40W	<4E
2SK184	N-FET	50V	0.6mA	Up<1.5V	
2SK1917M	N-FET	250V	10A	50W	<E4
2SK192	N-FET	18V	Idss>3mA	Up<3V	
2SK1924	N-FET	600V	6A	1.75W	
2SK193	N-FET-DG	15V	VHF		
2SK1940	N-FET	600V	12A	125W	<E75
2SK1941	N-FET	600V	16A	100W	<E55
2SK1943	N-FET	900V	5A	80W	<2E8
2SK1953	N-FET	600V	2A	25W	5E
2SK2038	N-FET	800V	5A	125W	2,00E+02
2SK2039	N-FET	900V	5A	150W	<2E5

2SK2043	N-FET	600V	2A	2W	4,00E+03
2SK2056	N-FET	800V	4A	40W	2.4E
2SK2078	N-FET	800V	9A	150W	<1E2
2SK2083	N-FET	900V	5A	70W	3,00E+06
2SK212	N-FET	20V	0.6mA	0.2W	
2SK2134	N-FET	200V	13A	70W	<E4
2SK2136	N-FET	200V	20A	75W	<E18
2SK214	N-FET	160V	0.5A	30W	
2SK2141	N-FET	600V	6A	35W	1.1E
2SK216	N-FET	200V	0.5A	30W	
2SK2161	N-FET	200V	9A	25W	0.35E
2SK223	N-FET	80V	1.2mA	0.4W	
2SK2333	N-FET	700V	6A	50W	<2E
2SK2352	N-FET	600V	6A	45W	<1E25
2SK240	N-FET	40V	2.6mA	Up<1.5V	
2SK241	N-FET	20V	FM/VHF		
2SK246	N-FET	50V	1,2mA	Up<6V	
2SK2485	N-FET	900V	6A	100W	2.8E
2SK2545	N-FET	600V	6A	40W	1.25E
2SK2561	N-FET	600V	9A	80W	1.2E
2SK2605	N-FET	800V	5A	45W	2.2E
2SK2632LS	N-FET	800V	2.5A	30W	<4E8
2SK301	N-FET	55V	20mA	0.25W	
2SK303	N-FET	30V	0.6mA	Up<4V	
2SK304	N-FET	30V	0.6mA	Up<4V	
2SK30ATM	N-FET	50V	6.5mA		
2SK315	N-FET	20V	2.5mA	0.2W	
2SK320	N-FET	450V	5A	50W	<1E83
2SK33	N-FET	20V	20mA	0.15W	
2SK330	N-FET	50V	14MA	0.2W	320R
2SK332	N-FET	40V	12mA	Up=0.5V	
2SK357	N-FET	150V	5A	40W	<E9
2SK359	N-FET	20V	30mA	0.4W	
2SK363	N-FET	40V	5mA	Up<1.2V	
2SK364	N-FET	40V	2.6mA	Up<1.5V	
2SK367	N-FET	100V	0.6mA		
2SK369	N-FET	40V	5mA	Up<1.2V	
2SK373	N-FET	100V	0.6mA		
2SK374	N-FET	55V	1mA	Up<5V	
2SK381	N-FET	50V	0.3mA	0.3W	
2SK386	N-FET	450V	10A	120W	
2SK389	2xN-FET	50V			
2SK40	N-FET	50V	6.5mA		
2SK400	N-FET	200V	8A	100W	0,00E+00
2SK404	N-FET	20V	1.2mA	0.2W	
2SK415	N-FET	800V	3A	100W	<6E
2SK423	N-FET	100V	0.5A	0.9W	25ns
2SK427	N-FET	15V	2.5mA	Up<1.5V	
2SK430	N-FET	150V	3A	20W	0,00E+00
2SK439	N-FET	20V	30mA	0.3W	
2SK511	N-FET	250V	0.3A	8W	
2SK513	N-FET	800V	3A	60W	50/120ns
2SK526	N-FET	250V	10A	40W	0.6R
2SK537	N-FET	900V	1A	60W	
2SK538	N-FET	900V	3A	100W	4.5R
2SK544	N-FET	20V	30mA	0.3W	
2SK55	N-FET	18V	14mA	VHF	
2SK553	N-FET	500V	5A	50W	1,00E+05
2SK555	N-FET	500V	7A	60W	<E85
2SK557	N-FET	500V	12A	100W	0,00E+00
2SK559	N-FET	450V	15A	100W	0,00E+00
2SK583	N-FET	50V	0.2A	0.6W	20E
2SK606	N-FET	30V	20mA	Up<3V	
2SK611	N-FET	100V	1A	10W	6E
2SK612	N-FET	100V	2A	20W	
2SK68	N-FET	50V	0.5mA	Up<1.5V	
2SK685	N-FET	1000V	5A	100W	2E
2SK701	N-FET	60V	2A	15W	<E6
2SK703	N-FET	100V	5A	35W	0,00E+00
2SK719	N-FET	900V	5A	120W	
2SK725	N-FET	500V	15A	125W	0,00E+00
2SK727	N-FET	900V	5A	125W	2,00E+05

2SK73	N-FET	200V	0.1A	5W	
2SK735	N-FET	450V	10A	100W	<0E8
2SK754	N-FET	160V	10A	50W	0,00E+00
2SK758	N-FET	250V	5A	40W	OE7
2SK769	N-FET	500V	10A	100W	1E
2SK786	N-FET	20V	3A	50W	7,00E+05
2SK787	N-FET	900V	8A	120W	
2SK790	N-FET	500V	15A	150W	
2SK791	N-FET	850V	3A	100W	4.5R
2SK792	N-FET	900V	3A	100W	4.5R
2SK793	N-FET	850V	5A	150W	2.5R
2SK794	N-FET	900V	5A	150W	2.5R
2SK796	N-FET	800V	3A	90W	5E
2SK806	N-FET	600V	3A	50W	<2E7
2SK817	N-FET	60V	26A	35W	0.08E
2SK83	N-FET	25V	10MA	0.1W	Up<2.
2SK851	N-FET	200V	30A	150W	
2SK856	N-FET	60V	45A	125W	<E03
2SK872	N-FET	900V	6A	150W	2.5E
2SK875	N-FET	450V	12A	120W	0.6E
2SK890	N-FET	200V	10A	75W	<E4
2SK891	N-FET	100V	18A	125W	<E18
2SK899	N-FET	500V	18A	125W	<E33
2SK902	N-FET	250V	30A	150W	
2SK903	N-FET	800V	3A	40W	4E
2SK904	N-FET	800V	3A	80W	4E
2SK940	N-FET	60V	0.8A	0.9W	1.1E
2SK943	N-FET	60V	25A	40W	E046
2SK951	N-FET	800V	2.5A	40W	7E
2SK952	N-FET	800V	0.5mA		
2SK955	N-FET	800V	5A	125W	2E
2SK956	N-FET	800V	9A	150W	1,00E+05
2SK962	N-FET	900V	0.5mA	Up>2.5V	
3SK131	N-FET-DG	20V	25mA	0.2W	
3SK60	N-FET-DG	15V	33mA		
3SK73	N-FET-DG	20V	3mA		
3SK74	N-FET-DG	20V	25mA	0.2W	
AC121	GE-P	20V	0.3A	0.9W	
AC122	GE-P	30V	0.2A	0.225W	
AC125	GE-P	32V	0.2A		
AC126	GE-P	32V	0.2A	0.5W	
AC127	GE-N	32V	0.5A		
AC128	GE-P	32V	1A	1W	
AC128/176K	GE	N/P	PAIRED,		COOLED
AC128K	GE-P	32V	1A	1W	
AC131	GE-P	30V	1A	0.75W	
AC132	GE-P	32V	0.2A	0.5W	
AC138	GE-P	32V	1.2A	0.22W	1.5MHz
AC141K	GE-N	32V	1.2A	1W	
AC151	GE-P	32V	0.2A	0.9W	
AC153	GE-P	32V	2A	1W	
AC153K	GE-P	32V	2A	1W	
AC176K	GE-N	32V	1A	1W	
AC180	GE-P	32V	1.5A	0.3W	1MHz
AC187	GE-N	25V	1A	1W	
AC187/188K	GE	N/P	PAIRED,COOLED		
AC187K	GE-N	25V	1A	1W	COOLED
AC188	GE-P	25V	1A	1W	
AC188K	GE-P	25V	1A	1W	
AD133	GE-P	50V	15A	36W	
AD136	GE-P	40V	10A	11W	
AD139	GE-P	32V	3.5A	13W	
AD148	GE-P	32V	3.5A		13.5W
AD149	GE-P	50V	3.5A	27W	
AD161	GE-N	32V	1A	6W	
AD161/162	GE	N/P	32V	1A	6W PAIRED
AD162	GE-P	32V	1A	6W	
AD165	GE-N	25V	1A	6W	
AD166	GE-P	60V	5A	27.5W	
AF106	GE-P	25V	10mA	VHF	220MHz
AF109R	GE-P	20V	12mA	VHF	260MHz
AF118	GE-P	70V	30mA	375mW	125MHz

AF121	GE-P	25V	10mA		270MHz
AF125	GE-P	32V	10mA		75MHz
AF127	GE-P	32V	10mA		75MHz
AF139	GE-P	20V	10mA		550MHz
AF200	GE-P	25V	10mA	0.145W	
AF201	GE-P	25V	10mA	0.145W	
AF239S	GE-P	15V	10mA		700MHz
AF279	GE-P	15V	10mA	60mW	780MHz
AF279S	GE-P	20V	10mA	0.6W	
AF280	GE-P	UHF	MIXER		550MHz
AF306	GE-P	25V	15mA	60mW	500MHz
AF367	GE-P	153V	10mA	UHF	800MHz
AF379	GE-P	UHF	1250MHz		
AL102	GE-P	130V	6A	30W	
AL112	GE-P	130V	6A	10W	
ASY27	GE-P	25V	0.2A	0.15W	
ASY77	GE-P	60V	1A	0.26W	500KHz
ASZ15	GE-P	100V	8A	30W	
ASZ18	GE-P	100V	8A	30W	
BC107B	SI-N	50V	0.2A	0.3W	250MHz
BC107C	SI-N	50V	0.2A	0.3W	250MHz
BC109B	SI-N	30V	0.2A	0.3W	300MHz
BC109C	SI-N	30V	0.2A	0.3W	150MHz
BC117	SI-N	120V	50mA	0.3W	>60MHz
BC119	SI-N	60V	1A	0.8W	10MHz
BC135	SI-N	45V	0.2W		>200MHz
BC136	SI-N	60V	0.5A	0.3W	>60MHz
BC139	SI-P	40V	0.5A	0.7W	
BC141-10	SI-N	100V	1A	0.75W	50MHz
BC141-16	SI-N	100V	1A	0.75W	50MHz
BC142	SI-N	80V	1A	0.8W	
BC143	SI-P	60V	1A	0.7W	AF/DRIVE
BC146	SI-N	20V	50mA	50mW	150MHz
BC161-16	SI-P	60V	1A	0.75W	50MHz
BC177A	SI-P	50V	0.1A	0.3W	130MHz
BC177B	SI-P	50V	0.1A	0.3W	130MHz
BC177C	SI-P	50V	0.1A	0.3W	130MHz
BC190	SI-N	70V	0.1A	0.3W	250MHz
BC285	SI-N	120V	0.1A	0.36W	80MHz
BC300	SI-N	120V	0.5A	6W	120MHz
BC303	SI-P	85V	1A	6W	75MHz
BC313	SI-P	60V	1A	4W	50MHz
BC323	SI-N	100V	5A	0.8W	100MHz
BC327-16	SI-P	50V	0.8A	625mW	100MHz
BC327-25	SI-P	50V	0.8A	625mW	100MHz
BC327-40	SI-P	50V	0.8A	625mW	100MHz
BC336	SI-P	25V	50mA	0.31W	50MHz
BC337-16	SI-N	50V	0.8A	625mW	150MHz
BC337-25	SI-N	50V	0.8A	625mW	150MHz
BC337-40	SI-N	50V	0.8A	0.625W	150MHz
BC368	SI-N	20V	1A	0.8W	100MHz
BC369	SI-P	20V	1A	0.8W	
BC376	SI-P	25V	1A	0.625W	150MHz
BC393	SI-P	180V	10mA	40mW	
BC441	SI-N	75V	2A	1W	
BC448	SI-P	80V	0.3A	0.625W	>100
BC449	SI-N	100V	0.3A	0.625W	
BC450	SI-P	100V	0.3A	0.625W	
BC451	SI-N	50V	0.1A	0.3W	>150MHz
BC461	SI-P	75V	2A	1W	
BC485	SI-N	45V	1A	0.625W	200MHz
BC487B	SI-N	60V	1A	0.625W	200MHz
BC488	SI-P	60V	0.1A	625mW	>135MHz
BC489	SI-N	80V	1A	0.625W	200MHz
BC490	SI-P	80V	1A	0.625W	200MHz
BC516	P-DARL	40V	0.4A	0.625W	
BC517	N-DARL	40V	0.4A	0.625W	
BC538	SI-N	80V	1A	0.625W	100MHz
BC546A	SI-N	80V	0.2A	0.5W	
BC546B	SI-N	80V	0.2A	0.5W	
BC546C	SI-N	80V	0.1A	0.5W	
BC547A	SI-N	50V	0.2A	0.5W	

BC547B	SI-N	50V	0.2A	0.5W	300MHz
BC547C	SI-N	50V	0.2A	0.5W	300MHz
BC550B	SI-N	50V	0.2A	0.5W	
BC550C	SI-N	50V	0.2A	0.5W	
BC556A	SI-P	60V	0.2A	0.5W	
BC556B	SI-P	80V	0.2A	0.5W	
BC557A	SI-P	50V	0.2A	0.5W	
BC557B	SI-P	50V	0.2A	0.5W	
BC557C	SI-P	50V	0.2A	0.5W	
BC560B	SI-P	50V	0.2A	0.5W	
BC560C	SI-P	50V	0.2A	0.5W	
BC618	N-DARL	80V	1A	0.625W	B>10
BC639	SI-N	80V	1A	0.8W	100MHz
BC640	SI-P	80V	1A	0.8W	130MHz
BC807-25	SI-P	50V	0.5A	0.25W	5B
BC807-40	SI-P	45V	0.5A	0.3W	100MHz
BC817-16	SI-N	50V	0.5A	0.25W	6A
BC817-25	SI-N	50V	0.5A	0.25W	6B
BC817-40	SI-N	50V	0.5A	0.25W	6C
BC828	SI-P	50V	0.8A	0.8W	100MHz
BC846B	SI-N	80V	0.1A	0.25W	1B
BC847A	SI-N	50V	0.1A	0.2W	
BC847B	SI-N	50V	0.1A	0.25W	1F
BC847BR	SI-N	50V	0.1A	0.25W	SMD
BC847C	SI-N	50V	0.1A	0.25W	1G
BC849C	SI-N	30V	0.1A	0.25W	2C
BC850C	SI-N	45V	0.1A	0.25W	2G
BC856A	SI-P	65V	0.1A	3A	150MHz
BC856B	SI-P	65V	0.1A	3B	150MHz
BC857A	SI-P	50V	0.1A		150MHz
BC857B	SI-P	45V	0.1A	0.2W	3F
BC857BR	SI-P	45V	0.1A	0.2W	
BC857C	SI-P	45V	0.1A	0.25W	3G
BC859B	SI-P	30V	0.1A	0.25W	4B
BC860B	SI-P	50V	0.1A		4F
BC860C	SI-P	50V	0.1A		4G
BC868	SI-N	25V	1A		60MHz
BC869	SI-P	25V	1A	1W	60MHz
BC879	N-DARL	100V	1A	0.8W	
BC880	P-DARL	100V	1A	0.8W	
BCP68	SI-N	20V	1A	1.5W	60MHz
BCV27	N-DARL	40V	0.5A	0.25W	B>1
BCX17	SI-P	50V	0.5A	T1	100MHz
BCX17R	SI-P	50V	0.5A	T4	100MHz
BCX19	SI-N	50V	0.5A	300mW	200MHz
BCX38B	N-DARL	80V	0.8A	1W	B>4000
BCX53	SI-P	100V	1A		50MHz
BCX56	SI-N	100V	1A		130MHz
BCY59	SI-N	45V	0.2A	1W	250MHz
BCY71	SI-P	45V	0.2A	0.35W	
BCY72	SI-P	30V	0.2A	0.35W	
BCY79	SI-P	45V	0.2A	1W	180MHz
BCY85	SI-N	100V	0.2A	0.3W	
BD109	SI-N	60V	3A	15W	
BD115	SI-N	245V	0.15A	0.8W	
BD129	SI-N	400V	0.5A	17.5W	
BD131	SI-N	70V	3A	15W	>60MHz
BD132	SI-P	45V	3A	15W	>60MHz
BD139	SI-N	80V	1.5A	12.5W	50MHz
BD139-16	SI-N	80V	1.5A	12.5W	50MHz
BD140	SI-P	80V	1.5A	12.5W	50MHz
BD140-16	SI-P	80V	1.5A	12.5W	50MHz
BD141	SI-N	140V	8A	117W	
BD142	SI-N	50V	15A	117W	
BD159	SI-N	375V	0.5A	20W	
BD160	SI-N	250V	5A	25W	
BD179	SI-N	80V	3A	30W	
BD180	SI-P	80V	3A	30W	>2MHz
BD183	SI-N	85V	15A	117W	
BD201	SI-N	60V	8A	55W	
BD201F	SI-N	60V	8A	32W	
BD204F	SI-P	60/60V	8A	60W	>7MHz

BD230	SI-N	100V	1.5A	12.5W	
BD231	SI-P	100V	1.5A	12.5W	
BD232	SI-N	300V	0.25A	7W	
BD237	SI-N	100V	2A	25W	3MHz
BD238	SI-P	100V	2A	25W	3MHz
BD239C	SI-N	100V	2A	30W	3MHz
BD240	SI-P	45V	2A	30W	
BD240C	SI-P	100V	2A	30W	3MHz
BD241C	SI-N	100V	3A	40W	3MHz
BD241D	SI-N	120V	3A	40W	3MHz
BD242C	SI-P	100V	3A	40W	3MHz
BD243C	SI-N	100V	6A	65W	3MHz
BD243F	SI-N	200V	6A	65W	3MHz
BD244C	SI-P	100V	6A	65W	3MHz
BD244F	SI-P	200V	6A	65W	3MHz
BD250C	SI-P	100V	25A	125W	3MHz
BD277	SI-P	45V	7A	70W	>10MHz
BD302	SI-P	60V	8A	55W	>3MHz
BD303	SI-N	60V	8A	55W	>3MHz
BD314	SI-P	80V	10A	150W	
BD317	SI-N	100V	16A	200W	1MHz
BD318	SI-P	100V	16A	200W	
BD329	SI-N	32V	3A	15W	130MHz
BD330	SI-P	32V	3A	15W	
BD335	N-DARL	100V	6A	60W	
BD336	P-DARL	100V	6A	60W	
BD337	N-DARL+D	120V	6A	60W	>10MHz
BD362	SI-P	32V	3A	15W	
BD371B	SI-N	60V	1,5A	2,5W	
BD385	SI-N	60V	1A	10W	>250MHz
BD387	SI-N	80V	1A	10W	>250MHz
BD410	SI-N	500V	1A	20W	
BD411	N-DARL	50V	2A	10W	B>25K
BD441	SI-N	80V	4A	36W	3MHz
BD442	SI-P	80V	4A	36W	3MHz
BD515	SI-N	45V	2A	10W	160MHz
BD537	SI-N	80V	8A	50W	
BD538	SI-P	80V	4A	50W	>3MHz
BD539	SI-N	40V	5A	45W	
BD543C	SI-N	100V	8A	70W	3MHz
BD545	SI-N	40V	15A	85W	3MHz
BD637	SI-N	100V	2A	30W	>3MHz
BD638	SI-P	100V	2A	30W	>3MHz
BD648	P-DARL	80V	8A	62,5W	
BD651	N-DARL	120V	8A	62,5W	
BD652	P-DARL	120V	8A	62,5W	
BD679A	N-DARL+D	80V	4A	40W	
BD680A	P-DARL+D	80V	4A	40W	
BD681	N-DARL+D	100V	4A	40W	B>75
BD682	P-DARL+D	100V	4A	40W	
BD683	N-DARL	120V	4A	40W	
BD684	P-DARL	120V	4A	40W	
BD711	SI-N	100V	12A	75W	
BD712	SI-P	100V	12A	75W	POWER
BD722	SI-P	80V	4A	36W	>3MHz
BD743C	SI-N	110V	15A	90W	>5MHz
BD744C	SI-P	110V	15A	90W	5MHz
BD750	SI-P	100V	20A	200W	
BD751	SI-N	100V	20A	200W	
BD791	SI-N	100V	4A	15W	
BD792	SI-P	100V	4A	15W	
BD801	SI-N	100V	8A	65W	>3MHz
BD829	SI-N	100V	1A	8W	
BD830	SI-P	100V	1A	8W	75MHz
BD839	SI-N	45V	1.5A	10W	125MHz
BD843	SI-N	100V	1.5A	10W	>150MHz
BD877	N-DARL	80V	1A	9W	200MHz
BD879	N-DARL	100V	1A	9W	200MHz
BD880	P-DARL	100V	1A		200MHz
BD901	N-DARL+D	100V	8A	70W	
BD902	P-DARL	100V	8A	70W	
BD911	SI-N	100V	15A	90W	

BD912	SI-P	100V	15A	90W	
BD939F	SI-N	120V	3A	19W	3MHz
BD941	SI-N	140V	3A	30W	3MHz
BD942	SI-P	140V	3A	30W	3MHz
BD943	SI-N	22V	5A	40W	3MHz
BD948	SI-P	45V	5A	40W	3MHz
BD951	SI-N	80V	5A	40W	>3MHz
BD956	SI-P	120V	5A	40W	3MHz
BDT61	N-DARL+D	60V	4A	50W	>10MHz
BDT61C	N-DARL+D	120V	4A	50W	>10MHz
BDT61F	N-DARL+D	60V	4A		
BDT62C	P-DARL	120V	10A	90W	B>1K
BDT63C	N-DARL	120V	10A	90W	B>1K
BDT64C	P-DARL	120V	12A	125W	B>1K
BDT65C	N-DARL	120V	12A	125W	B>1K
BDT85A	SI-N	100V	15A	125W	20MHz
BDT86A	SI-P	100V	15A	125W	20MHz
BDT87	SI-N	120V	15A	125W	10MHz
BDT88	SI-P	120V	12A	117W	
BDT95A	SI-N	100V	10A	90W	4MHz
BDT96A	SI-P	100V	10A	90W	4MHz
BDV64C	P-DARL+D	120V	20A	125W	B>
BDV65B	N-DARL+D	100V	20A	125W	B>
BDV65C	N-DARL+D	120V	20A	125W	B>
BDV66C	P-DARL+D	120V	16A	200W	7MHz
BDV66D	P-DARL+D	160V	16A	200W	
BDW22C	SI-P	100V	10A	90W	>3MHz
BDW23C	N-DARL+D	100V	6A	50W	
BDW42	N-DARL	100V	15A	85W	B>1K
BDW46	P-DARL	80V	15A	85W	B>1K
BDW47	P-DARL	100V	15A	85W	B>1K
BDW51C	SI-N	100V	15A	125W	>3MHz
BDW83C	N-DARL	100V	15A	150W	
BDW83D	N-DARL+D	120V	15A	150W	
BDW84C	P-DARL	100V	15A	150W	
BDW84D	P-DARL+D	120V	15A	150W	>1
BDW93CF	N-DARL	100V	12A	40W	ISOLA
BDW94C	P-DARL	100V	12A	80W	
BDX11	SI-N	160V	10A	117W	>0.8MHz
BDX16A	SI-P	140V	3A	25W	800KHz
BDX20	SI-P	160V	10A	117W	>4MHz
BDX32	SI-N	1700V	4A	40W	
BDX33C	N-DARL	100V	10A	70W	
BDX34C	P-DARL	100V	10A	70W	
BDX37	SI-N	80V	5A	15W	350ns
BDX44	N-DARL+D	90V	1A	5W	1.5us
BDX47	P-DARL	90V	1A	5W	
BDX50	SI-N	160V	16A	150W	>800KH
BDX53C	N-DARL	100V	6A	60W	B=500
BDX53F	N-DARL	160V	6A	60W	B=500
BDX54C	P-DARL	100V	6A	60W	B=500
BDX54F	P-DARL	160V	6A	60W	B=500
BDX62C	P-DARL	120V	8A	90W	
BDX63C	N-DARL	140V	8A	90W	
BDX64C	P-DARL	120V	12A	117W	B>1K
BDX65C	N-DARL	120V	12A	117W	
BDX66C	P-DARL	120V	16A	150W	
BDX66C	P-DARL	120V	16A	150W	
BDX67C	N-DARL	120V	16A	150W	
BDX71	SI-N	70V	10A	75W	>0.8MHz
BDX75	SI-N	45V	16A	75W	>0.8MHz
BDX77	SI-N	100V	8A	60W	>7MHz
BDX87C	N-DARL	100V	12A	120W	
BDX88C	P-DARL	100V	12A	120W	
BDX94	SI-P	80V	8A	90W	>4MHz
BDX95	SI-N	100V	8A	90W	>4MHz
BDX96	SI-P	100V	8A	90W	>4MHz
BDY20	SI-N	100V	15A	117W	1MHz
BDY29	SI-N	100V	30A	220W	POWER
BDY56	SI-N	180V	15A	115W	>10MHz
BDY58	SI-N	160V	25A	175W	
BDY73	SI-N	100V	15A	115W	>8KHz

BDY83B	SI-P	50V	4A	36W	3MHz
BDY90	SI-N	120V	10A	60W	0.35us
BF115	SI-N	50V	30mA	0.15W	
BF120	SI-N	220V	50mA	0.3W	
BF125	SI-N	AM/FM	V/M/O/ZF		450MHz
BF152	SI-N	30V	0.2W	VHF-	800MHz
BF155	SI-N	40V	20mA		600MHz
BF161	SI-N	50V	20mA		550MHz
BF163	SI-N	40V	20mW		600MHz
BF164	SI-N	40V	0.2W		600MHz
BF166	SI-N	40V	20MA	0.175W	500MHz
BF173	SI-N	40V	25mA	0.23W	600MHz
BF180	SI-N	30V	20mA	.15W	675MHz
BF182	SI-N	25V	20mA		650MHz
BF184	SI-N	20V	30mA		260MHz
BF186	SI-N	190V	0.06A	0.8W	120MHz
BF189	SI-N	30V	25mA		270MHz
BF195	SI-N	30V	30mA	.22W	200MHz
BF199	SI-N	40V	25mA	0.3W	550MHz
BF200	SI-N	30V	20mA	0.15W	500MHz
BF224	SI-N	45V	50mA	0.25W	450MHz
BF240	SI-N	40V	25mA	0.25W	400MHz
BF244A	N-FET	30V	25mA	0.3W	
BF244C	N-FET	30V	25mA	0.3W	
BF245A	N-FET	30V	25mA	0.3W	
BF245B	N-FET	30V	25mA	0.3W	
BF245C	N-FET	30V	0.1A	0.3W	170MC
BF246C	N-FET	25V	25mA	0.25W	
BF247B	N-FET	25V	25mA	0.25W	
BF247C	N-FET	25V	25mA	0.25W	
BF253	SI-N	30V	30mA		150MHz
BF254	SI-N	30V	30mA	.22W	260MHz
BF255	SI-N	20V	30mA	.22W	200MHz
BF256A	N-FET	30V	7mA	Vgs<7.5	
BF256B	N-FET	30V	13mA		
BF256C	N-FET	30V	10mA	0.25W	
BF259	SI-N	300V	0.1A	0.8W	90MHz
BF259S	SI-N	300V	0.1A	0.8W	90MHz
BF271	SI-N	40V	30mA	240mW	1GHz
BF299	SI-N	300V	0.1A	0.625W	
BF316	SI-P	UHF-M/O	550..660MHz		
BF324	SI-P	30V	25mA	.25W	450MHz
BF339	SI-P	VHF-V/M/O	500MHz		
BF343	SI-P	35V	35mA	.25W	>80MHz
BF357	SI-N	30V	0.05A		1.6GHz
BF362	SI-N	UHF-V	800MHz		
BF370	SI-N	40V	0.1A	0.5W	>500MHz
BF377	SI-N	15V	25mA		1.3GHz
BF393	SI-N	300V	0.5A	0.65W	
BF410B	N-FET	20V	0.7mA		
BF410C	N-FET	20V	12mA		AMPLIF
BF411	SI-N	110V	0.05A	0.3W	
BF417	SI-N	300V	0.2A	6W	50MHz
BF418	SI-P	300V	0.2A	6W	50MHz
BF419	SI-N	300V	0.1A	6W	
BF420	SI-N	300V	0.1A	0.83W	
BF421	SI-P	300V	0.1A	0.83W	
BF424	SI-P	30V	25mA		300MHz
BF435	SI-P	160V	0.2A	0.625W	80MHz
BF440	SI-P	40V	25mA		250MHz
BF441B	SI-P	40V	25mA		250MHz
BF450	SI-P	40V	25mA	.25W	375MHz
BF455	AM/FM-V/M/O	400MHz			
BF459	SI-N	300V	0.1A	10W	90MHz
BF462	SI-N	350V	0.5A	10W	45MHz
BF471	SI-N	300V	0.1A	2W	60MHz
BF472	SI-P	300V	30mA	2W	60MHz
BF479	SI-P	30V	50mA	.16W	1.4GHz
BF487	SI-N	400V	0.05A	0.83W	
BF493	SI-P	300V	0.5A	0.625W	
BF494	SI-N	20V	30mA		260MHz
BF495C	SI-N	30V	30mA	0.3W	200MHz

BF496	SI-N	30V	20mA	0.3W	550MHz
BF506	SI-P	40V	30mA	0.3W	550MHz
BF507	SI-N	30V	20mA	0.5W	>750MHz
BF509	SI-P	40V	30mA	0.3W	750MHz
BF516	SI-P	35V	20mA		850MHz
BF569	SI-P	40V	30mA	280mW	850MHz
BF585	SI-N	350V	0.05A	5W	70MHz
BF587	SI-N	400V	0.05A	5W	>70MHz
BF622	SI-N	250V	0.1A	2W	
BF679	SI-P	40V	30mA	.16W	880MHz
BF680	SI-P	40V	30mA	.16W	750MHz
BF689	SI-N	15V	25mA	0.2W	1GHz
BF689K	SI-N	25V	25mA	0.36W	0.2GHz
BF758	SI-N	300V	0.5A	2W	
BF759	SI-N	350V	0.5A	10W	VID-PO
BF763	SI-N	15V	25mA	0.36W	1.8GHz
BF770A	SI-N	15V	0.05A	3,67E+04	GHZ
BF791	SI-P	300V	0.1A	5W	
BF799	SI-N	30V	35mA	280mW	800MHz
BF819	SI-N	250V	0.1A	1.2W	
BF820	SI-N	300V	25mA		>60MHz
BF821	SI-P	300V	25mA	0.31W	
BF840	SI-N	40V	25mA	0.28W	380MHz
BF844	SI-N	450V	0.3A	625mW	>50MHz
BF859	SI-N	300V	0.1A	2.5W	
BF871	SI-N	300V	0.1A	1.8W	
BF872	SI-P	300V	0.1A	1.6W	60MHz
BF881	SI-N	400V	0.03A		>60MHz
BF883S	SI-N	275V	0.05A	7W	>60MHz
BF891	SI-P	400V	30mA		<60MHz
BF910	N-FET-DG	20V	50mA	0.33W	
BF926	SI-P	20V	25mA	17dB	350MHz
BF939	SI-P	30V	220mA	.25	750MHz
BF959	SI-N	20V	0.1A		1.1GHz
BF960	N-FET-DG	20V	25mA	1	.8GHz
BF961	N-FET-DG	20V	30mA	2	.2GHz
BF964	N-FET-DG	20V	30mA	2	.2GHz
BF966	N-FET-DG	20V	30mA	1	.8GHz
BF966S	N-FET-DG	20V	30mA	.2W	.8GHz
BF967	SI-P	30V	20mA	.16W	900MHz
BF968	SI-P	UHF	TRANS.		1100MHz
BF970	SI-P	35V	30mA	0.3W	1GHz
BF979	SI-P	20V	50mA	0.3W	1.75GHz
BF980A	N-FET-DG	18V	30mA	UHF	
BF981	N-FET-DG	20V	20mA	VHF	
BF982	N-FET-DG	20V	40mA		200MHz
BF989	N-FET	20V	30mA	0.2W	
BF990A	N-FET-DG	18V	30mA	0.2W	
BF991	N-FET-DG	20V	20mA	UHF	
BF992	N-FET	20V	40mA	0.2W	
BF994S	N-FET-DG	20V	30mA		200MHz
BF996S	N-FET-DG	20V	30mA		800MHz
BF998	N-FET-DG	12V	30mA		800MHz
BF999	N-FET	20V	30MA	0.2W	300MHz
BFG135	SI-N	25V	0.15A	1W	BIPOLAR
BFG198	SI-N	20V	0.1A	1W	8GHZ
BFG65	SI-N	10V	50mA	0.3W	8GHZ
BFG94	SI-N	15V	60mA	0.7W	BIPOLA
BFG96	SI-N	20V	75mA	0.7W	800MHz
BFG97	SI-N	20V	0.1A	0.5W	BIPOLA
BFQ10	N-FET	30V	30mA	250mW	
BFQ162	SI-N	20V	0.5A	3W	1GHz
BFQ232	SI-N	100V	0.3A		1GHz
BFQ232A	SI-N	115V	0.3A		800MHz
BFQ235A	SI-N	115V	0.3A	3W	800MHz
BFQ252	SI-P	100V	0.3A	3W	
BFQ252A	SI-P	115V	0.3A		800MHz
BFQ255	SI-P	100V	0.3A	3W	1GHz
BFQ255A	SI-P	115V	0.3A	3W	800MHz
BFQ262	SI-P	100V	0.4A	5W	1GHz
BFQ262A	SI-P	115V	0.4A	5W	800MHz
BFQ33C	SI-N	7V	20mA	0.14W	12.5GHz

BFQ34	SI-N	18V	0.15A	2.7W	4GHz
BFQ43	SI-N	18V	1.2A	4W	175MHz 1
BFQ65	SI-N	10V	50mA	0.3W	8GHz 8
BFQ68	SI-N	18V	0.3A	4.5W	4GHz
BFR29	N-FET	30V	10mA	Up<4V	
BFR35AP	SI-N	12V	30mA	14dB	4.9GHz
BFR36	SI-N	40V	200mA	0.8W	1.3GHz
BFR37	SI-N	30V	50mA	0.25W	1.4GHz
BFR38	SI-P	40V	20mA	0.2W	1GHz
BFR39	SI-N	90V	1A	0.8W	>100MHz
BFR40	SI-N	70V	1A	0.8W	>100MHz
BFR79	SI-P	90V	1A	0.8W	>100MHz
BFR84	N-FET-DG	20V	50mA	0.3W	
BFR90	SI-N	15V	30mA	19.5dB	5GHz
BFR90A	SI-N	15V	30mA	16dB	5.5GHz
BFR91	SI-N	12V	50mA	18dB	5GHz
BFR91A	SI-N	12V	50mA	14dB	6GHz
BFR92	SI-N	15V	30mA	19.5dB	5GHz
BFR92A	SI-N	15V	30mA	16dB	5.5GHz
BFR92R	SI-N	15V	30mA	REVERS	5GHz
BFR93A	SI-N	15V	50mA	14dB	6GHz
BFR95	SI-N	25V	0.15A	1.5W	3.5GHz
BFR96	SI-N	15V	75mA	16dB	5GHz
BFR96S	SI-N	15V	0.1A	11dB	5.5GHz
BFS17	SI-N	15V	25mA	E1	1GHz
BFS19	SI-N	30V	30mA		260MHz
BFS20	SI-N	30V	25mA	G1	450MHz
BFS22A	SI-N	3V	0.75A	4W	175MHz
BFS23A	SI-N	36V	0.5A	4.5W	500MHz
BFT25	SI-N	8V	6.5mA	50mW	500NHZ
BFT43	SI-N	125/100V	1A	0.8W	
BFT45	SI-P	250V	0.5A	0.75W	70MHz
BFT66	SI-N	15V	30mA	12dB	4.5GHz
BFT79	SI-P	90V	1A	0.8W	>100MHz
BFT95	SI-P	UHF	15V	25mA	3.6-5GHz
BFW10	N-FET	30V	20mA		AMPL.
BFW11	N-FET	30V	10mA		AMPL.
BFW12	N-FET	30V	5mA		AMPL.
BFW16A	SI-N	25V	0.3A	1.5W	1.2GHz
BFW17A	SI-N	25V	0.3A	1.5W	1.1GHz
BFW30	SI-N	10V	0.1A	0.25W	1.6GHz
BFW43	SI-P	150V	0.1A	0.4W	150MHz
BFW44	SI-P	150V	0.1A	0.7W	50MHz
BFW92	SI-N	15V	50mA	0.3W	1.6GHz
BFW92A	SI-N	15V	25mA	13dB	3.2GHz
BFX34	SI-N	60V	5A	0.87W	
BFX37	SI-P	90V	0.1A	0.36W	70MHz
BFX38	SI-P	55V	1A	0.8W	B>85
BFX40	SI-P	75V	1A	0.8W	B>85
BFX48	SI-P	30V	0.1A	0.36W	
BFX55	SI-N	60V	0.4A	2.2W	700MHz
BFX85	SI-N	100V	1A	0.8W	
BFX89	SI-N	15V	50mA	0.2W	1.3GHz
BFY39	SI-N	45V	0.1A	0.3W	150MHz
BFY50	SI-N	80V	1A	0.7W	55/175ns
BFY51	SI-N	60V	1A	0.7W	
BFY52	SI-N	40V	1A	0.8W	100MHz
BFY56	SI-N	60V	1A	0.8W	
BFY64	SI-P	40V	0.6A	0.7W	
BFY88	SI-N	25V	25mA		850MHz
BFY90	SI-N	15V	25mA	8dB	2GHz
BGX885N	CATV	AMPL.		17dB	860MHz
BGY88	CATV	AMP.		35dB	450MHz
BGY89	CATV	AMP.		38dB	450MHz
BLW32	SI-N	50V	0.65A	10W	3.5GHz
BLW60C	SI-N	18V	9A	100W	650MHz
BLX15	SI-N	110V	6.5A	195W	275MHz
BLY87C	SI-N	36V	1.53A	20W	175MHz
BLY88C	SI-N	18V	3A	36W	850MHz
BLY89C	SI-N	18V	6A	73W	800MHz
BLY93C	SI-N	65V	2A	25W	175MHz
BLY94	SI-N	65V	6A	50W	175MHz

BS107	N-FET	200V	0.13A	0.8W	26R
BS108	N-FET	200V	0.23A	0.8W	8E
BS170	N-FET	60V	0.3A	0.8W	5R
BS208	P-FET	200V	0.2A	0.8W	
BS250	P-FET	45V	0.18A	0.83W	
BSN254A	N-FET	250V	0.3A	1W	<7E
BSN274	N-FET	270V	0.25A	1W	<8E
BSN304	N-FET	300V	0.25A	1W	<8E
BSR14	SI-N	75V	0.8A		<35/285ns
BSR31	SI-P	70V	1A		B>100
BSR50	N-DARL	60V	2A	0.8W	350MHz
BSR60	P-DARL	45V	1A	0.8W	
BSS123	N-FET	100V	0.17A		13/29ns
BSS38	SI-N	120V	0.1A	0.2W	
BSS44	SI-P	65V	5A	5W	
BSS52	N-DARL	100V	1A	0.8W	
BSS68	SI-P	60/40V	0.8A		<50/110ns
BSS89	N-FET	240V	0.3A	1W	6R
BSS91	N-FET	200V	0.35A	1.5W	<6E
BSS92	P-FET	200V	0.15A	1W	38/45
BSV52	SI-N	20V	0.1A	225mW	400MHz
BSV80	N-FET	40V	10mA	0.35W	
BSV81	N-FET	30V	50mA	0.2W	100E
BSW43	SI-N	60V	0.2A	0.3W	B>180
BSW68A	SI-N	150V	2A	5W	130MHz
BSW85	SI-N	75V	0.5A	0.5W	250MHz
BSX20	SI-N	40V	0.5A	.36W	7/18ns
BSX26	SI-N	40V	0.5A	0.36W	
BSX29	SI-P	12V	0.2A	0.36W	25/35
BSX32	SI-N	65V	1A	0.8W	35/40ns
BSX47	SI-N	120V	1A	5W	
BSX52	SI-N	25V	0.2A	0.3W	B>180
BSX59	SI-N	45V	1A	0.8W	
BSX88	SI-N	40V	0.5A	0.36W	
BSY56	SI-N	120V	0.5A	0.8W	100MHz
BTS121A	N-FET	100V	22A	95W	0.1E
BU106	SI-N	325V	10A	50W	
BU107	SI-N	300V	10A	50W	
BU109	SI-N	330V	10A	85W	
BU110	SI-N	150V	10A	30W	15MHz
BU124A	SI-N	400V	10A	50W	6MHz
BU125	SI-N	130/60V	5A	0.8W	100MHz
BU128	SI-N	300/200V	10A	62W	
BU133	SI-N	750/250V	3A	30W	TO3
BU1506DX	SI-N+D	1500V	5A	32W	0.5US
BU1508AX	SI-N	1500V	8A	35W	0.6US
BU1508DX	SI-N+D	1500V	8A	35W	0.6US
BU180A	SI-N+D	400V	10A		
BU180E	N-DARL	1500V	5A	12W	
BU189	N-DARL	330V	8A	60W	
BU208A	SI-N	1500V	8A	150W	THIN B
BU208B	SI-N	700V	5A	80W	7MHz
BU208D	SI-N+D	1500V	8A	150W	
BU209	SI-N	1700V	4A	12.5W	TO3
BU226	SI-N	2000V	1.5A	10W	TO3
BU2506DF	SI-N+D	1500V	5A	45W	0.4us
BU2506DX	SI-N+D	1500V	5A	45W	0.4US
BU2508A	SI-N	1500V	8A	125W	0.4us
BU2508AF	SI-N	1500V	8A	45W	0.4us
BU2508AX	SI-N	1500V	8A	45W	0.4US
BU2508D	SI-N+D	1500V	8A	125W	0.4us
BU2508DF	SI-N+D	1500V	8A	45W	0.4us
BU2508DX	SI-N+D	1500V	8A	45W	0.4us
BU2520AF	SI-N	1500V	10A	45W	0.2us
BU2520AX	SI-N	1500V	10A	45W	0.2us
BU2520DF	SI-N+D	1500V	10A	45W	0.35
BU2520DX	SI-N+D	1500V	10A	45W	0.35
BU2525A	SI-N	1500V	12A	0.2us	
BU2525AF	SI-N	1500V	12A	45W	0.2us
BU2525AX	SI-N	1500V	12A	45W	0.2US
BU2525D	SI-N+D	1500V	12A	0.2us	
BU2527AF	SI-N	1500V	12A	45W	0.2us

BU2527AX	SI-N	1500V	12A	45W	0.2US
BU2722AF	SI-N	1700V	10A	45W	
BU312	SI-N	280/150V	6A	25W	
BU325	SI-N	200/200V	3A	25W	
BU326A	SI-N	900V	6A	75W	
BU326S-RFT	SI-N	800/400V	6A	60W	TO3
BU406	SI-N	400V	7A	65W	0.75us
BU406D	SI-N+D	400V	7A	65W	0.75us
BU407	SI-N	330V	7A	65W	0.75us
BU407D	SI-N+D	330V	7A	65W	0.75us
BU409D	SI-N+D	250V	7A	60W	
BU412	SI-N+D	280V	8A		
BU413	SI-N	330V	10A	60W	TO3
BU414B	SI-N+D	900V	8A	60W	
BU415A	SI-N	800V	12A	120W	TO3
BU415B	SI-N+D	800V	12A	120W	
BU426A	SI-N	900V	6A	114W	
BU426E	SI-N	800V	6A	70W	TO220
BU426V	SI-N	800/375V	6A	70W	
BU433	SI-N	375V	6A	70W	
BU500	SI-N	1500V	6A	75W	
BU500D	SI-N+D	1500/700V	6A	75W	
BU505	SI-N	1500V	2.5A	75W	0.9us
BU505D	SI-N+D	1500V	2.5A	75W	
BU505DF	SI-N+D	1500V	2.5A	20W	
BU506	SI-N	700V	5A	100W	POWER
BU506D	SI-N+D	700V	5A	100W	POWER
BU506DF	SI-N+D	1500V	5A	20W	POWER
BU508A	SI-N	1500V	8A	125W	0.7us
BU508A	SI-N	1500V	8A	125W	0.7us
BU508A	SI-N	1500V	8A	125W	0.7us
BU508AF	SI-N	1500V	8A	34W	0.7us
BU508AF	SI-N	1500V	8A	34W	0.7us
BU508AF	SI-N	1500V	8A	34W	0.7us
BU508D	SI-N+D	1500V	8A	125W	0.7us
BU508D	SI-N+D	1500V	8A	125W	0.7us
BU508DF	SI-N+D	1500V	8A	34W	0.7us
BU508DF	SI-N+D	1500V	8A	34W	0.7us
BU508DR	SI-N+D	1500V	8A	125W	
BU522	N-DARL	400/375V	7A	75W	
BU526	SI-N	800V	8A	86W	
BU536	SI-N	1100V	8A	62W	
BU546	SI-N	1350V	6A	100W	TO3
BU603	SI-N	1350V	5A	100W	0.7us
BU606D	SI-N+D	400V	7A	90W	
BU608	SI-N	400V	6A	90W	TO3
BU608D	SI-N+D	400V	7A	90W	
BU626A	SI-N	1000V	10A	100W	
BU705	SI-N	1500V	2.5A	75W	0.7us
BU706DF	SI-N+D	1500V	5A	32W	0.7us
BU706F	SI-N	1500V	5A	32W	0.7us
BU801	SI-N+D	600V	3A	40W	
BU806	N-DARL+D	400V	8A	60W	0.35
BU806FI	SI-N+D	400V	8A		
BU808DF	N-DARL+D	1500/700V	5A	50W	
BU810	N-DARL+D	600V	7A	75W	
BU824	N-DARL+D	650V	0.5A		
BU826	N-DARL+D	800V	6A	125W	0.2
BU826A	N-DARL+D	900V	6A	125W	0.2
BU920P	N-DARL	350V	10A	120W	
BU921P	SI-N	400/450V	10A	120W	
BU931	SI-N	500V	15A	175W	
BU931T	SI-N	450V	10A	125W	
BU932	N-DARL	500V	15A	175W	
BU932P	N-DARL	500V	15A	125W	
BU941P	N-DARL	500V	15A	150W	
BU941ZP	N-DARL	350V	15A	150W	
BUF405A	SI-N	1000/450V	7.5A	80W	
BUF405AF	SI-N	1000V	7.5A		ISOLATED
BUF410	SI-N	850V	15A	125W	
BUH1015	SI-N	1500V	14A	160W	0.11us
BUH1015HI	SI-N	1500V	14A	70W	0.11us

BUH1215	SI-N	1500V	19A	200W	0.11us
BUH315	SI-N	1500V	5A	50W	
BUH315D	SI-N+D	1500/700V	5A	50W	
BUH515	SI-N	1500V	8A	60W	3.9us
BUH515D	SI-N+D	1500/700V	8A	60W	
BUH517	SI-N	1700V	8A	60W	3.9us
BUH517D	SI-N+D	1700/700V	8A	60W	
BUH715	SI-N	1500V	10A	60W	
BUK436/800EN-FET		800V	4A	125W	<4E
BUK437/400EN-FET		400V	14A	180W	
BUK437/600EN-FET		600V	9A	180W	<1E2
BUK438/800EN-FET		800V	7.6A	220W	2E
BUK443/60B N-FET		60V	13A	25W	<E1
BUK444/800EN-FET		800V	1.2A	30W	8E
BUK445/600EN-FET		600V	2.2A	30W	2R5
BUK446/800EN-FET		800V	2A	30W	
BUK454/800N-FET		800V	2A	75W	
BUK455/600EN-FET		600V	4A	100W	2R5
BUK456/200EN-FET		200V	19A	150W	<E2
BUK456/60A N-FET		60V	52A	150W	0.028E
BUK456/800N-FET		800V	4A	125W	3E
BUK555/60B N-FET		60V	35A	125W	0.055E
BUL310	SI-N	1000V	5A	75W	0.4us
BUL310PI	SI-N	1000V	5A	35W	0.4us
BUL45	SI-N	400V	5A	75W	12MHz
BUL54A	SI-N	1000V	4A	65W	20MHz
BUL810	SI-N	1000V	15A	125W	
BUR51	SI-N	300/200V	60A	350W	
BUR52	SI-N	350/250V	60A	350W	
BUS14A	SI-N	1000/450V	30A	250W	
BUS23	SI-N	300V	15A	175W	
BUS48A	SI-N	1000V	15A	175W	
BUS48AP	SI-N	1000V	15A	125W	
BUS98A	SI-N	450V	30A	250W	
BUT11A	SI-N	1000V	5A	100W	0.8us
BUT11A	SI-N	1000V	5A	100W	0.8us
BUT11AF	SI-N	1500V	5A	20W	0.8us
BUT12A	SI-N	1000V	8A	125W	0.8us
BUT12AF	SI-N	1000V	8A	23W	0.8us
BUT13	N-DARL+D	400V	28A	175W	
BUT18A	SI-N	1000/450V	6A	110W	0.
BUT18AF	SI-N	1000V	6A	33W	0.8us
BUT30V	SI-N	200/125V	100A	250W	
BUT34	N-DARL+D	850V	50A	250W	
BUT56A	SI-N	1000V	8A	100W	
BUT57	N-DARL+D	400V	15A	110W	B>
BUT70	SI-N	200V	40A	200W	
BUT72	SI-N	400V	40A	200W	
BUT76A	SI-N	1000V	10A	100W	0.8us
BUT90	SI-N	200V	50A	250W	
BUT92	SI-N	350/250V	50A	250W	
BUT93	SI-N	600V	4A	55W	9MHz
BUV18	SI-N	120V	47A	250W	1.5us
BUV20	SI-N	160V	50A	250W	1.5us
BUV21	SI-N	250/200V	40A	250W	
BUV23	SI-N	325V	40A	250W	
BUV24	SI-N	400V	30A	250W	
BUV25	SI-N	500V	20A	250W	
BUV26	SI-N	180V	14A	85W	1.8us
BUV26A	SI-N	200V	20A	85W	
BUV27	SI-N	240V	12A	65W	40ns
BUV28	SI-N	400V	10A	65W	40ns
BUV28A	SI-N	450V	10A	65W	40NS
BUV46A	SI-N	1000/450V	6A	85W	
BUV48A	SI-N	1000V	15A	150W	0.8us
BUV48AF	SI-N	1000V	15A	65W	
BUV48C	SI-N	1200/700V	15A	150W	
BUV48CF	SI-N	1200V	15A	65W	
BUV50	SI-N	250V	25A	150W	
BUV56A	SI-N	1000V	10A	70W	
BUV61	SI-N	300V	50A	250W	
BUV70	SI-N	1300/550V	10A	140W	

BUV90	N-DARL+D	650V	10A	125W	
BUV93	SI-N	600/350V	2A	15W	12MHz
BUV98A	SI-N	1000V	30A	150W	5MHz
BUW11A	SI-N	1000V	5A	100W	0.8us
BUW11AF	SI-N	1000V	5A	32W	0.8us
BUW12	SI-N	850V	8A	125W	0.8us
BUW12A	SI-N	1000V	8A	125W	0.8us
BUW12F	SI-N	850V	8A	34W	0.8us
BUW13	SI-N	850V	15A	175W	0.8us
BUW13A	SI-N	1000V	15A	175W	0.8us
BUW23	SI-P	450V	10A	125W	<300NS
BUW26	SI-N	800V	10A	125W	20MHz
BUW42	SI-P	400V	15A	150W	
BUW48	SI-N	120V	30A	150W	1.5us
BUW49	SI-N	160V	30A	150W	
BUW50	SI-N	250V	25A	150W	TO-218
BUW72	SI-N	450V	10A	100W	
BUW81A	N-DARL	800V	10A	80W	
BUW84	SI-N	800V	2A	50W	0.4us
BUW85	SI-N	1000V	2A	50W	0.4us
BUX10	SI-N	160V	25A	150W	1.5us
BUX12	SI-N	300V	20A	150W	
BUX13	SI-N	400V	15A	150W	>8MHz
BUX20	SI-N	160V	50A	350W	1.5us
BUX22	SI-N	300V	40A	250W	POWSWI
BUX23	SI-N	400/325V	30A	350W	
BUX24	SI-N	450/400V	20A	350W	>8
BUX32B	SI-N	1000V	8A	150W	
BUX37	N-DARL	400V	15A	35W	
BUX39	SI-N	120/90V	30A	120W	8MHz
BUX40	SI-N	160V	20A	120W	1.2us
BUX41	SI-N	250V	15A	120W	
BUX41N	SI-N	220/160V	18A	120W	
BUX42	SI-N	300V	12A	120W	
BUX48A	SI-N	1000V	15A	175W	0.8us
BUX51	SI-N	300/200V	3.5A	10W	>8
BUX54	SI-N	450V	2A	10W	>8MHz
BUX55	SI-N	450V	2A	10W	8MHz
BUX66	SI-P	200/150V	2A	35W	>20MHz
BUX77	SI-N	100V	5A	40W	>2.5MHz
BUX80	SI-N	800V	10A	100W	
BUX81	SI-N	1000V	10A	100W	
BUX82	SI-N	800V	6A	60W	
BUX84	SI-N	800V	2A	40W	0.4us
BUX85	SI-N	1000V	2A	40W	0.4us
BUX85F	SI-N	1000V	2A	18W	0.4us
BUX86P	SI-N	800V	0.5A	20W	0.4us
BUX87	SI-N	1000V	0.5A	20W	0.4us
BUX87P	SI-N	1000V	0.5A	20W	0.4us
BUX88	SI-N	1500V	12A	160W	7MHz
BUX98A	SI-N	450V	30A	250W	
BUX98C	SI-N	1200V	30A	250W	5MHz
BUY18S	SI-N	80/40V	10A	20W	
BUY47	SI-N	150/120V	7A	10W	90MHz
BUY49P	SI-N	250V	3A	10W	
BUY49S	SI-N	250V	3A	10W	50MHz
BUY69A	SI-N	1000V	10A	100W	1us
BUY70A	SI-N	1000/400V	10A	75W	
BUY71	SI-N	2200V	2A	40W	HORDEFL
BUY72	SI-N	280/200V	10A	60W	
BUY89	SI-N	1500V	6A	80W	
BUZ10	N-FET	50V	20A	80W	0.08R
BUZ100	N-FET	50V	60A	250W	0.18E
BUZ11	N-FET	50V	36A		
BUZ11A	N-FET	50V	27A	90W	0.055R
BUZ14	N-FET	50V	39A	125W	
BUZ15	N-FET	50V	45A	125W	
BUZ171	P-FET	50V	8A	40W	0.3R
BUZ21	N-FET	100V	21A		
BUZ215	N-FET	500V	5A	75W	<1E5
BUZ22	N-FET	100V	34A	125W	0.055
BUZ30A	N-FET	200V	7A	75W	

BUZ310	N-FET	1000V	2.5A	75W	<5E
BUZ325	N-FET	400V	12.5A	125W	<E3
BUZ326	N-FET	400V	10.5A	125W	
BUZ330	N-FET	500V	9.5A	125W	0,00E+00
BUZ332	N-FET	600V	8.5A	150W	0.8R
BUZ332A	N-FET	600V	8A	150W	0.9E
BUZ338	N-FET	500V	13.5A	180W	<E4
BUZ341	N-FET	200V	33A	170W	0.07E
BUZ345	N-FET	100V	41A	150W	<E045
BUZ349	N-FET	100V	32A	125W	
BUZ380	N-FET	1000V	5.5A	125W	140
BUZ384	N-FET	500V	10.5A	125W	
BUZ50A	N-FET	1000V	2.5A	75W	5E
BUZ71	N-FET	50V	18A	80W	0.1R
BUZ71AF	N-FET	50V	11A	35W	0.12R
BUZ72A	N-FET	100V	11A		
BUZ72AF	N-FET	100V	10A	40W	ISOLAT
BUZ73	N-FET	200V	7A	40W	0.4R
BUZ73A	N-FET	200V	5.8A	40W	0.6R
BUZ90	N-FET	600V	4.5A	70W	<1E6
BUZ900	N-FET	160V	8A	125W	
BUZ901	N-FET	200V	8A	125W	
BUZ905	P-FET	160V	8A	125W	
BUZ906	P-FET	200V	8A	125W	
BUZ90A	N-FET	600V	4A	75W	2R
BUZ90AF	N-FET	600V	4.3A	75W	
BUZ91A	N-FET	600V	8A	150W	0.9R
BUZ93	N-FET	600V	3.6A	80W	<2E5
CA3018	DARLINGTON	BJT	ARRAY		
D44H11	SI-N	80V	10A	50W	50MHz
D44H8	SI-N	60V	10A	50W	
D45H11	SI-N	80V	10A	50W	0.5us
DTA114EK	SI-P	50V	0.1A	0.2W	10K/10
DTA114ES	SI-P	50V	0.1A		10K/10KOHM
DTA114TL	SI-P	50V	0.1A		10KOHM
DTA114YL	SI-P	50V	0.1A		10K/47KOHM
DTA124ES	SI-P	50V	0.1A		22K/22KOHM
DTA124XS	SI-P	50V	0.1A		22K/47KOHM
DTA143EK	SI-P	50V	0.1A	0.2W	47/47K
DTA143ES	SI-P	50V	0.1A		4K7/4K7OHM
DTA144EK	SI-P	50V	0.1A	0.2W	47K/47
DTA144ES	SI-P	50V	0.1A		47K/47K
DTA144TS	SI-P	50V	0.1A	0.3W	Rb=47K
DTC114ES	SI-N	50V	0.1A		10K/10KOHM
DTC114TS	SI-N	50V	0.1A		10K
DTC114YS	SI-N	50V	0.1A		10K/47K
DTC124EK	SI-N	50V	0.1A	0.2W	22/22K
DTC124ES	SI-N	50V	0.1A		22K/22KOHM
DTC143EK	SI-N	50V	0.1A	0.2W	4K7/4K
DTC143ES	SI-N	50V	0.1A		4K7/4K7OHM
DTC143TS	SI-N	50V	0.1A		4K7OHM
DTC143XS	SI-N	50V	0.1A	0.3W	4.7K/1
DTC144EK	SI-N	50V	0.1A	0.2W	47/47K
DTC144ES	SI-N	50V	0.1A		47K/47KOHM
DTC144EU	SI-N	50V	0.1A	0.2W	47/47K
DTC144TS	SI-N	50V	0.1A	0.3W	47KOhm
DTC144WS	SI-N	50V	0.1A	0.2W	47/22K
ESM6045DV	N-DARL+D	450V	84A	250W	
FT5754M	DARLINGTON	ARRAY			
FT5764M	DARLINGTON	ARRAY			
GD243	GE-P	65V	3A	10W	
GT20D101	N-IGBT	250V	20A	180W	
GT20D201	P-IGBT	250V	20A	250W	
H6N80	N-FET	800V	4.2A	170W	1,00E+09
HPA100R	SI-N+D	1500V	10A	150W	0.2
HPA150R	SI-N+D	1500V	15A	180W	0.2
IR2403	DARL.ARRAY	7x45V	0.4A		
IR2422	7XDARLINGTON	TRAN.	ARRAY		
IRF120	N-FET	100V	9.2A	60W	<58/5
IRF140	N-FET	100V	28A	150W	0,00E+00
IRF230	N-FET	200V	9A	75W	<0E4
IRF240	N-FET	200V	18A	125W	

IRF250	N-FET	200V	30A	150W	
IRF330	N-FET	400V	5.5A	75W	<1E
IRF340	N-FET	400V	10A	125W	<62/1
IRF350	N-FET	400V	13A	150W	0.4E
IRF440	N-FET	500V	8A	125W	<0E85
IRF450	N-FET	500V	13A	150W	
IRF520	N-FET	100V	10A	70W	0.27R
IRF530	N-FET	100V	16A	90W	0.16R
IRF540	N-FET	100V	28A	150W	0.077
IRF630	N-FET	200V	9A	75W	0.4E
IRF640	N-FET	200V	18A	125W	0.18R
IRF644	N-FET	250V	14A	125W	<E28
IRF730	N-FET	400V	5.5A	100W	1.0R
IRF740	N-FET	400V	10A	125W	0.55R
IRF740F	N-FET	400V	5.5A	40W	<E55
IRF820	N-FET	500V	3A	75W	3.0R
IRF830	N-FET	500V	4.5A	100W	1.5R
IRF830F	N-FET	500V	3A	35W	1.5R
IRF840	N-FET	500V	4.5A	40W	0.85R
IRF840F	N-FET	500V	4.5A	40W	0.85R
IRF9140	P-FET	100V	19A	125W	
IRF9240	P-FET	200V	11A	125W	<E5
IRF9530	P-FET	100V	12A	88W	0.3R
IRF9540	P-FET	100V	19.0A	150W	0R2
IRF9610	P-FET	200V	1.75A	20W	3R0
IRF9620	P-FET	200V	3.5A	40W	1R5
IRF9630	P-FET	200V	6.5A	75W	0R8
IRF9640	P-FET	200V	11A	125W	0R5
IRFBC30	N-FET	600V	3.9A	100W	2R2
IRFBC40	N-FET	600V	6.2A	125W	1R2
IRFBE30	N-FET	800V	4.1A	125W	<3E
IRFD120	N-FET	100V	1.3A	1.3W	<E27
IRFD9120	P-FET	100V	1A	1.3W	<E6
IRFD9220	P-FET	200V	0.6A	1,00E+05	1W <9
IRFF120	N-FET	100V	6A	20W	0.3E
IRFP054	N-FET	60V	70A	230W	<0E014
IRFP064	N-FET	60V	70A	300W	<E009
IRFP140	N-FET	100V	31A	180W	0E77
IRFP150	N-FET	100V	40A	180W	0,00E+00
IRFP240	N-FET	200V	20A	150W	0,00E+00
IRFP250	N-FET	200V	33A	180W	
IRFP340	N-FET	400V	11A	150W	<E55
IRFP350	N-FET	400V	18A	250W	0,00E+00
IRFP360	N-FET	400V	28A	410W	0.2E
IRFP450	N-FET	500V	14A	180W	0,00E+00
IRFP460	N-FET	500V	25A	410W	0E27
IRFP9140	P-FET	100V	19A	150W	0E2
IRFP9240	P-FET	200V	12A	150W	
IRFPC40	N-FET	600V	6.8A	150W	1.2E
IRFPC50	N-FET	600V	13A	250W	0.60E
IRFPE40	N-FET	800V	5.4A	150W	<2E
IRFPE50	N-FET	900V	7.8A	190W	<1E2
IRFPF40	N-FET	900V	4.7A	150W	<2E5
IRFPF50	N-FET	900V	6.7A	190W	<1E6
IRFR9024	P-FET	60V	9.6A	50W	0.28W
IRFZ20	N-FET	50V	15A	40W	<120/70
IRFZ44	N-FET	60V	46A	250W	0,00E+00
IRFZ48	N-FET	60V	50A	250W	0.018E
ITT9013G	SI-N	30V	0.5A		100MHz
J111	N-FET	40V	50mA	0.4W	30E
J300	N-FET	25V	6mA	0.35W	
J309	N-FET	25V	30mA	Up<4V	VHF
J310	N-FET	25V	60mA	Up<6.5V	VH
KSA708	SI-N	80V	0.7A	0.8W	50MHz
KSA733	SI-P	60V	0.15A	0.25W	50MHz
KSC2316	SI-N	120V	0.8A	0.9W	120MHz
KSC2328A	SI-N	30V	2A	1W	120MHz
KSC2330	SI-N	300V	0.1A		50MHz
KSC2331	SI-N	80V	0.7A	1W	30MHz
KTA1273	SI-P	30V	2A	1W	120MHz
KTC3198	SI-N	60V	0.15A	0.4W	130MHz
KTC9012	SI-P	30V	0.5A	0.625W	

KTC9013	SI-N	30V	0.5A	0.625W	
KTC9014	SI-N	50V	0.15A	0.625W	
KTC9015	SI-P	50V	0.15A	0.625W	
KTC9018	SI-N	30V	20mA	0.2W	500MHz
KTD1351	SI-N	60V	3A	30W	3MHz
LM394CH	SUPERMATCH	TRANS.PR.			
LM394H	SUPERMATCH	TRANS.PR.			
LM395T	BLOWOUT	RESIST.	TRANSISTO		
M54661P	4xTRANS.ARRAY+DIOD	1.5A			
MAT02FH	2xSI-N	40V	20mA	0.5W	450MHz
MGF1302	N-FET	6V	0.1A	0.3W	4GHz
MJ10001	N-DARL+D	500V	20A	175W	B>
MJ10005	N-DARL+D	500/400V	20A	175	
MJ1001	N-DARL	80V	8A	90W	
MJ10012	N-DARL+D	600V	10A	175W	
MJ10016	N-DARL+D	500V	50A	250W	1us
MJ11015	P-DARL	120V	30A	200W	
MJ11016	N-DARL	120V	30A	200W	
MJ11032	N-DARL	120V	50A	300W	
MJ11033	P-DARL	120V	50A	300W	
MJ15003	SI-N	140V	20A	250W	3MHz
MJ15004	SI-P	140V	20A	250W	3MHz
MJ15015	SI-N	120V	15A	180W	0.8MHz
MJ15016	SI-P	120V	15A	180W	0.8MHz
MJ15022	SI-N	350/200V	16A	250W	
MJ15023	SI-P	350V	16A	250W	4MHz
MJ15024	SI-N	250V	16A	250W	
MJ15025	SI-P	400V	16A	250W	4MHz
MJ16018	SI-N	1500V	10A	175W	
MJ2501	P-DARL	80V	10A	150W	
MJ2955	SI-P	100V	15A	150W	4MHz
MJ3001	N-DARL	80V	10A	150W	
MJ4032	P-DARL	100V	10A	150W	
MJ4035	N-DARL	100V	16A	150W	
MJ413	SI-N	400V	10A	125W	> 2.5MHz
MJ4502	SI-P	100V	30A	200W	
MJ802	SI-N	90V	30A	200W	
MJE13004	SI-N	300V	4A	75W	TO220
MJE13005	SI-N	300V	8A	75W	
MJE13005	SI-N	300V	8A	75W	
MJE13007	SI-N	400V	8A	80W	
MJE13009	SI-N	400V	12A	100W	
MJE15030	SI-N	150V	8A	50W	30MHz
MJE15031	SI-P	150V	8A	50W	30MHz
MJE18004	SI-N	450V	5A	100W	13MHz
MJE18006	SI-N	450V	6A	100W	14MHz
MJE18008	SI-N	450V	8A	125W	0.3US
MJE210	SI-P	40V	5A	15W	>65MHz
MJE243	SI-N	100V	4A	15W	>40MHz
MJE253	SI-P	100V	4A	15W	>40MHz
MJE270	N-DARL	100V	2A	15W	>16MHz
MJE271	P-DARL	100V	2A	15W	B>1K5
MJE2955T	SI-P	70V	10A	90W	AFPOWER
MJE3055T	SI-N	70V	10A	90W	AFPOW.
MJE340	SI-N	300V	0.5A	20W	VIDPOW
MJE350	SI-P	300V	0.5A	20W	VIDPOW
MJE5850	SI-P	350/300V	8A	80W	
MJE800	N-DARL+D	60V	4A	40W	B>750
MJE8502	SI-N	700V	5A	80W	B>750
MJF18004	SI-N	450V	5A	35W	13MHz
MJF18008	SI-N	450V	8A	45W	0.3us
MJF18204	SI-N	600V	5A	35W	13MHz
MJW16018	SI-P	800V	10A	150W	3MHz
MJW16206	SI-N	1200V	12A	150W	3MHz
MJW16212	SI-N	650V	10A	150W	
MPF102	N-FET	25V	2mA	Up<8V	
MPS3640	SI-P	12V	80mA	635mW	500MHz
MPSA06	SI-N	80V	0.5A	0.625W	DRIV
MPSA10	SI-N	40V	0.1A	0.21W	50MHz
MPSA12	N-DARL	20V	0.5A	0.625W	
MPSA14	SI-N	30V	0.5A	0.625W	
MPSA18	SI-N	45V	0.2A	625mW	100MHz

MPSA42	SI-N	300V	0.5A	0.625W	
MPSA44	SI-N	500V	0.3A	625mW	20MHz
MPSA56	SI-P	80V	0.5A	0.625W	DRIV
MPSA70	SI-P	40V	0.1A	0.35W	>125MHz
MPSA92	SI-P	300V	0.5A	0.625W	
MPSH10	SI-N	25V	40mA	0.35W	650MHz
MRF237	SI-N	36V	0.6A	4W	174MHz
MRF455	SI-N	36V	15A	60W	30MHz
MRF475	SI-N	20V	4A	4W	50MHz
ON4359	N-DARL+D	120V	4A	40W	>10MHz
P6N60	N-FET	600V	6A	125W	1.00E+08
PH2222A	SI-N	75V	0.8A	0.5W	PLASTI
PH2369	SI-N	15V	0.5A	0.5W	12/18ns
PN2222A	SI-N	75V	0.8A	0.5W	PLASTI
PN2907	SI-P	40V	0.6A	0.4W	PLASTI
PN2907A	SI-P	60V	0.6A	0.4W	PLASTI
PN3563	SI-N	30V	50mA	0.2W	600MHz
PN3638	SI-P	25V	0.5A	0.625W	100MHz
R1004	SI-N	50V	0.1A		47K/47K
RFP40N10	N-FET	100V	40A	160W	0.04E
S175	RF	PWR	AMP		TRANSISTOR
S1854	DRIVER	STAGE	112.5/117.5V		
S2000AF	SI-N	1500V	8A	50W	0.7us
S2000N	SI-N	1500V	8A	50W	0.7us
S2055N	SI-N+D	1500V	8A	50W	0.3us
S2530A	SI-N	1000V	10A	100W	
SGSF313	SI-N	450V	7A	70W	0.3us
SGSF313XI	SI-N	1000V	5A	25W	0.3us
SGSF344	SI-N	600V	7A	85W	
SGSF445	SI-N	600V	7A	95W	
SGSF464	SI-N	600V	10A	140W	
SGSIF344	SI-N	600V	7A	35W	
SGSIF444	SI-N	600V	7A	55W	
SLA4061	N-DARL	120V	5A	25W	POWER
SLA4390	DARLINGTON	ARRAY			
SS8050	SI-N	40V	1.5A	1W	100MHz
SS8550	SI-P	40V	1.5A	1W	100MHz
SSM2210P	2xSI-N	40V	20mA	0.5W	200MHz
SSM2220P	2xSI-P	36V	20mA	0.5W	190MHz
STA301A	N-ARRAY	3x60V	4A		B>1K
STA341M	P/N-ARRAY	30V	1A		B>100
STA401A	N-ARRAY	4x60V	4A		B>1K
STA402A	P-ARRAY	4x50V	4A		B>1K
STA403A	N-ARRAY	4x100V	4A		B>1K
STA434A	P/N-ARRAY	2*60V	4A	20W	B>
STA441C	N-ARRAY	4x160V	1.5A		B>40
STA451C	P/N-ARRAY	2x60V	3A		B>40
STA471A	N-ARRAY	4x60V	2A		B>2K
STA8012	TRANSISTOR	ARRAY			
STA901M	TRANSISTOR	ARRAY			
STP3NA60	N-FET	600V	2.9A	80W	<4E
STP3NA60F	N-FET	600V	2.1A	40W	<4E
STP4NA60	N-FET	600V	4.3A	100W	<2E2
STP4NA60F	N-FET	600V	2.7A	40W	<2E2
STP4NA80	N-FET	800V	4A	110W	<3E
STP4NA80F	N-FET	800V	2.5A	45W	<3E
STW15NA50	N-FET	500V	14.6A	190W	0.0
SUP70N06-1	N-FET	60V	70A	142W	0.014E
THD200FI	SI-N	1500V	10A	60W	
TIP102	N-DARL	100V	8A	80W	
TIP107	P-DARL	100V	15A	80W	
TIP112	N-DARL	100V	2A	50W	
TIP117	P-DARL	100V	2A	50W	
TIP122	N-DARL	100V	5A	65W	
TIP127	P-DARL	100V	5A	65W	
TIP132	N-DARL	100V	8A	70W	
TIP137	P-DARL	100V	8A	70W	
TIP142	N-DARL	100V	10A	125W	
TIP142T	N-DARL	100V	10A	80W	
TIP147	P-DARL+D	100V	10A	125W	
TIP152	N-DARL+D	400/400V	7A	80W	
TIP162	N-DARL	380V	10A	3W	

TIP2955	SI-P	100V	15A	90W	NF/S-L
TIP29E	SI-N	180V	2A	30W	>3MHz
TIP3055	SI-N	100V	15A	90W	NF/S-L
TIP33C	SI-N	115V	10A	80W	
TIP34C	SI-P	100V	10A	80W	3MHz
TIP35C	SI-N	100V	25A	125W	3MHz
TIP36C	SI-P	100V	25A	125W	3MHz
TIP41C	SI-N	100V	6A	65W	3MHz
TIP42C	SI-P	140V	6A	65W	
TIP50	SI-N	400V	1A	40W	2us
TIP54	SI-N	500V	3A	100W	>2.5MHz
TIPL760	SI-N	850/400V	4A	75W	
TIPL760A	SI-N	100V	4A	80W	12MHz
TIPL761A	SI-N	1000V	4A	100W	
TIPL762A	SI-N	800V	6A	120W	POWER
TIPL763A	SI-N	1000V	8A	120W	8MHz
TIPL790A	SI-N	150V	10A	70W	10MHz
TIPL791A	SI-N	450V	4A	75W	
U440	2xN-FET	25V	30mA	0.35W	
UPA63H	2xN-FET	60V	Idss>20mA	0.5	
UPA81C	N-ARRAY	8x40V	0.4A		B>1K
VN10KM	N-FET	60V	0.31A	5E	Up<2.5
VN66AFD	N-FET	60V	2A	12W	3E Up<2.
VN88AFD	N-FET	80V	1.3A	20W	Up<2.5
ZTX213	SI-P	45V	0.2A	0.3W	350MHz
ZTX342	SI-N	120V	0.1A	0.3W	
ZTX450	SI-N	60V	1A	1W	150MHz
ZTX550	SI-P	60V	1A	1W	>150MHz
ZTX653	SI-N	120V	2A	1W	>140MHz
ZTX753	SI-P	120V	2A	1W	TO92
ZTX753M1TA	SI-P	120V	2A	1W	